
This is an electronic reprint of the original article.
This reprint may differ from the original in pagination and typographic detail.

Author(s): MacLeod, Sarah J. & Kafanov, Sergey & Pekola, Jukka
Title: Periodicity in Al/Ti superconducting single electron transistors
Year: 2009
Version: Final published version

Please cite the original version:

MacLeod, Sarah J. & Kafanov, Sergey & Pekola, Jukka. 2009. Periodicity in Al/Ti superconducting single electron transistors. Applied Physics Letters. Volume 95, Issue 5. P. 052503/1-3. ISSN 0003-6951 (printed). DOI: 10.1063/1.3194777.

Rights: © 2009 American Institute of Physics. This article may be downloaded for personal use only. Any other use requires prior permission of the author and the American Institute of Physics. The following article appeared in Applied Physics Letters and may be found at <http://scitation.aip.org/content/aip/journal/apl/95/5/10.1063/1.3194777>

All material supplied via Aaltodoc is protected by copyright and other intellectual property rights, and duplication or sale of all or part of any of the repository collections is not permitted, except that material may be duplicated by you for your research use or educational purposes in electronic or print form. You must obtain permission for any other use. Electronic or print copies may not be offered, whether for sale or otherwise to anyone who is not an authorised user.

Periodicity in Al/Ti superconducting single electron transistors

Sarah J. MacLeod, Sergey Kafanov, and Jukka P. Pekola

Citation: *Applied Physics Letters* **95**, 052503 (2009); doi: 10.1063/1.3194777

View online: <http://dx.doi.org/10.1063/1.3194777>

View Table of Contents: <http://scitation.aip.org/content/aip/journal/apl/95/5?ver=pdfcov>

Published by the AIP Publishing

Articles you may be interested in

[Probing quasiparticle excitations in a hybrid single electron transistor](#)

Appl. Phys. Lett. **100**, 262601 (2012); 10.1063/1.4730407

[Quasiparticle density of states measurements in clean superconducting AlMn alloys](#)

J. Appl. Phys. **107**, 093903 (2010); 10.1063/1.3369280

[Studies of Al-Ti Alloys by SEM](#)


AIP Conf. Proc. **899**, 669 (2007); 10.1063/1.2733410

[Single-charge devices with ultras-small Nb/Al O_x/Nb trilayer Josephson junctions](#)

J. Appl. Phys. **97**, 054501 (2005); 10.1063/1.1855399

[Radio-frequency-induced transport of Cooper pairs in superconducting single electron transistors in a dissipative environment](#)

J. Appl. Phys. **95**, 6325 (2004); 10.1063/1.1713024

The advertisement features a blue background on the left with the text 'CREATE your best design' in white and orange. On the right, there is a 3D simulation of a horn antenna with a color-coded field distribution. A control panel on the left lists parameters for a TE11 cutoff frequency simulation, including frequency, wavelength, flare angle, corrugation thickness, horn thickness, horn length, waveguide length, and matching corrugation length. The COMSOL logo is in the bottom right corner.

TE11 cutoff frequency (fc):	4.868 Hz
Frequency:	fc*1.2 Hz
Wavelength (λ):	0.5205 m
Flare angle:	17 °
Corrugation thickness:	0.105 m
Corrugation length:	0.155 m
Horn thickness:	0.5 m
Horn length:	4 m
Waveguide length:	1 m
Matching corrugation length:	0.25 m

Input waveguide cross pol. ratio: 17.657 %
Output aperture cross pol. ratio: 3.025 %
 Target criterion: passed

Periodicity in Al/Ti superconducting single electron transistors

Sarah J. MacLeod,^{1,a)} Sergey Kafanov,¹ and Jukka P. Pekola¹

¹Low Temperature Laboratory, Helsinki University of Technology, P.O. Box 3500, 02015 TKK, Espoo, Finland

(Received 10 June 2009; accepted 13 July 2009; published online 3 August 2009)

We present experiments on single Cooper-pair transistors made of two different superconducting materials. We chose Ti and Al to create an energy gap profile such that the island has a higher gap than the leads, thereby acting as a barrier to quasiparticle tunneling. Our transport measurements demonstrate that quasiparticle poisoning is suppressed in all our TiAlTi structures (higher gap for the island) with clear $2e$ periodicity observed, whereas full quasiparticle poisoning is observed in all AlTiAl devices (higher gap for the leads) with e periodicity. © 2009 American Institute of Physics. [DOI: 10.1063/1.3194777]

Superconducting single electron transistors (SSETs) consist of a superconducting island weakly coupled to two superconducting leads via low capacitance, high resistance Josephson junctions and a capacitive gate. The gate charge $Q_g = C_g V_g$, given by the gate capacitance C_g and applied voltage V_g , controls the number of electrons on the island. Thus current through the SSET is expected to peak every $2e$ in gate charge for bias voltages at which the Coulomb energy barrier for Cooper pairs is removed.^{1–4} This $2e$ -periodicity is a signature of current carried by Cooper pairs and not by single electrons [quasiparticles (QPs)]. It has been shown theoretically that electron transport in an SSET is dependent upon the parity of the total number of conduction electrons on the island.¹ Although $2e$ periodicity is expected, e periodic behavior is often observed in the experiment (see, e.g.).^{5,6} This is believed to be a consequence of nonequilibrium QPs, which exist even at low temperatures where thermal QPs would ideally vanish. One parameter which has been shown to affect QP tunneling on and off the SSET island is the relative difference between superconducting gaps of the leads and the island.⁷ If the island gap is made larger than the lead gap this will increase the QP energy on the island, which in turn favors $2e$ -periodicity at low temperatures. Previous studies have used Al–AlO_x–Al SSETs, where the difference in the gaps of the leads and the island has been achieved by flowing oxygen during the deposition of one of the Al layers⁸ or by varying the thickness of the Al layer.^{9–12}

An alternative to these works is to use two materials with naturally different superconducting gaps, such as aluminum and niobium. However such junctions suffered from large leakage current and QP poisoning.^{13–19} Previous research has also used Ta and Al to trap QPs in x-ray detection applications²⁰ and to study thermodynamic fluctuations.²¹ In the same spirit, here we have fabricated and measured the first SSETs from Al and Ti. These materials have a large difference in gaps ($\Delta_{\text{Ti}} \approx 200 \mu\text{eV}$, $\Delta_{\text{Al}} \approx 50 \mu\text{eV}$). We fabricated mirror devices on the same chip, comprising of AlTiAl and TiAlTi SSETs. Figure 1 shows a scanning electron micrograph of the mirror pair SSET device (b). The brighter areas are the evaporated Ti. The device on the right is a TiAlTi SSET and on the left is an AlTiAl SSET with the

measurement setup illustrated. Additionally, schematics of the gap profiles are shown inset. As Ti has a smaller gap than Al, the Ti island acts as a QP well in the AlTiAl device, hence this SSET should exhibit e periodicity. In contrast $2e$ periodicity is expected in the TiAlTi SSET as it is energetically unfavorable for a QP to tunnel onto and stay on the Al island.

The samples were fabricated by electron-beam lithography using the standard shadow deposition technique.²² Each mirror pair device was fabricated in one vacuum cycle. Measurements were made at temperatures from 50 mK up to about 300 mK. The source-drain current is measured as a function of voltage bias, V_b , and gate voltage, V_g which is plotted as a stability diagram for the three AlTiAl and TiAlTi SSET mirror pairs measured. The stability diagrams were measured using a two-probe, voltage-biased configuration. From these measurements we extracted the sample parameters as detailed in Table I, with pairs being denoted by the same subscript. Our samples typically had a series resistance of $R_N \sim 10\text{--}20 \text{ k}\Omega$ across the junctions and with Josephson energy $E_J \sim 30\text{--}50 \mu\text{eV}$. E_J was extracted using $E_J = (\hbar/2e)I_c$, where I_c is the critical current given by²³

$$I_c = \frac{2}{e(R_N/2)} \frac{\Delta_{\text{Ti}}\Delta_{\text{Al}}}{\Delta_{\text{Ti}} + \Delta_{\text{Al}}} K\left(\left|\frac{\Delta_{\text{Al}} - \Delta_{\text{Ti}}}{\Delta_{\text{Ti}} + \Delta_{\text{Al}}}\right|\right), \quad (1)$$

where R_N is the normal-state in series resistance given in Table I, $K(x)$ is an elliptic integral, and we assume $\Delta_{\text{Al}} \sim 5\Delta_{\text{Ti}}$ (see discussion which follows). The charging energy is roughly $E_c \sim 200 \mu\text{eV}$. We extracted E_c , as well as the sum of the Ti and Al gaps $\Delta_{\text{Ti}} + \Delta_{\text{Al}}$ from the stability diagrams by considering the energy requirements for different tunneling processes through the island. For a given tunneling




FIG. 1. Scanning electron micrograph of the mirror pair device (b), with the measurement set-up for the AlTiAl device drawn. Inset: a schematic of the gap profiles for the AlTiAl SSET (left) and TiAlTi SSET (right).

^{a)}Electronic mail: sarah.macleod@ltd.hut.fi.

TABLE I. Sample parameters of AlTiAl and TiAlTi SSETs. Here the sum of the Al and Ti gaps is given by $\Delta_{\text{Al}} + \Delta_{\text{Ti}}$, R_N is the normal-state resistance of the two junctions in series, E_c is the charging energy, E_J is the Josephson energy, D_i corresponds to the i th deposition, Ox gives the oxidation pressure and time, and P is the observed periodicity of the gate modulations.

Sample	$\Delta_{\text{Al}} + \Delta_{\text{Ti}}$ (μeV)	R_N (k Ω)	E_J (μeV)	E_c (μeV)	D_1 (nm)	Ox (mbar/min)	D_2 (nm)	P
AlTiAl _a	280	25.3	25.7	255	Al (20)	0.24/15	Ti (40)	e
TiAlTi _a	280	27.6	23.6	255	Al (20)	0.24/15	Ti (40)	$2e$
AlTiAl _b	250	12.7	45.7	250	Al (20)	0.11/10	Ti (30)	e
TiAlTi _b	250	13.8	42.1	210	Al (20)	0.11/10	Ti (30)	$2e$
AlTiAl _c	220	9.2	55.6	195	Al (20)	0.26/15	Ti (40)	e
TiAlTi _c	240	12.7	43.9	250	Al (20)	0.26/15	Ti (40)	$2e$

event, the bias voltage must supply sufficient energy in order to overcome the change in the charging energy $\Delta U = U(n \pm m) - U(n)$ caused by transferring m electrons on/off the island. Here the charging energy $U(n) = (Q_g - ne)^2 / 2C_\Sigma$ is determined by the number of excess electrons on the island n , induced gate charge Q_g , and the sum of the capacitances $C_\Sigma = C_1 + C_2 + C_g$, where C_i is the capacitance of the i th junction and C_g is the capacitance of the gate.

For $V_b > 0$ the condition at the i th junction to transfer a charge of m and with q QPs created is given by²⁴

$$m\kappa_i e V_b = U(n \pm m) - U(n) + q(\Delta_{\text{Ti}} + \Delta_{\text{Al}}) \\ = 2mE_c \left[(-1)^{i-1} \left(\frac{Q_g}{e} - n \right) + \frac{m}{2} \right] + q(\Delta_{\text{Ti}} + \Delta_{\text{Al}}). \quad (2)$$

Here $\kappa_i = 1 - (C_i + C_g/2) / C_\Sigma$ is the fraction of the bias voltage across junction i for $i = 1, 2$.

Figure 2(a) shows the condition for resonant Cooper pair tunneling given by the solid line ($m=2, q=0$) as well as the threshold above which QP tunneling is allowed given by the dotted line ($m=1, q=1$). Here lines with a positive (negative) slope are for tunneling processes which transfer a charge m off (on) the island through junction 1 (2). The bright spots around $V_b=0$, where the solid lines cross, are supercurrent features due to Cooper pair tunneling. The Josephson quasiparticle cycles are the diamondlike structures occurring for

$|V_b| > 0.5$ mV, along the resonant Cooper pair tunneling condition (solid line) and above the quasiparticle threshold (dotted lines). The three points of the ‘‘sawtooth’’ feature at odd values of V_g are due to $3e$ or a combination of $3e$ and QP tunneling processes. $3e$ tunneling is a higher-order process due to a Cooper pair tunneling on (off) the island while simultaneously a QP tunnels off (on), thereby effectively transferring a charge of e to (from) the island. The central apex of the sawtooth feature coincides with the intersection of opposite $3e$ tunneling conditions (dashed lines); hence this feature is believed to be due to a charge of e tunneling through the island by $3e$ processes. This is favorable when V_b satisfies²⁵

$$(m_1\kappa_1 + m_2\kappa_2)eV_b = U(n \pm \delta m) - U(n) + q(\Delta_{\text{Ti}} + \Delta_{\text{Al}}). \quad (3)$$

Here $\delta m = m_2 - m_1$ gives the charge transferred through the island by m_1 electrons tunneling off via junction 1 as m_2 electrons simultaneously tunnel on via junction 2. The two points on either side of the central apex occur along the $3e$ tunneling condition (dashed line) and above the QP threshold (dotted line). The right (left)-most feature (at $V_b > 0$) is due to a charge of e tunneling off (onto) the island via $3e$ tunneling followed by a QP tunneling event on (off) the island.

The TiAlTi SSET sample has a higher gap on the island [Fig. 2(a)], whereas the AlTiAl SSET has a higher gap for the leads, as shown in Fig. 2(b). Figure 2(a) has a clear $2e$ periodic structure for the TiAlTi SSET in the current around $V_b=0$, with slight quasiparticle poisoning (the spots occurring at $V_g = (2n+1)Q_g/e$ for integer n). This is highlighted in Fig. 2(c), which shows a cross section of Fig. 2(a) at constant V_b . Here small peaks in the current occur at odd values of V_g in addition to the main peaks at even values of V_g . In the AlTiAl SSETs [Fig. 2(b)] only e periodic gate modulations are observed. This is emphasized in Fig. 2(d), which shows e -periodic modulations with V_g at constant V_b .

Gate modulations of sample TiAlTi_c at different bath temperatures are shown in Fig. 3(a), with the transition from $2e$ to e with increasing temperature due to an increase in the concentration of thermal QPs.² In Fig. 3(b) we estimate the energy gaps of Ti and Al to differ by a factor of ~ 5 by measuring a TiAlTi SSET which was not fabricated into a mirror pair. It had an in series normal resistance of $R_N = 52$ k Ω , periodicity, $P = 2e$, and an Al island of thickness 30 nm and Ti leads of thickness 25 nm. The bath was heated until the gate modulations were suppressed. We plot the amplitude of the gate modulations in I versus temperature at a




FIG. 2. (Color online) (a) Stability diagram of TiAlTi_a on the plane of bias V_b and normalized gate voltage Q_g/e . To emphasize the observed current features we plot $\log|I|$; the white (dark) areas correspond to higher (lower) current with a range of $|I| = 100$ pA. We modeled the voltage conditions for Cooper pair tunneling (solid line), QP tunneling (dotted line) and $3e$ tunneling (dashed line). (b) Stability diagram of AlTiAl_c with I given in arbitrary units, again lighter areas correspond to higher current. (c) Cross section of (a) at constant bias voltage, $V_b = 0.06$ mV. (d) Cross section of (b) at constant bias voltage, $V_b = 0.06$ mV.




FIG. 3. (Color online) (a) Gate modulations in I vs gate voltage for TiAlTi_c with increasing temperature. Curves are vertically offset by 0.5 nA for clarity. Each temperature measurement was performed separately; therefore curves were horizontally aligned to account for charge jumps. (b) Amplitude of the gate modulation in I vs temperature for a TiAlTi SSET fabricated to extract the T_c of Ti.

small constant bias voltage. We fit a straight line to the data and the intersection point where the gate modulations tend to zero gives an estimate of the critical temperature of Ti, $T_c^{\text{Ti}} \approx 290$ mK. Using the relation $\Delta(0) \approx 1.76k_B T_c$ (Ref. 26) we extract $\Delta_{\text{Ti}} = 41 \mu\text{eV}$ at $T=0$ K. This indicates the gap of Ti is roughly five times smaller than that of Al.

In summary, we have exploited the large difference between the superconducting gaps of Ti and Al to suppress QP poisoning in SSETs. We have measured the gate modulation of our SSETs, in which $2e$ periodicity was observed in all the samples where the gap was larger on the island than in the leads. In contrast, e periodicity was observed in all the SSETs with an opposite gap profile. Our observations demonstrate that Ti and Al can be used to control the gap profile of SSETs to suppress QP poisoning.

We thank Tommy Holmqvist for assistance in sample fabrication, as well as Yuri Pashkin, Juha Leppäkangas, and Erkki Thuneberg for useful discussions. This work is partially supported by the European Community's Seventh Framework Program under Grant Agreement No. 218783 (SCOPE).

- ¹D. V. Averin and Yu. V. Nazarov, *Phys. Rev. Lett.* **69**, 1993 (1992).
- ²M. Tuominen, J. Hergenrother, T. Tighe, and M. Tinkham, *Phys. Rev. Lett.* **69**, 1997 (1992); M. T. Tuominen, J. M. Hergenrother, T. S. Tighe, and M. Tinkham, *Physica B* **194**, 1061 (1994).
- ³T. M. Eiles, J. M. Martinis, and M. H. Devoret, *Phys. Rev. Lett.* **70**, 1862 (1993).
- ⁴A. Amar, D. Song, C. J. Lobb, and F. C. Wellstood, *Phys. Rev. Lett.* **72**, 3234 (1994).
- ⁵T. Eiles and J. Martinis, *Phys. Rev. B* **50**, 627 (1994).
- ⁶C. H. van der Wal, Ph.D. thesis, Delft University of Technology, 2001.
- ⁷C. Chi and J. Clarke, *Phys. Rev. B* **20**, 4465 (1979).
- ⁸J. Aumentado, M. Keller, J. Martinis, and M. Devoret, *Phys. Rev. Lett.* **92**, 066802 (2004).
- ⁹T. Yamamoto, Y. Nakamura, Y. Pashkin, O. Astafiev, and J. Tsai, *Appl. Phys. Lett.* **88**, 212509 (2006).
- ¹⁰N. Court, A. Ferguson, and R. Clark, *Supercond. Sci. Technol.* **21**, 015013 (2008).
- ¹¹N. Court, A. Ferguson, R. Lutchyn, and R. Clark, *Phys. Rev. B* **77**, 100501 (2008).
- ¹²A. Ferguson, *Appl. Phys. Lett.* **93**, 052501 (2008).
- ¹³A. Savin, M. Meschke, J. Pekola, Y. Pashkin, T. Li, H. Im, and J. Tsai, *Appl. Phys. Lett.* **91**, 063512 (2007).
- ¹⁴H. Im, Y. Pashkin, T. Yamamoto, O. Astafiev, Y. Nakamura, and J. Tsai, *Appl. Phys. Lett.* **88**, 112113 (2006).
- ¹⁵R. Dolata, H. Scherer, A. Zorin, and J. Niemeyer, *J. Appl. Phys.* **97**, 054501 (2005).
- ¹⁶M. Watanabe, Y. Nakamura, and J. Tsai, *Appl. Phys. Lett.* **84**, 410 (2004).
- ¹⁷N. Kim, K. Hansen, S. Paraoanu, and J. Pekola, *Physica B* **329**, 1519 (2003).
- ¹⁸R. Dolata, H. Scherer, A. Zorin, and J. Niemeyer, *J. Vac. Sci. Technol. B* **21**, 775 (2003).
- ¹⁹Y. Harada, D. Haviland, P. Delsing, C. Chen, and T. Claeson, *Appl. Phys. Lett.* **65**, 636 (1994).
- ²⁰M. Gaidis, S. Friedrich, D. Prober, S. Moseley, and A. Szymkowiak, *IEEE Trans. Appl. Supercond.* **3**, 2088 (1993).
- ²¹C. Wilson, L. Frunzio, and D. Prober, *Phys. Rev. Lett.* **87**, 067004 (2001).
- ²²G. Dolan, *Appl. Phys. Lett.* **31**, 337 (1977).
- ²³A. Barone and G. Paterno, *Physics and Applications of the Josephson Effect* (Wiley, New York, 1982).
- ²⁴R. Fitzgerald, S. Pohlen, and M. Tinkham, *Phys. Rev. B* **57**, R11073 (1998).
- ²⁵S. L. Pohlen, Ph.D. thesis, Harvard University, 1999.
- ²⁶M. Tinkham, *Introduction to Superconductivity*, 2nd ed. (Dover, New York, 1996).