Design of millimetre-wave antennas on LTCC and PCB technologies for beam-steering applications

Antti Lamminen

Design of millimetre-wave antennas on LTCC and PCB technologies for beam-steering applications

Antti Lamminen

A doctoral dissertation completed for the degree of Doctor of Science (Technology) to be defended, with the permission of the Aalto University School of Electrical Engineering, at a public examination held at the lecture hall TU1, TUAS building, Maarintie 8 on 15 November 2019 at 12.

Aalto University
School of Electrical Engineering
Department of Electronics and Nanoengineering

Supervising professor

Asst. Prof. Zachary Taylor, Aalto University, Finland

Thesis advisors

Emer. Prof. Antti Räisänen, Aalto University, Finland

Dr. Jussi Säily, VTT Technical Research Centre of Finland Ltd, Finland

Preliminary examiners

Prof. Jian Yang, Chalmers University of Technology, Sweden

Assoc. Prof. Jorge R. Costa, Instituto Universitário de Lisboa, Portugal

Opponent

Emer. Prof. Juan R. Mosig, École polytechnique fédérale de Lausanne, Switzerland

Aalto University publication series

DOCTORAL DISSERTATIONS 194/2019

© 2019 Antti Lamminen

ISBN 978-952-60-8778-8 (printed)

ISBN 978-952-60-8779-5 (pdf)

ISSN 1799-4934 (printed)

ISSN 1799-4942 (pdf)

<http://urn.fi/URN:ISBN:978-952-60-8779-5>

Unigrafia Oy

Helsinki 2019

Finland

Author

Antti Lamminen

Name of the doctoral dissertation

Design of millimetre-wave antennas on LTCC and PCB technologies for beam-steering applications

Publisher School of Electrical Engineering

Unit Department of Electronics and Nanoengineering

Series Aalto University publication series DOCTORAL DISSERTATIONS 194/2019

Field of research Radio Engineering

Manuscript submitted 3 June 2019

Date of the defence 15 November 2019

Permission for public defence granted (date) 1 October 2019

Language English

☐ **Monograph**

☒ **Article dissertation**

☐ **Essay dissertation**

Abstract

An increasing need for wider bandwidths and higher data rates makes the use of millimetre-wave frequencies (30–300 GHz) attractive for the wireless communications applications. At millimetre-wave frequencies, directive antennas with a moderate or high antenna gain are usually needed to compensate for a high free-space path loss. Directive antennas have a narrow radiation beam and therefore beam steering is required to cover a wide angular range. Other requirements for the millimetre-wave antennas are, for example, a small form factor and integrability with the radio frequency (RF) front ends.

The objective of this thesis is to develop practical millimetre-wave antenna solutions for 60–110 GHz frequencies using low-cost manufacturing technologies, such as low temperature co-fired ceramic (LTCC) and printed circuit board (PCB). Investigations are done to improve the antenna performance, such as to increase the antenna gain and the operational bandwidth, and to suppress the mutual coupling between antennas. In addition to fixed-beam antennas radiating broadside or end-fire radiation beams, three beam-steering antenna demonstrators are also developed.

The performance of 60 GHz patch antennas and arrays on LTCC is improved by processing air cavities inside substrate to increase antenna gain and operational bandwidth. A 60 GHz uniplanar-compact electromagnetic band-gap (UC-EBG) structure is implemented on LTCC to increase the antenna gain and reduce the mutual coupling between antennas. A dual-resonant patch antenna and a 16-element array are designed for wideband performance at W-band (75–110 GHz). To reduce the feed network losses, a 60 GHz chain antenna array with a substrate-integrated (SIW) feed network is designed on LTCC.

A surface-wave assisted 60 GHz dipole and an array are designed on LTCC for end-fire radiation. A high-gain beam-switching dipole is presented for 77 GHz. A 90 GHz phased-array transmitter on LTCC is developed for providing beam steering over $\pm 25^\circ$. A beam-switching dual-spherical lens antenna system is presented for the E-band (71–76 GHz). The lens has a beam-switching array with 16 Vivaldi antennas on a multilayer PCB as a feed. Beam steering between $\pm 40^\circ$ is demonstrated in one dimension.

Keywords antenna, lens, millimetre wave, phased array

ISBN (printed) 978-952-60-8778-8

ISBN (pdf) 978-952-60-8779-5

ISSN (printed) 1799-4934

ISSN (pdf) 1799-4942

Location of publisher Helsinki

Location of printing Helsinki **Year** 2019

Pages 149

urn <http://urn.fi/URN:ISBN:978-952-60-8779-5>

Tekijä

Antti Lamminen

Väitöskirjan nimi

Millimetriaaltoantennien suunnittelu ja toteutus LTCC- ja PCB-tekniikoilla keilankääntösovelluksiin

Julkaisija Sähkötekniikan korkeakoulu**Yksikkö** Elektroniikan ja nanotekniikan laitos**Sarja** Aalto University publication series DOCTORAL DISSERTATIONS 194/2019**Tutkimusala** Radiotekniikka**Käsikirjoituksen pvm** 03.06.2019**Väitöspäivä** 15.11.2019**Väittelyluvan myöntämispäivä** 01.10.2019**Kieli** Englanti☐ **Monografia**☒ **Artikkeliväitöskirja**☐ **Esseeväitöskirja****Tiivistelmä**

Kaistanleveyden ja datanopeuksien kasvava tarve lisää kiinnostusta millimetriaaltoaajuuksien (30–300 GHz) hyödyntämiseen langattomissa tiedonsiirtosovelluksissa. Millimetriaaltoaajuuksilla tarvitaan yleensä suuntaavia antennoja, joilla on keskisuuri tai suuri antennivahvistus, kompensoimaan voimakasta vapaan tilan vaimennusta. Suuntaavilla antennilla on kapea säteilykeila ja täten keilanohtausta tarvitaan laajan kulma-alueen kattamiseksi. Muita vaatimuksia millimetriaaltoantenneille ovat mm. pieni koko ja integroitavuus radiotaajuusalueiden kanssa.

Tämän väitöskirjan tavoitteena on kehittää käytännöllisiä millimetriaaltoantenniratkaisuja 60–110 GHz taajuuksille käyttäen kustannustehokkaita valmistusmenetelmiä, kuten monikerroskeraami- (LTCC) ja piirilevytekniikkaa (PCB). Työssä tutkitaan menetelmiä antennin suorituskyvyn parantamiseen, kuten antennivahvistuksen ja kaistanleveyden kasvattamiseen, sekä antennien välisen keskinäiskytkennän pienentämiseen. Kiinteäkeilaisten rintama- ja päätysäteilijäantennien lisäksi työssä kehitetään kolme keilaohjattavaa antenniprototyyppiä.

60 GHz taajuudella toimivien LTCC-mikroliuska-antennien ja antenniryhmien suorituskykyä parannetaan prosessoimalla ilmaonteloita antennialustan sisään antennivahvistuksen ja kaistanleveyden kasvattamiseksi. Myös impedanssipintarakennetta (UC-EBG) käytetään 60 GHz:n LTCC-antennien ja antenniryhmien antennivahvistuksen kasvattamiseen sekä keskinäiskytkennän pienentämiseen. Kaksoisresonanssi -tyyppinen antenni ja 16-elementtinen ryhmä suunnitellaan toimimaan laajalla taajuuskaistalla W-alueella (75–110 GHz). Antenniryhmän syöttöverkon häviöiden pienentämiseksi suunnitellaan 60 GHz:n ketjuantenniryhmä, jossa syöttöverkko toteutetaan LTCC-alustaan integroitujen aaltoputkien (SIW) avulla.

Päätysäteilijäksi suunnitellaan pinta-aaltoavusteinen 60 GHz:n dipoli ja -ryhmä LTCC:lle. Korkeavahvistuksinen keilakytkettävä dipoli esitetään 77 GHz taajuudelle. 90 GHz:n vaiheohjattu lähetinantenniryhmä toteutetaan LTCC:llä. Ryhmän säteilykeilaa voidaan ohjata $\pm 25^\circ$ kulma-alueella. Keilakytkettävä kaksoispuolipallo -linssi antenni esitetään E-alueella (71–76 GHz). Linssiä syötetään 16:lla Vivaldi-antennilla, jotka on valmistettu monikerrospiirilevyille. Säteilykeila voidaan kytkeä 16 eri suuntaan $\pm 40^\circ$ kulma-alueella yhdessä tasossa.

Avainsanat antenni, linssi, millimetriaalto, vaiheohjattu ryhmä**ISBN (painettu)** 978-952-60-8778-8**ISBN (pdf)** 978-952-60-8779-5**ISSN (painettu)** 1799-4934**ISSN (pdf)** 1799-4942**Julkaisupaikka** Helsinki**Painopaikka** Helsinki**Vuosi** 2019**Sivumäärä** 149**urn** <http://urn.fi/URN:ISBN:978-952-60-8779-5>

Preface

The research work for this thesis was carried out in the Antennas and RF Technology team at VTT Technical Research Centre of Finland Ltd during years 2006–2019. The work was mostly funded by the Business Finland (Tekes) through the projects TAFE, BRAWE, BEAMS, and 5WAVE.

I would like to thank my managers Pekka Rantakari, Tauno Vähä-Heikkilä, and especially Jouko Aurinsalo for giving me an opportunity to work in interesting projects in the field of millimetre-wave technology. I also thank Pertti Järvensivu for providing a framework for the research work as a project manager.

I wish to thank my advisor Emer. Prof. Antti Räisänen and supervisor Asst. Prof. Zachary Taylor for the opportunity to carry out my doctoral studies at Aalto University. I would like to thank the co-authors of the publications for making this thesis possible. Many thanks to Ali Vahdati, Sabin Karki, Aki Karttunen, Juha Ala-Laurinaho, and Assoc. Prof. Ville Viikari for fruitful cooperation. I want to thank the pre-examiners Prof. Jian Yang and Assoc. Prof. Jorge R. Costa for the valuable comments and suggestions. I also wish to thank Emer. Prof. Juan R. Mosig for agreeing to act as the opponent in the defense.

Special thanks go to Jussi Säily for mentoring and encouragement during years. Thanks also to Manu Lahdes, Mikko Kaunisto, Tommi Dufva, Markku Lahti, Kari Kautio, and Antti Vimpari for inspiring cooperation. I also thank the LTCC processing staff at VTT for the realisation of high quality prototypes. I am grateful to the technicians for the assembly work, and Hannu Hakojärvi and Ismo Huhtinen for performing the measurements with strong expertise. Many thanks also to other colleagues at VTT.

I thank my family for the support during years and my friends for the fun times we share in recreational activities.

Helsinki, October 6, 2019,

Antti Lamminen

Contents

Preface	1
Contents	3
List of Publications	5
Author's Contribution	7
List of Figures	9
List of Abbreviations	11
List of Symbols	13
1. Introduction	15
2. Background	21
2.1 General overview of beam-steering antennas	21
2.2 State of the art of millimetre-wave beam-steering antennas . .	26
2.2.1 Phased arrays	26
2.2.2 Beam-switching lens antennas	29
3. Manufacturing technologies	31
3.1 Low temperature co-fired ceramic	31
3.2 Printed circuit board	32
3.3 Other platforms	33
4. Planar antenna designs on LTCC	35
4.1 Antennas for broadside radiation	35
4.1.1 60 GHz patch antennas and arrays with cavities . . .	35
4.1.2 60 GHz electromagnetic band-gap structure	39
4.1.3 W-band dual-resonant patch antenna array	41
4.1.4 60 GHz chain antenna array	42
4.2 Antennas for end-fire radiation	45

4.2.1	60 GHz surface-wave assisted dipole and array	45
4.3	Comparison of the planar antennas	47
5.	Switchable beam antenna systems	49
5.1	77 GHz beam-switching high-gain dipole	49
5.2	90 GHz phased antenna array transmitter	50
5.3	71–76 GHz beam-switching dual-spherical lens antenna	56
5.4	Comparison of the switchable beam antenna systems	59
6.	Summary of publications	61
7.	Conclusions	65
	References	67
	Publications	73

List of Publications

This thesis consists of an overview and of the following publications which are referred to in the text by their Roman numerals.

- I** A. E. I. Lamminen, J. Säily, and A. R. Vimpari. 60-GHz patch antennas and arrays on LTCC with embedded-cavity substrates. *IEEE Transactions on Antennas and Propagation*, vol. 56, no. 9, 2865–2874, Sep. 2008.
- II** A. E. I. Lamminen, A. R. Vimpari and J. Säily. UC-EBG on LTCC for 60-GHz frequency band antenna applications. *IEEE Transactions on Antennas and Propagation*, vol. 57, no. 10, 2904–2912, Oct. 2009.
- III** A. Vahdati, A. Lamminen, M. Varonen, J. Säily, M. Lahti, K. Kautio, M. Lahdes, D. Parveg, D. Karaca and K. A. I. Halonen. 90 GHz CMOS phased-array transmitter integrated on LTCC. *IEEE Transactions on Antennas and Propagation*, vol. 65, no. 12, 6363–6371, Dec. 2017.
- IV** A. E. I. Lamminen, S. K. Karki, A. Karttunen, M. Kaunisto, J. Säily, M. Lahdes, J. Ala-Laurinaho and V. Viikari. Beam-switching dual-spherical lens antenna with low scan loss at 71–76 GHz. *IEEE Antennas and Wireless Propagation Letters*, vol. 17, no. 10, 1871–1875, Oct. 2018.
- V** A. Lamminen and J. Säily. Wideband millimetre wave end-fire antenna and array for wireless short-range applications. In *Proc. 4th European Conference on Antennas and Propagation (EuCAP 2010)*, Barcelona, Spain, pp. 1–5, Apr. 2010.
- VI** A. Lamminen and J. Säily. 77 GHz beam-switching high-gain end-fire antenna on LTCC. In *Proc. 20th International Conference on Applied Electromagnetics and Communications (ICECom 2010)*, Dubrovnik, Croatia, pp. 1–4, Sep. 2010.

VII A. Lamminen and J. Säily. Wideband stacked patch antenna array on LTCC for W-band. In *Proc. 5th European Conference on Antennas and Propagation (EuCAP 2011)*, Rome, Italy, pp. 2962–2966, Apr. 2011.

VIII A. Lamminen and J. Säily. High gain 60 GHz LTCC chain antenna array with substrate integrated waveguide feed network. In *Proc. 6th European Conference on Antennas and Propagation (EuCAP 2012)*, Prague, Czech Republic, pp. 2569–2573, Mar. 2012.

Author's Contribution

Publication I: “60-GHz patch antennas and arrays on LTCC with embedded-cavity substrates”

This publication is the result of collaborative work. The author implemented an air cavity design inside LTCC substrate to improve the 60 GHz antenna performance. The author implemented a Wilkinson power divider design on LTCC to improve the array feeding network performance. The author designed the antennas, the antenna arrays, and the feeding networks. The author was responsible for writing the manuscript.

Publication II: “UC-EBG on LTCC for 60-GHz frequency band antenna applications”

This publication is the result of collaborative work. The author implemented an uniplanar compact electromagnetic bandgap (UC-EBG) design on LTCC to improve the 60 GHz antenna performance. The author was responsible for writing the manuscript.

Publication III: “90 GHz CMOS phased-array transmitter integrated on LTCC”

This publication is the result of collaborative work. The author implemented a 90 GHz cavity resonator antenna design to increase antenna gain. The author designed the antenna array, the waveguide transition, and the power division network on LTCC. The author proposed the method of integration of LTCC with the printed circuit board. The author assisted in the radiation pattern measurements. For writing the manuscript, the author contributed writing Section IIA and partly Sections III and IV.

Publication IV: “Beam-switching dual-spherical lens antenna with low scan loss at 71–76 GHz”

This publication is the result of collaborative work. The author designed the feeding antennas and the matching networks for the SP4T switches. The author performed the full-wave simulations of the lens system. For writing the manuscript, the author contributed writing Sections IIB–C and IIIA.

Publication V: “Wideband millimetre wave end-fire antenna and array for wireless short-range applications”

This publication is the result of collaborative work. The author designed the 60 GHz antenna and the antenna array. The author found the method for antenna gain improvement. The author was responsible for writing the manuscript.

Publication VI: “77 GHz beam-switching high-gain end-fire antenna on LTCC”

This publication is the result of collaborative work. The author designed the gain-increased beam-switching end-fire antenna for 77 GHz. The author was responsible for writing the manuscript.

Publication VII: “Wideband stacked patch antenna array on LTCC for W-band”

This publication is the result of collaborative work. The author implemented the dual-resonant antenna design for the W-band. The author designed the antenna array. The author was responsible for writing the manuscript.

Publication VIII: “High gain 60 GHz LTCC chain antenna array with substrate integrated waveguide feed network”

This publication is the result of collaborative work. The author designed the antenna array and the waveguide transition. The author was responsible for writing the manuscript.

Language check

The language of my dissertation has been checked by Assistant Professor Zachary Taylor. This has not affected the scientific content of my dissertation.

List of Figures

1.1	Illustrations of antenna-in-package systems	16
1.2	Directivity and beamwidth of a square antenna aperture	17
2.1	Radio link	21
2.2	Linear and planar antenna arrays	22
2.3	Beam-steering principle of a phased array	24
2.4	Beam-steering integrated lens antenna	26
3.1	Examples of LTCC and PCB build ups	33
4.1	Geometries of the 60 GHz ACMPAs	36
4.2	Variation of the substrate sizes of the ACMPAs	37
4.3	Simulated gain patterns of the 60 GHz ACMPA without and with cavity	38
4.4	Photographs of the 60 GHz LTCC antenna arrays	38
4.5	Layouts of the ACMPAs with the UC-EBG	39
4.6	Photographs of the 60 GHz UC-EBG on LTCC	40
4.7	Radiation patterns of the 60 GHz antenna arrays with the UC-EBG	41
4.8	Equivalent circuit for a dual-resonant patch antenna	42
4.9	W-band stacked patch antenna array	43
4.10	Schematics of a chain antenna	44
4.11	Layout of the 60 GHz LTCC chain array	44
4.12	Photographs of the 60 GHz chain array on LTCC	45
4.13	60 GHz end-fire antenna and array on LTCC	46
5.1	77 GHz beam-switching end-fire antenna on LTCC	50
5.2	90 GHz phased-array element on LTCC	51
5.3	Simulated radiation patterns of the 90 GHz phased-array ele- ment	52
5.4	90 GHz 1 × 4 phased array on LTCC	52

List of Figures

5.5	S-parameters of the 90 GHz back-to-back power distribution network	53
5.6	90 GHz phased array Tx on LTCC mounted on PCB	54
5.7	Beam steering with the 90 GHz phased array	55
5.8	Dual-spherical lens and Vivaldi feed antenna for E-band	57
5.9	Beam-switching network and Vivaldi antennas on PCB	58
5.10	Simulated directivity and antenna gain of the lens system . . .	58

List of Abbreviations

1D	One-dimensional
2D	Two-dimensional
5G	Fifth Generation
AC	Aperture-coupled
ACMPA	Aperture-coupled microstrip line-fed patch antenna
AiP	Antenna-in-package
AR	Aspect ratio
AuPt	Gold platinum
AWR	Applied Wave Research®
BCB	Benzocyclobutene
BGA	Ball grid array
BiCMOS	Bipolar-CMOS
CMOS	Complementary metal oxide semiconductor
CST	Computer Simulation Technology®
DC	Direct current
E-band	Frequency band 60–90 GHz
EIRP	Equivalent isotropic radiated power
EM	Electromagnetic
FR-4	Flame-retardant laminate material
GaAs	Gallium arsenide
Gbit	Gigabit, 10^9 bits
GB	Gigabyte, 10^9 bytes
GCPW	Grounded coplanar waveguide
GHz	10^9 Hz
GSG	Ground-signal-ground
GSMA	Global System for Mobile Communications

List of Abbreviations

HBT	Heterojunction bipolar transistor
HD	High-definition
HDI	High density interconnect
HFSS	High-Frequency Structure Simulator®
HPBW	Half-power beamwidth
IF	Intermediate frequency
IPD	Integrated passive devices
LCP	Liquid crystal polymer
LNA	Low-noise amplifier
LO	Local oscillator
LTCC	Low temperature co-fired ceramic
MMIC	Monolithic microwave integrated circuit
NiAu	Nickel-gold
PA	Power amplifier
PCB	Printed circuit board
PDMS	Polydimethylsiloxane
PRS	Partially reflective surface
PTFE	Polytetrafluoroethylene (Teflon)
QAM	Quadrature amplitude modulation
RF	Radio frequency
Rx	Receiver
Si	Silicon
SiGe	Silicon-germanium
SIW	Substrate integrated waveguide
SP4T	Single-pole four-throw
THz	10^{12} Hz
TRL	Thru-reflect-line
TRx	Transceiver
Tx	Transmitter
UC-EBG	Uniplanar compact electromagnetic bandgap
V-band	Frequency band 50–75 GHz
W-band	Frequency band 75–110 GHz
WiGig	Wireless Gigabit
WPAN	Wireless Personal Area Network
WR-10	Rectangular waveguide for W-band
WR-15	Rectangular waveguide for V-band

List of Symbols

A	Area of antenna aperture	[m ²]
a_i	Amplitude and phase factor of array element i	
c	Speed of light, $2.998 \cdot 10^8$	[m/s]
D	Directivity	[dB]
d	Array element spacing	[m]
$\mathbf{E}(\mathbf{r})$	Far field of antenna array	[V/m]
$\mathbf{E}_i(\mathbf{r})$	Far field of array element i	[V/m]
f	Frequency	[Hz]
$f(\mathbf{u}_r)$	Array factor	
G	Antenna gain	[dBi]
G_r	Receiving antenna gain	[dBi]
G_t	Transmitting antenna gain	[dBi]
i	Array element index	
j	Imaginary unit	
k	Wave number	[1/m]
l	Length of antenna aperture	[m]
M	Number of antenna elements in y -direction	
m	Array element index in y -direction	
N	Number of antenna elements in x -direction	
n	Array element index in x -direction	
p	Parameter for substrate size modification	[m]
P_r	Received power	[W]
P_t	Transmitted power	[W]
$\mathbf{r}_i$	Position vector of array element i	[m]
R_b	Radius of lens extension hemisphere	[m]
R_t	Radius of lens collimating hemisphere	[m]

List of Symbols

S	Scattering parameters	
s	Distance between transmitting and receiving antennas	[m]
$\tan \delta$	Dielectric loss tangent	
$\mathbf{u}_r$	Unit vector in r direction	
γ	Phase	[rad, °]
δ	Phase shift	[rad, °]
ϵ_r	Relative permittivity	
η	Efficiency	
θ	Elevation angle in spherical coordinates	[rad, °]
$\theta_{3\text{dB}}$	-3-dB beam width	[rad, °]
λ	Wavelength	[m]
λ_0	Free-space wavelength	[m]
σ	Electrical conductivity	[S/m]
σ_{Au}	Effective conductivity for gold paste	[S/m]
ϕ	Azimuth angle in spherical coordinates	[rad, °]
Ω	Ohm	

1. Introduction

During the past couple of decades, interest of using millimetre waves has turned away from the military sector towards commercial applications, such as millimetre-wave communications and automotive radar sensors [1]. In addition, passive millimetre-wave imaging has been developed for low visibility conditions and for security screening for detection of concealed weapons [2], [3]. Exploitation of millimetre-waves for wireless communications is mainly motivated by the increasing need for wider bandwidths and higher data rates, currently up to 1–10 Gbps, which are not available at the microwave frequency bands [4]. It has been shown that link distances of 200 m are feasible at 28 GHz or 38 GHz in urban environments when using steerable directional antennas at base stations and mobile devices [5]. For the 60 GHz frequency band, short-range applications are targeted, such as wireless high-definition (HD) video transmission and Wireless Personal Area Networks (WPAN) [4]. The 71–76 GHz, 81–86 GHz, and 92–95 GHz are referred as E-band and are used for point-to-point local area networks, mobile backhaul and broadband internet access [4]. In such applications, highly directive antennas are required for longer link ranges [6].

For the upcoming fifth generation (5G) wireless networks, 26 GHz, 28 GHz and 40 GHz frequency bands are the most likely candidates for the millimetre-wave bands [7]. The GSMA Association recommends also 50 GHz and 66 GHz bands for the 5G mobile networks [7]. Frequencies above 100 GHz are also interesting for the future generation (6G and beyond) wireless communications systems due to wide unexplored frequency spectrum [8].

The main objective of this work is the design and realisation of antennas and antenna arrays for millimetre-wave frequencies; in particular the 60–110 GHz frequency range for future wireless communications applications. Common requirements for such systems are: moderate or high antenna gain, beam steering capability, low manufacturing cost, small form factor, and integrability with radio frequency (RF) front ends, often called antenna-in-package (AiP) systems [9] (see Fig. 1.1). These requirements set some limitations to usable manufacturing technologies. In this work, the developed antennas are manufactured on low temperature co-fired ceramic substrates (LTCC) or on multilayer printed circuit boards (PCB).

Figure 1.1. Illustrations of antenna-in-package (AiP) systems. (a)–(b) Antennas are manufactured on low temperature co-fired ceramic (LTCC) substrate and monolithic microwave integrated circuit (MMIC) is assembled on LTCC by using flip-chip technique. LTCC is mounted on a carrier printed circuit board (PCB) by using ball grid array (BGA) solder balls or wire-bonding techniques. (c) Antennas are manufactured on PCB. Also the MMIC is flip-chipped on PCB. In this work, configurations (b) and (c) are utilised in Sections 5.2 and 5.3, respectively.

A planar millimetre-wave antenna may consist of a patch, a dipole, a slot, a tapered slot, a Yagi, or other type of antenna patterned on top of, or inside, a dielectric substrate. The substrate can be a single-layer type or may consist of multiple dielectric and conductive layers stacked and laminated together. Planar antennas have a small form factor, are integrable with active circuits and are suitable for mass production. However, there are some key questions with respect to millimetre-wave antenna performance such as: How to make an antenna radiate efficiently into the desired direction(s) while minimising radiation into the non-desired directions? Further, how to make the antenna perform efficiently in a wide frequency range? In this work, solutions are developed to address these questions.

Figure 1.2. (a) Square antenna array with side length l and area A . (b) Directivity and beamwidth for different frequencies and array sizes.

One way to overcome the high free-space path loss at millimetre-wave frequencies is to increase the transmitting and/or receiving antenna gain. The antenna gain is $G = \eta D$, in which η is efficiency and D is directivity [10]. So, to obtain high antenna gain, the directivity should be high and the losses of the antenna should be low. The losses commonly comprise of conductor and dielectric losses of the used substrate material. But losses may also arise from the feeding network components of beam-steering antennas. The maximum directivity of a planar antenna aperture with a uniform amplitude and phase illumination is $D_{\max} = 4\pi A/\lambda_0^2$ where A is aperture area and λ_0 is free-space wavelength [11]. For example, for $D_{\max} = 25$ dB at 75 GHz, $A = 0.0004$ m². For a square aperture this results in as an aperture size of 20 mm $\times$ 20 mm. The -3-dB beamwidth (in degrees) of the radiation pattern is $\theta_{3\text{dB}} = 50.8\lambda_0/l$ where l is the length of an array. For an aperture of size 20 mm $\times$ 20 mm, the $\theta_{3\text{dB}} \approx 10^\circ$ in the two principal planes at 75 GHz (see Fig. 1.2).

For integrated radio modules, the antenna apertures are usually implemented as antenna arrays having dipole, slot, patch or other type of antenna as an array element. A single antenna has a gain of about 3–7 dBi. Commonly used

element spacing in an array is between $0.5\lambda_0$ – $0.7\lambda_0$. The number of required antenna elements increase with the aperture size. For $D_{\max} = 25$ dB at 75 GHz and element spacing of $0.5\lambda_0$, the number of needed array elements would be $10 \times 10 = 100$ in total, in practise even higher. Naturally, the antenna gain is always smaller than the maximum aperture directivity due to losses in the antennas and feeding networks, and due to non-uniform amplitude and phase distribution in the antenna array.

To cover a wide angular range with a narrow radiation beam, a phased antenna array can be implemented. In a phased array, phase shifters are used to steer the main beam of the antenna array. Possible phase shifting configurations are RF phase shifting, LO phase shifting, IF phase shifting and digital beamforming [12]. The RF phase shifting is probably the most feasible for millimetre-wave applications due to the lowest power consumption and the smallest chip area [12]. However, also in the RF phase shifting configuration, a phase shifter is needed for each antenna element. This increases the complexity, losses and cost of a phased array, especially for large and highly-directive antenna arrays. For transceivers including moderate-gain antenna arrays, the system gain can be increased by means of free-space power combining technique, i.e., by placing a power amplifier (PA) or a low-noise amplifier (LNA) in addition to a phase shifter on each antenna path in the transceiver's transmitter (Tx) or receiver (Rx) chain.

All array antennas suffer from scan loss because the effective aperture of the antenna gets smaller when the beam is steered away from the boresight. Depending on the mutual distance between the array elements, the phased array may also suffer from grating lobes, i.e., multiple main beams when the beam is steered away from the boresight. This is illustrated in Chapter 2. In a phased array, an active phase shifter is needed for each antenna array element which leads to complex systems in large antenna arrays. In addition, the total power consumption is increased and heat dissipation may become an issue.

Instead of a phased array, a beam-switching antenna can be used where usually a lens or a reflector antenna is illuminated with a feeding antenna array. The idea is to have a large lens or reflector providing high antenna gain. The feeding antennas are switched “on” and “off”, one at a time using RF switches. Since only one feeding antenna is active at a time, the overall complexity and power consumption could be only a fraction of a phased array. Drawbacks are the switching network losses and complexity if high number of different beams are desired.

Several millimetre-wave antennas pointing towards different directions are needed, especially in a mobile device, to maximise the angular coverage [13]. In this work, antennas and antenna arrays radiating broadside or end-fire beams are designed for 60–110 GHz frequency range (see Fig. 1.1). Investigations are done to improve antenna performance such as to increase antenna gain or operational bandwidth and to suppress mutual coupling in antenna arrays. Three beam-steering antennas are developed: a 77 GHz beam-switching end-

fire antenna, a 90 GHz phased antenna array transmitter and a 71–76 GHz beam-switching dual-spherical lens antenna system. The developed antennas could be used for the future wireless communications applications in the user devices such as tablets or mobile phones. The lens antenna system is a potential candidate for the millimetre-wave access points.

The content of this thesis is as follows. A relevant theoretical background and the state-of-the art of beam-steerable millimetre-wave antennas are reviewed in Chapter 2. The applicable manufacturing technologies are introduced in Chapter 3. The planar antenna designs developed in this work are presented in Chapter 4. The switchable beam antenna systems are described in Chapter 5. The summary of publications is presented in Chapter 6. Finally, conclusions are drawn in Chapter 7.

2. Background

2.1 General overview of beam-steering antennas

The Friis transmission equation (2.1) describes the power transmission over a radio link [14] as illustrated in Fig. 2.1

$$P_r = G_t G_r \left(\frac{c}{4\pi s f} \right)^2 P_t. \quad (2.1)$$

It is seen that the received power P_r is inversely proportional to frequency f and distance s , c is the speed of light. The P_r also depends on the antenna gains of the receiving and transmitting antennas, G_r and G_t , and the transmitted power P_t . At millimetre-wave frequencies, P_t is usually limited. In order to have adequate P_r , G_r and/or G_t should be increased to compensate for an increasing f .

The radiation pattern of a single antenna element is typically wide (the -3 dB beamwidth $\sim 70^\circ$ for a microstrip antenna) and therefore the antenna gain is low. To increase the antenna gain, i.e., to focus the radiation more into a specific direction, the electrical size of the antenna must be increased. Another method is to place two or more antennas with similar characteristics in an array, where the antenna elements are in a particular geometrical formation. An array antenna is defined as “an antenna comprised of a number of identical radiating

Figure 2.1. Radio link between transmitting and receiving antennas.

Figure 2.2. Antenna arrays: a) a linear array and b) a planar array.

elements in a regular arrangement and excited to obtain a prescribed radiation pattern” [15]. Typical antenna array geometries are a linear and a planar array shown in Fig. 2.2.

Antenna array factor

The far-field of the antenna array element i located at $\mathbf{r}_i$ can be computed from the far field of the basic element, $\mathbf{E}_0(\mathbf{r})$, located at the origin as follows [14]

$$\mathbf{E}_i(\mathbf{r}) = a_i e^{jk\mathbf{u}_r \cdot \mathbf{r}_i} \mathbf{E}_0(\mathbf{r}). \quad (2.2)$$

So, only the far-field of the basic antenna element has to be calculated. The far-fields of other elements of the array differ from the basic element with phase and magnitude factors. Let us assume that there are N elements in an array, their amplitudes and phases are defined by complex factors $a_1, a_2, a_3, \dots, a_N$. The position vectors of the elements are $\mathbf{r}_1, \mathbf{r}_2, \mathbf{r}_3, \dots, \mathbf{r}_N$, respectively. The far-field of the array can be expressed as a sum

$$\mathbf{E}(\mathbf{r}) = \sum_{i=1}^N a_i e^{jk\mathbf{u}_r \cdot \mathbf{r}_i} \mathbf{E}_0(\mathbf{r}) = f(\mathbf{u}_r) \mathbf{E}_0(\mathbf{r}), \quad (2.3)$$

where $f(\mathbf{u}_r)$ is referred to as an array factor and it is independent of the characteristics of the elements. The far-field of an antenna array is a multiple of the array factor and the far-field of an individual element.

Array factor of a linear array

Often, a constant phase shift is used between adjacent array elements and the feeding of the elements is thus called progressive [14]. Usually, all the elements are fed with uniform current amplitudes, because it is simpler to use identical feeding circuits for the elements. Also the separation of the elements is usually kept constant, because of the lack of deterministic design methods for arrays

with unequal element spacing [14], thus $|\mathbf{r}_{i+1} - \mathbf{r}_i| = d = \text{constant}$.

Let us first consider a linear array of N elements where the elements are placed along the x -axis in the spherical coordinates (see Fig. 2.2a). The array factor can be expressed as [10]

$$f(\mathbf{u}_r) = \sum_{i=1}^N a_i e^{j(i-1)kd_x \sin \theta \cos \phi}, \quad (2.4)$$

where d_x is the element separation in the x -direction, $k = 2\pi/\lambda$ is a wave number and λ is wavelength. With a constant phase shift and equal feeding amplitudes the excitation factor of the element i can be written in a form

$$a_i = a e^{j(i-1)\delta_x}, \quad (2.5)$$

where a is real. The phase of the element i is $\delta_{ix} = (i-1)\delta_x$, where δ_x represents a constant phase shift. Equation (2.4) now yields

$$f(\gamma) = a \sum_{i=1}^N e^{j(i-1)(kd_x \sin \theta \cos \phi + \delta_x)} = a \sum_{i=1}^N (e^{j\gamma})^{(i-1)}, \quad (2.6)$$

where $\gamma = kd_x \sin \theta \cos \phi + \delta_x$. Equation (2.6) is a geometric serie and can be summed up in a closed form as

$$f(\gamma) = a \frac{e^{jN\gamma} - 1}{e^{j\gamma} - 1}, \quad (2.7)$$

which can be further simplified using complex properties of the sine function, $\sin \gamma = (e^{j\gamma} - e^{-j\gamma})/(2j)$:

$$f(\gamma) = a e^{j(N-1)\gamma/2} \frac{\sin(N\gamma/2)}{\sin(\gamma/2)}. \quad (2.8)$$

The maximum value of $\sin(N\gamma/2)/\sin(\gamma/2)$ is equal to N ($\gamma = 0$). If the feed amplitudes are normalised, i.e., $a = 1/N$, the absolute value of the array factor yields

$$|f(\gamma)| = \left| \frac{\sin(N\gamma/2)}{N \sin(\gamma/2)} \right|. \quad (2.9)$$

The direction of the major lobe is obtained when $\gamma = 0 \implies kd_x \sin \theta \cos \phi = -\delta_x$. For a linear array in the xz -plane, if the phase shift is $\delta_x = 0$, then $\theta = 0$ and $\theta = \pi$, and the array is called *broadside array*. For the *end-fire array*, $\delta_x = \pm kd_x$ and the major lobe is directed at $\theta = \pi/2$. With phase shifts between $-kd_x \leq \delta_x \leq kd_x$ the major lobe can be directed between angles $0 \leq \theta \leq \pi/2$. If only one major lobe is desired, one has to choose $kd_x = \pi \implies d = \lambda/2$.

Array factor of a planar array

A planar array, which can be thought as an array formed by the combination of several linear arrays (Fig. 2.2b), can be used to further increase the directivity and the antenna gain. Planar arrays provide more symmetrical patterns than

Figure 2.3. Array factor for a 4-element array with different phasing and element spacing of (a) $d = 0.5\lambda$ and (b) $d = 0.8\lambda$. Phase shifts are: 0° (solid line), -45° (dashed line), -90° (dotted line), -135° (dash-dot line). (c) Cosine-type element pattern and (d) resulting antenna array pattern with $d = 0.5\lambda$.

linear arrays. With a planar array the main beam of the antenna can be directed towards any point in space [10]. The rectangular array of $N \times M$ elements is formed by an M -element linear array consisting of N -element linear arrays. The array factor of a planar array is a multiplication of the array factors of the two linear arrays [10]

$$f(\gamma) = \sum_{n=1}^N a_n e^{j(n-1)kd_x \sin\theta \cos\phi + \delta_x} \sum_{m=1}^M a_m e^{j(m-1)kd_y \sin\theta \sin\phi + \delta_y}, \quad (2.10)$$

where the phase shifts δ_x and δ_y are constants but not necessarily equal. The absolute value of the array factor for the planar array can be written as

$$|f(\gamma)| = \left| \frac{\sin(N\gamma_x/2)}{N \sin(\gamma_x/2)} \frac{\sin(M\gamma_y/2)}{M \sin(\gamma_y/2)} \right|, \quad (2.11)$$

where $\gamma_x = kd_x \sin\theta \cos\phi + \delta_x$ and $\gamma_y = kd_y \sin\theta \sin\phi + \delta_y$.

The array factor with different phase shifts, a generic element pattern and resulting antenna array patterns for a 4-element array are illustrated in Fig. 2.3. It is observed that the array factor is symmetrical with respect to the horizontal axis. With $d = 0.5\lambda$ in Fig. 2.3a, only one major lobe is seen when steered from 0° to 45° . With $d = 0.8\lambda$ in Fig. 2.3b, the major lobe is narrower and more directive than in Fig. 2.3a but grating lobes, i.e., additional maximums appear when the beam is steered. Also the scan angles are smaller ($< 30^\circ$) than in Fig. 2.3a with the same phase shifts. An antenna element usually radiates into a hemisphere and back radiation is prevented by a ground plane. This is illustrated in Fig. 2.3c. As the element pattern is multiplied by the array factor, the pattern for the whole antenna array is also directed into a hemisphere as shown in Fig. 2.3d. Scan loss usually occurs when the beam is steered due to angular dependence of the element pattern which is seen as decreasing amplitude in Fig. 2.3d.

For some applications, antenna arrays need to conform to a shaped surface. If the aperture dimensions are much smaller than the radius of curvature, the array can be considered as locally planar with a limited field of view [11]. Large arrays conform to the surface and may be used to scan over a large sector. However, the analysis and synthesis of such arrays is significantly more complex than for a nearly planar or a conventional planar array [11]. At millimetre-wave frequencies, the arrays are physically small (around 2–4 cm, see Fig. 1.2) and can be usually considered as planar or locally planar.

Integrated lens antenna

Beam steering can be also achieved with an integrated lens antenna [16], [17], [18]. The collimating part of the lens can be, for example, elliptical or hemispherical. An elliptical lens can be approximated with an extended hemispherical lens [16]. A cylindrical extension is commonly used in which the feed antennas are placed on a planar extension surface (see Fig. 2.4). Beam steering occurs when the lens is fed with an offset from the rotational symmetry axis of the lens. The drawback of the cylindrical extension is the scan loss with large beam-steering angles [17].

The feed antennas can be also placed on a spherical surface instead of a cylindrical one. The hemispherical extension has the radius equal to the extension length and the scan loss is very small due to symmetry [18]. The collimating hemisphere and the extension hemisphere radii can be estimated as [19]

$$\frac{R_b}{R_t} = \frac{1}{\sqrt{2}} \frac{\epsilon_r}{\epsilon_r - 1}, \quad (2.12)$$

where R_b is the extension hemisphere radius, R_t is the collimating hemisphere radius, and ϵ_r is the relative permittivity of the lens material. For example, with $R_t = 26$ mm and $\epsilon_r = 2.1$ this leads to $R_b = 35$ mm. The detailed design is done using ray tracing and electromagnetic simulations.

Figure 2.4. Beam-steering integrated lens antenna. The lens has a hemispherical collimating part. The extension part can be cylindrical or hemispherical.

2.2 State of the art of millimetre-wave beam-steering antennas

In this section, recent publications relevant to antenna-in-package systems developed in this work are reviewed. The focus is on phased antenna arrays on LTCC and PCB and beam-switching lens antennas operating in the frequency range 60–110 GHz.

2.2.1 Phased arrays

A 60 GHz CMOS phased array having 12 patch antenna elements on LTCC was presented in [20]. Beam steering of 30° was verified with simulations and measurements. Kam et al. implemented 16-element phased patch antenna arrays on an LTCC package [21] and an organic package consisting of LCP and RO4000 materials [22] with phase shifters manufactured on 120 nm SiGe BiCMOS technology. Beam scanning of angles $\phi = -225^\circ, -135^\circ, -45^\circ$ ($\theta = 18^\circ$) was demonstrated in [22]. A four-element phased array using 65 nm CMOS technology was demonstrated at 60 GHz on LTCC by Kuo et al. in [23]. Beam scanning between $\pm 25^\circ$ was measured with cavity-backed rectangular slot loop antennas. Cohen et al. at Intel published a Tx/Rx fully integrated 32-element phased array at 60 GHz on a 90 nm CMOS [24]. The antenna module of size $25 \text{ mm} \times 25 \text{ mm}$ consisted of a 6×6 patch antenna array including four dummies on LTCC with the antenna gain of 19 dBi. Beam scanning between $\pm 30^\circ$ was achieved. A 60 GHz CMOS phased-array transceiver pair for multi-Gbit/s wireless communications was published in [25]. The transceiver was packaged with a 32-element antenna array. The transceiver pair supported the WirelessHD and WiGig standards at the maximum data rate of 7.14 Gbit/s and

6.76 Gbit/s.

A 77 GHz radar receiver phased array was published in [26]. The array had four patch antennas on a single Rogers 3003 PCB layer. Beam steering between $\pm 30^\circ$ was achieved with phase shifters manufactured using 130 nm SiGe HBT technology. A dual-polarisation 16-element phased array transceiver at W-band frequencies was shown in [27]. The array had 32 receive elements and 16 transmit elements and 16 dual-polarised antennas in a package. The transceiver was manufactured on a 130 nm SiGe BiCMOS process and had a size of 6.6 mm $\times$ 6.7 mm. A 16-element W-band dual-polarised phased array transceiver with wideband patch antennas on multilayer PCB was presented in [28]. The chipset was manufactured in 180 nm SiGe BiCMOS technology. Beam steering between $\pm 30^\circ$ was demonstrated. The transceiver provided the maximum wireless data rate of 30 Gbit/s at 1 m distance per polarisation using 64-QAM modulation. For 20 m distance, 8 Gbit/s was achieved for dual polarisation using QPSK modulation. A 94 GHz imaging radar with 4 $\times$ Tx and 4 $\times$ Rx phased arrays was demonstrated in [29]. The radar included patch antenna arrays on LTCC and had a $\pm 28^\circ$ scanning range. The antennas were in a 2 $\times$ 2 configuration whereas a 1 $\times$ 4 array is implemented in this work in Section 5.2 [III]. The antenna gains are about the same (13 dBi) but the $|S_{11}| < -10$ dB bandwidth for a single element was only 5 GHz in [29] and is 9 GHz in [III]. This is due to a thicker antenna substrate which is enabled by the via fences surrounding the patches.

Feasibility of wafer-scale integration of BiCMOS power amplifiers with an antenna array on quartz substrate was demonstrated at 94 GHz in [30]. A 3 $\times$ 3 amplifier array with size of 7.3 mm $\times$ 6 mm was implemented together with the feeding network. The quartz substrate with antennas was glued on top of the silicon wafer. The antenna directivity and gain were 15.5 dB and 12 dBi. The total on-chip power was 21–23 dBm and total radiated power was 17.5–19.5 dBm. At 60 GHz, wafer-scale transmit phased arrays with 64- and 256-elements were presented in [31]. The 64-element array was a complete reticle with a size of 21.4 mm $\times$ 22 mm and the measured equivalent isotropic radiated power (EIRP) of 38 dBm. The 256-element array was based on subreticle stitching technique of 64-element arrays and had a size of 41.4 mm $\times$ 42 mm with the EIRP of 45 dBm. A 1–4 Gbit/s communication system was demonstrated using the 64-element array up to $\pm 45^\circ$ scan angles, and over 4-, 30-, and 100-m distances.

The state-of-the-art AiP phased arrays are summarised in Table 2.1. It can be observed that the most common MMIC technologies are CMOS and SiGe BiCMOS. Antennas are often packaged using LTCC technology. In recent years, PCB implementations have also become popular. Different types of microstrip patch antennas are typically used as an array element. The number of elements vary from 4 even up to 384 in [32]. Traditional aperture-coupled patch antenna designs were implemented in [20], [24], [29], [33], [34] on PCB or LTCC substrates for 60 GHz or 94 GHz frequency bands. The main advantage of such design is that the antenna feed lines and the MMICs are separated from the radiating patches by a ground plane and interference with the antenna radiation

is minimised. Air cavities inside antenna substrates were implemented in [21], [22] and [23] to increase the bandwidth and the antenna gain. Very similar design is presented in this work in Section 4.1.1 [I]. In fact, [I] was cited in [20] and [22].

An aperture-stacked patch antenna was designed in [28] and [32] on PCB for medium gain and large bandwidth at W-band. A stacked patch antenna design is proposed on LTCC also in this work in Section 4.1.3 based on [VII], which was cited in [28]. Due to PCB process limitations, antenna element spacing in [32] was 0.63λ at 90 GHz which contributed to grating lobes in the array patterns. Those could be avoided by using LTCC since it enables smaller line and gap widths than the standard PCB process (see Chapter 3). The stacked patch arrays designed on PCB for the 60 GHz band in [35] had the -3-dB gain bandwidth from 9% to 13%, which was smaller than 23% presented in [VII].

A 1×4 dipole array was designed on Teflon substrate for the 60 GHz band in [36]. The substrate thickness was only $125 \mu\text{m}$ which may not be mechanically robust. A single antenna and a 1×4 dipole array design is presented in this work on LTCC in Section 4.2.1 [V]. The main differences are that an integrated balun is used on a ground plane and radiation is enhanced by a surface wave. Thus, a relatively thick substrate can be used. It is shown that the antenna gain of a single element can exceed the gain of a 1×4 array when using a large substrate.

Table 2.1. State-of-the-art AiP phased arrays in chronological order.

Ref.	Freq. (GHz)	# of elements	Package	Antenna type	MMIC process
[32] ¹⁹	80–100	256Tx, 128Rx	PCB	stacked patch	180 nm SiGe BiCMOS
[35] ¹⁹	60	4×16	PCB	stacked patch	130 nm SiGe BiCMOS
[36] ¹⁹	60	4	Teflon	end-fire dipole	65 nm CMOS
[37] ¹⁹	60	8Tx, 8Rx	LTCC	patch	SiGe BiCMOS
[38] ¹⁸	60	8×32	PCB	series-fed patch	130 nm SiGe BiCMOS
[33] ¹⁸	60	144 TRx	LTCC	slot-coupled patch	28/40 nm CMOS
[28] ¹⁸	70–100	16	PCB	stacked patch	180 nm SiGe BiCMOS
[34] ¹⁷	94	4Tx, 4Rx	PCB	AC patch	130 nm SiGe BiCMOS
[31] ¹⁶	60	64, 256	Quartz	dipole, patch	130 nm SiGe BiCMOS
[26] ¹⁶	77	4 Rx	PCB	series-fed patch	130 nm SiGe BiCMOS
[29] ¹⁵	94	4Tx, 4Rx	LTCC	patch	65 nm CMOS
[27] ¹³	94	16Tx, 32Rx	n/a	dual-polarised	130 nm SiGe BiCMOS
[39] ¹³	77	5	PCB	series-fed patch	SiGe BiCMOS
[24] ¹³	60	32 TRx	LTCC	AC patch	90 nm CMOS
[23] ¹²	60	4Tx, 4Rx	LTCC	slot loop with cavity	65 nm CMOS
[25] ¹¹	60	32 TRx	ceramic	n/a	65 nm CMOS
[22] ¹¹	60	16	LCP	patch with cavity	120 nm SiGe BiCMOS
[21] ¹¹	60	16	LTCC	patch with cavity	120 nm SiGe BiCMOS
[20] ¹¹	60	12	LTCC	AC patch	65 nm CMOS

2.2.2 Beam-switching lens antennas

Theoretical studies and design curves for an extended hemispherical lens antenna excited with a double slot feed antenna were published in [16]. A 70 GHz extended hemispherical lens with a directivity of 30.4 dB was demonstrated in [40]. An aperture-coupled patch antenna was used as a feed. For beam-steering applications, the properties of silicon and quartz lenses with off-axis feed antennas were investigated in [17]. It was concluded that the maximum scan angle of an extended hemispherical lens is around 20° without significant decrease in antenna gain. Beam scanning and beam shaping capabilities of focal-array-fed lens antennas were investigated in [41]. Experimental demonstrations of beam shaping were done at 28.5 GHz using 1, 6, or 10 feeding patch antennas.

A mechanically steerable lens antenna around 60 GHz was developed in [42]. The lens had a single stationary horn as a feed and a collimated-beam lens was tilted around its central focal point. A $\pm 45^\circ$ beam-steering range was demonstrated with a scan loss lower than 1.1 dB. However, a very short beam-switching time required by the 5G wireless networks [43] can not be achieved with mechanical rotation of a lens. Thus, electrical beam switching is needed. A 2D beam-steerable lens antenna system with a 64-element patch feeding antenna array was developed for E-band (71–76 GHz) frequencies in [43]. The Rexolite lens had the maximum measured directivity of 36.7 dB. A beam-switching range of $\pm 4^\circ \times \pm 17^\circ$ was demonstrated. Although directivity was high, the antenna gain was only between 0 to 15 dBi. Such large variation in the antenna gain was mostly due to the mismatch losses in the beam-switching network. In this work, impedance matching networks are used for the switches in Section 5.3 [IV] and the antenna gain variation is smaller than 6.5 dB at 71–76 GHz. Another 2D beam-switching lens antenna for E-band was presented in [44]. Sixteen patch antennas were used as feeds. Scan angles up to 18° and 27° were demonstrated with quartz lenses with radii of 12.5 mm and 7.5 mm. Similar SP4T switches were used as in this work in Section 5.3 [IV], but the beam-switching network losses were not reported.

A wide-scan spherical Teflon lens with tapered slot antennas as feeds operating at 77 GHz was published in [45]. A $\pm 90^\circ$ scan range with -3.5 dB and -6 dB crossover levels was achieved using 33- and 23-element feed antenna arrays. Schottky diodes were used as detectors. An extended hemispherical lens with feed antennas on spherical surface was studied in [46]. Good beam shapes and low scan loss up to 30° beam-steering angles was demonstrated for Teflon lens at 77 GHz. This work was continued and a lens system with electrically switchable feeding antenna array is presented in this thesis in Section 5.3 [IV]. The antenna is fed from a single RF port and can be used in both ends of an RF link, i.e., as a transmitting or a receiving antenna.

3. Manufacturing technologies

Suitable manufacturing technologies for millimetre-wave antennas are, for example, low temperature co-fired ceramic (LTCC) and printed circuit board (PCB), which are used in this work. Other solutions are thin-film processing on high-resistivity silicon, quartz, or alumina substrates, integrated passive devices (IPD), and membrane technologies. Antennas can be also fabricated directly on the MMIC chip. From the antenna efficiency point of view, the permittivity and the loss tangent of the substrate should be low. In addition, the conductors should have a high conductivity and a smooth surface profile to minimise the feed network losses. The substrates should also be compatible with multi-layered manufacturing processes and integration with active components using flip-chip or wire-bonding techniques.

3.1 Low temperature co-fired ceramic

LTCC is a multilayer (even up to 70 layers) platform technology which enables fabrication of RF passive components such as transmission lines, filters, and antennas in a cost-effective package. Integration with MMICs can be done by using wire bonding or flip-chip techniques to make an antenna-in-package (AiP) system. The LTCC module can be further integrated with a low-cost (such as FR-4) PCB platform by using ball grid array (BGA) solder balls.

LTCC technology enables printing of conductors and processing of vias on each layer separately. The main advantages of LTCC are low conductor and dielectric losses, good thermal conductivity, stability, and hermeticity. From the antenna point of view, a disadvantage is a relatively high dielectric constant (commonly 6–8) which often cause problems in the form of surface waves [47]. Several commercial LTCC material systems are available, such as 9K7 and 951 by DuPont and A6M-E by Ferro (formerly A6-S, A6M) [48] which is used in this work. The Ferro A6M-E has electrical parameters of $\epsilon_r = 5.7 \pm 0.15$ and $\tan \delta = 0.0015$ at 10 GHz and around $\epsilon_r = 6$ and $\tan \delta = 0.0015$ up to 100 GHz [49]. The tape material is available in standard thicknesses of 51 μm , 127 μm and 254 μm . The fired (sintered) layer thickness for the 127 μm tape is 97 μm .

The detailed design guidelines for the LTCC processing can be found in [48].

For the millimetre-wave applications, the most important parameters are the minimum line and gap widths, via diameter and spacing, and processing accuracy. At VTT, line and gap widths down to $50\text{ }\mu\text{m}$ are possible. The commonly used via diameter is $100\text{ }\mu\text{m}$ with a catch pad having a diameter of at least $200\text{ }\mu\text{m}$. The full manufacturing panel size is $100\text{ mm} \times 100\text{ mm}$ but also a half panel or a quarter panel can be fabricated. The LTCC process description can be found, for example, in [50]. An example of an LTCC build up is shown in Fig. 3.1a.

3.2 Printed circuit board

Suitable PCB materials for the millimetre-wave applications are, for example, liquid crystal polymer (LCP) [51] ($\epsilon_r = 3.16 \pm 0.05$, $\tan\delta < 0.0049$ up to 97 GHz [52]), PTFE (Teflon) -based materials such as RO3003 by Rogers [53] ($\epsilon_r = 3.2$ at 79 GHz , $\tan\delta = 0.001$ at 10 GHz [54]) and TLY laminates by Taconic ($\epsilon_r = 2.2$, $\tan\delta = 0.0009$ at 10 GHz [55]). Isola Group has a low-loss laminate Astra MT77 [56] ($\epsilon_r = 3.0 \pm 0.1$, $\tan\delta = 0.0015 \pm 0.0005$ up to 100 GHz [57]) which is used in this work for the lens feeding array in Chapter 5. The relative permittivity for the PCB materials is usually around $\epsilon_r = 2-3$, which is feasible from the antenna point of view. The most materials are suitable for the multilayer stack ups. A hybrid approach is possible (see Fig. 3.1b), in which a high-frequency laminate is used for the millimetre-wave parts and a low-cost FR-4 is used for the DC and control signal routing. Often the same material is used for the whole build up. A “prepreg” acting as a gluing layer is used between the “laminates” to keep all the layers together. There is also an increasing need for high density interconnect (HDI) PCBs. These so called anylayer build ups resemble LTCC technology in a sense that blind vias can be processed on each layer separately, thus providing design flexibility with small via and catch pad diameters. Anylayer PCB usually has only one core layer and other layers are prepreg films as shown in Fig. 3.1c. It is important to maintain symmetry in the multilayer PCB build ups from the dielectric laminate and copper cladding point of views.

Technical information and design guidelines for the PCB processing can be found in [58]. The standard value for minimum line and gap widths is $100\text{ }\mu\text{m}$. Different types of vias can be used, such as a blind via (“A” in Figs. 3.1b, 3.1c) or a plated-through via (“B” and “C” in Fig. 3.1b). The aspect ratio (AR), i.e., “The ratio of hole diameter to board thickness or blind hole deepness” [58], depends on the via type. For the blind via the $\text{AR}=1:1$, and for the plated-through via the $\text{AR}=1:10$ at maximum [58]. The annular ring defining the catch pad size for the vias depends on the via size. Usually, for a blind via having a diameter of $150\text{ }\mu\text{m}$, a catch pad of size at least $300\text{ }\mu\text{m}$ should be used.

Several types of finishes are available for the PCB copper conductors such as ENIG, ISIG, or ENEPIG [58]. The ENIG is a common choice since it enables

Figure 3.1. Examples of multi-layer (a) LTCC, (b) hybrid PCB, and (c) anylayer PCB build ups. “A” denotes a via through a single layer in (a) and a blind via in (b) and (c). “B” and “C” denote plated through vias between L1 and L3 and between L1 and L5 in (b). “D” is an open cavity. Green layers on the outermost sides of the stack in (b) and (c) are solder masks.

both, wire bonding and soldering of components on the PCB. The drawback of the ENIG is nickel which has a lower conductivity than silver or gold leading to increased conductor losses. The PCB manufacturing panel size is usually 297 mm $\times$ 420 mm (A3) which is much larger than that of LTCC (100 mm $\times$ 100 mm). This enables manufacturing of multiple millimetre-wave antennas and arrays on a single panel which reduces manufacturing costs in mass production.

3.3 Other platforms

Single-layer millimetre-wave antennas can be processed, for example, on a high-resistivity silicon substrate. A single antenna is not an efficient radiator due to surface waves, but the antenna can be used as a feed for a silicon lens [16]. The feed is placed on the bottom surface of the lens and the substrate is a part of the lens extension. The IPD platform usually has a few thin (about

6–10 μm thick) dielectric and metal layers on top of a glass substrate [59], [60]. The IPD chip can be integrated into a PCB using solder bumps. The membrane antennas are usually manufactured by removing (lossy) substrate material underneath the antenna to improve radiation characteristics and the efficiency. As for examples, antennas on 20 μm thick polydimethylsiloxane (PDMS) [61] and benzocyclobutene (BCB) membranes [62] have been published for the 60 GHz frequency band. On-chip antennas are attractive since they can be integrated directly with the MMICs without having any wire-bond or flip-chip interconnections. However, the antenna gain of an on-chip antenna is usually low (for example -10 dBi in [63]) due to lossy silicon substrate. The on-chip antenna performance has been improved in [64] by placing a partially reflective surface (PRS) underneath the antenna. A maximum gain of 1.42 dBi has been measured.

4. Planar antenna designs on LTCC

4.1 Antennas for broadside radiation

4.1.1 60 GHz patch antennas and arrays with cavities

The designs of 60 GHz aperture-coupled microstrip line-fed patch antennas (ACMPAs) and 4×4 arrays on LTCC are presented in [I]. In addition to the traditional antenna and array designs used as a reference, improved versions are also developed. The bandwidth and antenna gain increase are achieved by using an embedded cavity inside the antenna substrate. The antenna array performance is also improved by using the Wilkinson power dividers in the feed network instead of the quarter-wave matched T-junctions.

The impedance bandwidth of a microstrip antenna increases with substrate thickness and decreases with an increase in substrate permittivity [65]. Thus, it is advantageous to use a thick substrate with a low dielectric constant if wide operation frequency band is needed. Conversely, the surface wave power generated by an antenna increases with substrate thickness and dielectric constant [65]. Since the surface wave power is usually considered a loss mechanism, a low dielectric constant is desirable to maximise the radiation performance of an antenna. For the LTCC processing, the tape materials typically have a relatively high dielectric constant of around $\epsilon_r = 6 - 8$. However, the ϵ_r can be effectively reduced by using air cavities inside the antenna substrate.

The antenna structures are designed on the Ferro A6-S LTCC tape system ($\epsilon_r = 5.99, \tan \delta = 0.0015$) with a fired tape thickness of $100 \mu\text{m}$. An effective conductivity of $\sigma_{\text{Au}} = 7 \times 10^6 \text{ S/m}$ is used for the conductors printed using the gold paste. The ACMPA is fed by a microstrip line and the antenna element is excited by a nonresonant aperture in the ground plane. Three metal layers are needed: one for the microstrip line, one for the ground plane and another for the radiating patch. One tape layer is needed for the microstrip feed line and three tape layers for the radiating patch. The simulated maximum gain

Figure 4.1. Geometries of the 60 GHz aperture-coupled microstrip line-fed patch antennas. (a) without and (b) with cavity. (© 2008 IEEE [I])

for the ACMPA is 3.7 dBi. The geometry of the ACMPA is illustrated in Fig. 4.1a. The ACMPA with a cavity has six layers of LTCC tapes (see Fig. 4.1b). The 200- μm -thick superstrate above the radiator focuses the electromagnetic field upward. In order to prevent the deformation of the cavity during the LTCC process, the two lowest layers are fabricated on a different LTCC panel than the four uppermost layers. After the sintering and dicing processes, the four-layer parts with open-type cavities are flipped and glued on their counterpart two-layer substrates and embedded cavities are formed. When fabricated this way, the cavity can be very large, as long as the cavity walls are sufficiently thick; at least 2 mm thick. The results in Table I of [I] show that the cavity edges should be at least 3 mm apart from the patch edges to achieve the maximum gain of 7.2 dBi. The simulated radiation patterns in Fig. 3 of [I] show the pattern improvement by using a cavity, especially in the E-plane. Radiation toward directions of $\pm 90^\circ$ is reduced by 5.1 dB and the back-radiation level is reduced by 4.2 dB due to suppressed surface-wave power.

The effect of the substrate size on the ACMPA performance with and without cavity is simulated by changing the parameter p as illustrated in Fig. 4.2. The E- and H-plane co-polarised gain patterns are shown in Fig. 4.3. It can be observed that the ACMPA without cavity is sensitive to the substrate size. The E-plane pattern changes with varying p and has peaks and dips around $\theta = 0^\circ$. This is due to surface waves which radiate from the antenna edges and sum up with the patch radiation. In the H-plane, the pattern is more stable and symmetrical. For the ACMPA with cavity, both the E- and H-plane patterns

Figure 4.2. Variation of the substrate sizes of the ACMPA without (left) and with cavity (right).

are more stable around $\theta = 0^\circ$. It can be concluded that for the ACMPA with a cavity, most of the radiation is excited by the patch and the surface-wave power is significantly reduced.

Three types of antenna arrays are designed: a 4×4 array with a reactive T-junction feed network, a 4×4 array with a Wilkinson feed network, and a 4×4 array with a cavity and a Wilkinson feed network. An element spacing of 3 mm ($0.6\lambda_0$) is used. Photographs of the manufactured arrays are shown in Fig. 4.4.

The S-parameters of the antennas and the power dividers are measured on a probe station using the thru-reflect-line (TRL) calibration method. The microstrip-line TRL kit is manufactured in the same LTCC process. Measured center frequencies and -10-dB impedance bandwidths are 60.6 GHz and 60.8 GHz, 5.8% and 9.5% for the ACMPA and ACMPA with the embedded cavity. The mutual coupling between array elements without the cavity is -14 dB and -21 dB in the E- and H-planes, respectively. With the cavity the values are of the same order in both planes, -18 dB and -19 dB, at 60 GHz. In the reactive T-junction, the measured matching at input port is $|S_{11}| = -17$ dB whereas the matching at the output ports is only $|S_{22}| = -5.2$ dB and $|S_{33}| = -6.5$ dB. The measured isolation between the output ports is $|S_{23}| = -7$ dB and the coupling from the input port to the output port is $|S_{12}| = -3.3$ dB. For the Wilkinson, the return loss is better than 19 dB for all ports at 60 GHz. The isolation is -19 dB and the coupling is -3.3 dB. In an ideal case, the coupling would be -3.01 dB. The difference is mainly caused by conductor losses.

The radiation patterns of the antenna arrays are presented in Figs. 15–17 of [I]. With a reactive feed network no clear side lobes are seen and the back-lobe level is high, about -8.7 dB. The maximum gain, 14.1 dBi, is also lower than the 15.7 dBi obtained with a Wilkinson feed network. With a Wilkinson feed network (Fig. 16 of [I]) the measured patterns are very close to the simulated ones. The back-lobe level is -18.2 dB and the -3 dB beamwidth is 20.3° . With the cavity design (Fig. 17 of [I]) the maximum gain and the back-lobe level are 18.2 dBi and -19.2 dB and the -3 dB beamwidth is 19.7° .

The patch arrays presented here are suitable for short-range millimetre-wave applications such as gigabit-WLANs. The antenna elements are isolated from the feed network and active circuits can be integrated into the same LTCC

Figure 4.3. Simulated gain patterns of the 60 GHz ACMPA without and with cavity with different substrate sizes. Without cavity (a) E-plane and (b) H-plane. With cavity (c) E-plane and (d) H-plane.

Figure 4.4. Photographs of the 16-element antenna arrays on LTCC. (a) Radiating patches, (b) reactive feed network, and (c) Wilkinson feed network.

substrate with the flip-chip technology. The designs are also likely scalable to E-band (70–90 GHz).

The novel contribution of this Section [I] is the comparison between the 60 GHz ACMPA antennas and arrays with and without embedded cavity inside the LTCC substrate. In addition, comparison between antenna arrays having either reactive T-junctions or Wilkinson power dividers in the feed network is done. A 2.5 dBi higher antenna gain is achieved for the array with the cavity than for the reference ACMPA array. Based on the measured radiation patterns of the arrays, it can be concluded that the Wilkinson is a better choice as a power divider element than the quarter-wave matched T-junction.

4.1.2 60 GHz electromagnetic band-gap structure

In the previous section, an air cavity is used to increase the bandwidth and gain of the 60 GHz LTCC antennas and arrays. Although very effective, the air cavity requires additional processing steps to remove parts of the dielectric substrate which may increase the manufacturing cost. In this section, another method is implemented to increase the 60 GHz LTCC antenna gain and to decrease mutual coupling in antenna arrays. The method is based on the use of a uniplanar compact electromagnetic band-gap (UC-EBG) structure patterned on top of the LTCC substrate. The UC-EBG has been previously presented around 12 GHz in [66]. Here, its feasibility is investigated with the 60 GHz antennas and arrays on LTCC.

The UC-EBG unit cell is presented in Fig. 2 of [II]. The dimensions are optimised in the Ansoft HFSS for operation around 60 GHz. The simulated reflection phase is shown in Fig. 3 of [II]. The frequency bandgap of the HFSS-optimized UC-EBG is between 57.2–62.9 GHz, i.e., at this frequency range the reflection phase is between $\pm 90^\circ$. The UC-EBG is implemented on a patch antenna substrate to reduce the surface-wave excitation and to increase the antenna gain. The ACMPA design presented in [I] is chosen as a test structure.

Figure 4.5. The layouts of the ACMPAs with the UC-EBG grids. (a) V1: $r_1 = 0.53$, $R_1 = 7.4$ and (b) V2: $r_2 = 1.46$, $R_2 = 9.3$ (mm). (© 2009 IEEE [II])

Figure 4.6. Photographs of the UC-EBG on LTCC. (a) close-up view of the UC-EBG grid. (b) 16-element array surrounded with the UC-EBG.

Three periods of UC-EBG cells are placed symmetrically around the radiating patch on top of the substrate. Two versions with the distance $r_1 = 0.53$ mm (V1) and $r_2 = 1.46$ mm (V2) between the patch edges and the UC-EBG edges are designed (see Fig. 4.5). It is seen from the simulation results in Fig. 5 of [II] that in V1 the UC-EBG is too close to the patch and the patch resonance is distorted. Such an effect is not observed with V2 so the separation is sufficient.

The UC-EBG resonance is simulated and measured using a WR-15 waveguide on top of the UC-EBG grid. The simulated center frequency is 59.9 GHz whereas the measured center frequencies are 61.3 GHz and 60.4 GHz for the test structures of manufacturing runs P1 and P2, respectively (Fig. 7 of [II]). The difference between the simulation and the measurements are due to the manufacturing inaccuracies in the LTCC process. The mutual coupling between two antennas placed 5.8 mm distance from each other is presented for the E-plane (Fig. 9 of [II]) and the H-plane (Fig. 10 of [II]) configurations. A maximum reduction of 11.8 dB is observed at 63.4 GHz for the E-plane coupling with the UC-EBG. In the H-plane, the coupling is low (below -37 dB at >58 GHz) without the UC-EBG. With the UC-EBG the coupling is increased below the resonance around 62 GHz. Above resonance the coupling is about -40 dB up to 67 GHz with the UC-EBG. Thus, the UC-EBG is more beneficial in suppressing the coupling in the E-plane than in the H-plane.

Measured radiation patterns at several different frequencies are shown in Fig. 14 of [III]. It is observed that the radiation pattern of the conventional ACMPA remains quite constant and the gain varies between 3.7–4.5 dBi having the maximum at 60 GHz. Large variations are seen in the UC-EBG antenna patterns that are also observed in the HFSS simulations. This effect is due to the UC-EBG whos behavior is strongly frequency dependent. At resonance, large currents are induced in the UC-EBG grid and the grid itself contributes to the radiation making the antenna effective aperture larger thus increasing the

Figure 4.7. Measured co-pol. gain patterns of the 16-element arrays (ref.) without and (ebg) with UC-EBG. (a) E-plane, (b) H-plane. The scale is from -20 dBi to 20 dBi with 5 dBi steps. (© 2009 IEEE [III])

gain. The gain is 3 dB higher at 62 GHz and 4.5 dB higher at 61 GHz for the UC-EBG antenna than for the reference ACMPA without the UC-EBG. For the 16-element ACMPA array surrounded with an UC-EBG grid shown in Fig. 4.6, the maximum gain, 18.0 dBi, is achieved at 61 GHz and is 2.3 dBi higher than without the UC-EBG (see Fig. 4.7).

The implementation of UC-EBG for 60-GHz antenna applications is very challenging due to its narrow-band resonance. Although obtaining improvements in the antenna gain and the E-plane mutual coupling, the small bandwidth and large size makes the current UC-EBG design quite impractical to be used in the 60-GHz phased-array antenna applications. However, a higher gain for an LTCC antenna array can be achieved by placing the UC-EBG around the whole array. The design could be also beneficial for reducing the cross-coupling between, for example, receive and transmit antennas and arrays or other components in 3D integrated LTCC modules.

The novel contribution of this Section [II] is the implementation of the 60 GHz UC-EBG on LTCC. The main achievements are the 11.8 dB reduction for the E-plane coupling with the UC-EBG between antennas and the 2.3 dBi higher gain for a 16-element array surrounded with the UC-EBG.

4.1.3 W-band dual-resonant patch antenna array

Antennas on LTCC substrates often suffer from narrow bandwidth due to the high-permittivity substrate. In this section, a design of a stacked microstrip patch antenna and a 16-element array on LTCC for a wideband operation at W-band is presented. A parasitic patch is added on LTCC substrate to increase bandwidth. The stacked configuration is designed by using an equivalent circuit together with EM simulators.

The equivalent circuit used for the initial design of the stacked patch antenna

Figure 4.8. Equivalent circuit for dual-resonant patch antenna. (© 2011 EurAAP [VII])

is shown in Fig. 4.8 [67]. The parallel (B) and series (D) RLC-circuits model the driven patch and the parasitic patch. The first transformer (A) represents the coupling between the feed line and the driven patch. The second transformer (C) represents the coupling between the two patches. The equivalent circuit is implemented in the AWR Microwave Office circuit simulator. The circuit model parameters are optimised for the maximum bandwidth. By excluding the parasitic patch, the input impedance for the driven patch can be estimated (see Fig. 2 of [VII]). The final optimisation of the antenna is done using Ansoft HFSS. The maximum gain varies between 1.8 dBi and 4.3 dBi peaking at 80 GHz. The radiation efficiency is between 82% and 90%. A 16-element stacked patch antenna array of size $D = 9.3$ mm and an element separation of $d = 2$ mm is also designed as shown in Fig. 4.9. Microstrip line feed network with Wilkinson power dividers is optimised for the center frequency of 93 GHz. The required 100- Ω resistors are screen-printed on LTCC using a resistive paste.

The maximum gain of 14.2 dBi is measured for the array at 84 GHz (see Figs. 7–13 of [VII]). The cross-polarisation level is about -25 dB. The back-radiation level is -12 dB at the highest. The -3-dB beamwidth decreases with increasing frequency and varies between 18° and 26° . The -3-dB gain bandwidth is between 78.5 GHz and 98.5 GHz. The antenna efficiency calculated from the simulated directivity and the measured gain is 48% at the highest. The main advantage of the developed antenna is that wideband operation is achieved without any additional processing steps, such as creating cavities inside substrate.

The novel contribution of this Section [VII] is the design of a stacked patch antenna array on LTCC for a large frequency range (78.5–98.5 GHz) at W-band.

4.1.4 60 GHz chain antenna array

For a high antenna directivity and gain, a large antenna aperture or array is a requisite. As seen in Fig. 1.2, for example for the 25 dB directivity, an aperture size of 25 mm $\times$ 25 mm at 60 GHz is needed. For an antenna array with the element spacing of 2.5 mm ($\lambda_0/2$), the number of required antenna elements would be at least $10 \times 10 = 100$. As the complexity and the losses of the array feed network increase with the array size, planar transmission lines such as

Figure 4.9. Stacked patch array geometry. (a) top view of the array, (b) LTCC layer structure, (c) top view of an array element. (© 2011 EurAAP [VII])

a microstrip line, may become impractical for large arrays. In this section, a design of a traveling wave chain antenna array operating at 60 GHz frequency band is presented. The antenna consists of several parallel microstrip chains printed on an LTCC substrate. The array feed network is constructed using substrate integrated waveguide (SIW) technology to minimise transmission line losses. The design is described in [VIII].

Traditionally, chain antenna arrays are fed from the edge using microstrip lines or probes [68] and the beam scans with frequency. In this work, the chains are fed symmetrically from the center with an offset for a broadside radiation pattern (see Fig. 4.10). The strip lengths a and b are approximately $\lambda_s/2$ at the center frequency where the λ_s is the guided wavelength of the strip. In the edge-fed antenna (Fig. 4.10a), the vertical strips marked with red radiate in the vertical direction and sum up in the far field while the horizontal strips marked with blue effectively cancel each others radiation. Using an offset feed shown in (Fig. 4.10c), the vertical strips are fed in phase and the antenna radiates a broadside beam.

The chain antenna is optimised for a three-layered Ferro A6-M LTCC substrate. The electrical parameters of the Ferro A6-M are $\epsilon_r = 5.7$ and $\tan\delta = 0.0015$. The conductive gold paste has $\sigma_{Au} = 7.0 \cdot 10^6$ S/m. The antenna is fed by a probe formed by vias between the chain and the ground plane. The simulated peak realised gain is 11.2 dBi (see Fig. 2 of [VIII]). The radiation efficiency is higher than 80% between 57 GHz and 64 GHz with a peak value of 85% at 62 GHz. A sub-array of 4 chain antennas is a basic building block of a large integrated chain array fed through a SIW feed network. For the 4-chain array, the simulated peak realised gain is 15.9 dBi and the radiation efficiency is 75% at 62 GHz (see Fig. 5 of [VIII]).

A transition from a standard WR-15 waveguide to a SIW is designed for the measurement purposes. The transition consists of stacked patch antennas and the driven patch is excited from the SIW using a via instead of a coupling

Figure 4.10. Schematics of a chain antenna. (a) edge-fed, (b) center-fed, and (c) offset-fed chain antennas. (© 2012 EurAAP [VIII])

Figure 4.11. Layout of the LTCC chain array. (a) side view showing the layer structure, (b) top view without ground plane. (© 2012 EurAAP [VIII])

aperture in the patch ground plane (see Fig. 7 of [VIII]). A large chain array with dimensions of 27 mm $\times$ 22 mm is designed (see Fig. 4.11). The array consists of 8 chain antennas in the vertical direction and 4 chains in the horizontal direction. In the horizontal direction, the chains are connected together to form a single long chain having multiple feed points. Photographs of the manufactured antenna array are shown in Fig. 4.12.

The simulated and measured H- and E-plane radiation patterns of the chain array are shown in Figs. 12–15, and the maximum antenna gains as a function of frequency in Fig. 16 of [VIII]. The simulated and measured peak gains are about 21 dBi and 22 dBi. The proposed antenna design is suitable for low-cost millimetre-wave applications in which relatively high antenna gain is required. The antenna does not require very narrow conductors or spacings which enables scaling of the design even for higher frequencies, such as 70–100 GHz.

The novel contribution of this Section [VIII] is the design of a 60 GHz chain antenna array on LTCC which is integrated with a SIW feed network. The chains are at resonance and fed from the center with an offset to provide broadside

Figure 4.12. Photographs of the manufactured LTCC chain array. (a) antenna side, (b) SIW side. (© 2012 EurAAP [VIII])

radiation beam. For the 8-chain prototype the maximum measured gain of 22 dBi is achieved at 62 GHz.

4.2 Antennas for end-fire radiation

4.2.1 60 GHz surface-wave assisted dipole and array

For the end-fire radiation, a planar dipole and a 1×4 array is designed on LTCC for the 60 GHz band ([V]). The antenna consists of a dipole element, a ground plane with an integrated balun, a microstrip feed line, and a reflector. The operation principle is based on radiating TE_0 surface wave launched by the dipole inside LTCC. The center frequency is mainly determined by the length of the dipole whereas the impedance matching is done with the slot in the ground plane and an open-ended microstrip stub. The reflector directs the radiation into a hemisphere. In the antenna array, Wilkinson power dividers are used in the feeding network to distribute power equally to four elements. The feeding line is ended with the GSG pads to enable measurements on a probe station. The layouts and photographs of the manufactured antennas are shown in Fig. 4.13.

A parametric analysis is carried out using the EM simulator Ansys (formerly Ansoft) HFSS. It is observed that the antenna is the most sensitive to the thickness and the length of the substrate. The radiation beam shape is good up to the substrate thickness of $h_2 = 270 \mu\text{m}$ but is distorted with thicker substrates (see Fig. 3 of [V]). By changing the length of the substrate, the antenna gain is increased. With the length l_s varied from 2 mm to 11 mm, the gain is increased from 4 dBi up to 10 dBi (see Fig. 4 of [V]). The maximum gain of 10.7 dBi with a rotationally symmetrical radiation pattern is achieved with $l_s \approx 15$ mm.

The measured $|S_{11}|$ for a single antenna is below -10 dB at 53–59 GHz and

Figure 4.13. 60 GHz end-fire antenna and 1×4 array on LTCC. (a) layouts: single element (top left), array (top right), side view (bottom), (b) manufactured test structures: single element (left), array (center), single element mounted on a 1.85 mm V-connector (right). © 2010 EurAAP [V]

at 65–68 GHz and rises to the maximum value of -6.8 dB at 62 GHz (Fig. 6 of [V]). For the antenna array, the measured $|S_{11}|$ is below -10 dB at 52–68 GHz (Fig. 7 of [V]). With the V-connector used in the radiation pattern measurements, the $|S_{11}|$ for the single element is below -9 dB across the frequency band. For the array, the $|S_{11}|$ is below -10 dB at 54–65 GHz (Fig. 8 of [V]). The radiation patterns for the element and the array are presented in Figs. 9–10 of [V]. The measured gain for the single element is 3.1–7.1 dBi at 55–64 GHz. The cross-polarisation level is below -14 dB in the H- and E-planes at 60 GHz. For the array, the measured gain is 7.0–9.5 dBi at 55–64 GHz. The cross-polarisation level is below -16 dB in the H- and E-planes at 55 GHz. The array gain is smaller than expected (about 8–12 dBi) but could be explained by the fact that the array element sees a wider substrate than the single antenna. It was observed in the parametric analysis that a wide substrate deforms the radiation pattern and decreases the gain. In fact, a higher antenna gain can be achieved with a single element having a long substrate than with a 4-element antenna array. It is noteworthy that the radiation pattern of a single antenna is symmetrical whereas the 1×4 array has a fan-shaped radiation beam.

A wideband end-fire antenna and a 4-element array on LTCC were designed. It can be concluded that the designed antenna is more suitable to be used as a single element than in an array due to rather small gain of the 1×4 array. The array performance could be improved by processing slots between the array elements. The developed antenna may find its use in the 60 GHz wireless

short-range applications in mobile devices.

The novel contribution of this Section [V] is the design of a 60 GHz surface-wave assisted end-fire antenna and a 1×4 array on LTCC. It is demonstrated that the antenna gain of a single element can be increased up to 10.7 dBi by enlarging the substrate size, thus exceeding the gain of a 1×4 array.

4.3 Comparison of the planar antennas

The patch antenna design without cavity presented in [I] has a relatively small bandwidth and low antenna gain. The design could be suitable for low-cost applications where a very large bandwidth or data rate is not required. However, as seen in Fig. 4.3, the radiation pattern of a single element is sensitive to the substrate size. Decent performance can be achieved with an antenna array as shown in Fig. 16 of [I] due to more directive radiation pattern of the array. Wider bandwidth and higher antenna gain can be achieved by implementing a cavity inside the antenna substrate [I]. The design is feasible also for a single antenna element since the radiation pattern is not sensitive to the substrate size (see Fig. 4.3). The manufacturing process is more complex but the same cavity could be used also for packaging of the MMICs in an AiP system. The UC-EBG on LTCC has a narrow-band resonance and if it is placed around a patch antenna, the bandwidth is smaller than without UC-EBG [II]. A higher antenna gain can be achieved when placed around an array but a high manufacturing accuracy is required (see Table I of [II]). Very wideband performance can be achieved by stacking two patches in the LTCC substrate [VII]. The drawback is that the antenna gain is only moderate with the stacked configuration.

The chain antenna presented in [VIII] is a potential candidate for applications where a high antenna gain is needed. The SIW is used in the feed network on LTCC and has the loss of 0.65 dB/cm around 60 GHz. The loss is much smaller than the 1.3 dB/cm of a microstrip line. The SIW enables implementation of large antenna arrays with relatively high efficiencies. The resonant-type chains are patterned on top of an LTCC substrate and do not require very narrow conductors or spacings. The downside of the proposed design is the rather small bandwidth.

The end-fire antenna and array presented in [V] could be usable in the AiP solutions where the radiation beam parallel to the LTCC and PCB is of necessity (see Fig. 1.1). For example, an end-fire beam would be natural for antennas locating on the edges of a mobile device. In addition, end-fire antennas could be used in conjunction with broadside antennas to maximise the angular coverage. The single-element gain of the proposed antenna can be adjusted between 3–10 dBi and large bandwidth can be obtained. However, the designed end-fire antenna is not very efficient as an array. It is observed in Fig. 3 of [V] that the antenna is quite sensitive to the substrate thickness and is probably sensitive also to the surroundings in an AiP.

5. Switchable beam antenna systems

5.1 77 GHz beam-switching high-gain dipole

The end-fire antenna is optimised on LTCC for maximum gain at 77 GHz in [VI]. In addition, a beam-switching demonstration is done using a TGS4306-FC GaAs pin-diode SP4T switch by Qorvo [69]. A waveguide-to-microstrip transition is designed for the radiation pattern measurements. The WR10-to-microstrip line transition consists of a microstrip line, a ground plane with a coupling aperture, a driven patch and a parasitic patch. The two patches resonate at slightly different frequencies which results in as a dual-resonant structure and a wide bandwidth (see Fig. 1 of [VI]). The simulated and measured $|S_{11}|$ is below -10 dB at 78–110 GHz and the simulated insertion loss is 0.3 dB at the center frequency (Fig. 4 of [VI]). Due to lack of space in the LTCC panel, a back-to-back transition is not available and only $|S_{11}|$ is measured. However, the agreement between the simulated and the measured $|S_{11}|$ is very good.

The antenna has three Ferro A6-M tape layers for the optimal performance. The design is quite similar to the one shown in [V]. The substrate size is optimised for the maximum gain and is 3.9 mm × 7.3 mm × 0.3 mm (Fig. 2 of [VI]). The simulated $|S_{11}|$ is below -10 dB above 68 GHz at least up to 110 GHz. The simulated maximum antenna gain is 10.5 dBi at 76 GHz and the radiation efficiency is 89% (Fig. 6 of [VI]). Three end-fire antennas are integrated with the SP4T switch in the middle for the beam-switching demonstration. The antennas produce radiation beams with 90° steps in the E-plane. The pads for the DC bias lines locate on the edges (see Fig. 5.1). Although intended for flip-chip mounting, the switch had to be glued on LTCC with conductive epoxy due to gold paste being unsuitable for soldering. However, solderable AuPt paste is available for Ferro A6-M and should be used in the solder pads to avoid problems due to gluing.

The E- and H-plane radiation patterns are shown in Fig. 8–10 of [VI]. Beam switching is clearly observed. Simulated and measured main beams agree well with each other and the -3-dB beamwidth is about 40°. The front-to-back ratio is

Figure 5.1. Developed 77 GHz beam-switching end-fire antenna on LTCC. (a) layout, (b) manufactured test structure. (© 2010 IEEE [VI])

about 15 dB. Some ripples can be seen due to reflections from the measurement waveguide. A distorted H-plane pattern is observed for the antenna C which is probably caused by a disconnected DC bias cable during the measurements. The measured maximum gain is 3.3 dBi. When taking into account the 2.8 dB insertion loss of the switch [69], the 0.9 dB loss of the transition and the 2.2 dB loss of the microstrip line, the maximum gain of the end-fire antenna is 9.2 dBi at 78 GHz. The 1.1 dB difference between the simulations and the measurements can be related to a mismatch loss between the LTCC substrate and the glued switch.

A beam-switching end-fire antenna on LTCC is demonstrated at 77 GHz. The number of switchable beams can be increased by adding more antenna elements in the desired geometry and by using a larger switching network. Gluing the switches and the DC lines on the LTCC cause additional challenges and reliability issues. Solderable AuPt paste should be used on the LTCC pads intended for flip-chipping or soldering of components.

The novel contribution of this Section [VI] is the implementation of a 77 GHz beam-switching high-gain end-fire antenna on LTCC. Electrical beam switching to three directions is demonstrated by using an RF switch mounted on LTCC.

5.2 90 GHz phased antenna array transmitter

In this section, the design and main results of a 90 GHz 1×4 -element phased-antenna-array transmitter (Tx) are described. The design has been presented earlier in [70] and is related to [III]. The operation principle of the phased array Tx is that a local oscillator (LO) signal is brought using a WR-10 waveguide and is mixed with the intermediate frequency (IF) to produce an RF signal. Then the RF signal is distributed into four branches using a power-division network on LTCC. Each branch include a phase shifter and a buffer amplifier connected

Figure 5.2. Simulation model of the 90 GHz phased-array antenna element on LTCC. Top view (left) and side view (right). (© 2017 IEEE [III])

to an antenna on LTCC.

The MMICs used for the Tx; the mixer, the phase shifters, and the amplifiers, are manufactured using Complementary Metal Oxide Semiconductor (CMOS) technologies. The MMICs are integrated on LTCC by using flip-chip technique. In this work, the focus is on the design of passive RF structures on LTCC: the antenna array, the waveguide transition, the transmission lines, and the power-division network.

The LTCC antenna is geometrically a modified version of an aperture-coupled patch antenna. The patch is surrounded with via fences and metal planes with openings. A similar type of an antenna has been earlier published for the 60 GHz frequency range in [71] and for the 122 GHz band in [72] and [73]. The important part of the antenna is that the via fences form a rectangular LTCC-filled resonator. The radiation is produced from the resonator together with the patch antenna. In this work, the patch and the resonator dimensions are optimised for the center frequency of 90 GHz and for the maximum broadside antenna gain.

The optimised antenna has four Ferro A6M-E LTCC tape layers ($\epsilon_r = 5.7$, $\tan \delta = 0.0015$) with a fired layer thickness of $97 \mu\text{m}$; one layer for the microstrip feed line and three layers for the radiating part. The patch is placed one layer apart from the top surface for impedance matching into 50Ω . Effective conductivity of $\sigma_{\text{Au}} = 7 \times 10^6 \text{ S/m}$, which includes the surface roughness effect, is used for the gold paste in simulations. The antenna geometry is shown in Fig. 5.2.

In an antenna array, the maximum size of the resonator is limited by the antenna element spacing. In this work, an element spacing of $0.6\lambda_0 = 2 \text{ mm}$ at 90 GHz was chosen. The spacing is the same also for the via fences between the array elements. The effect of the resonator size on the antenna radiation patterns is shown in Fig. 5.3. It can be observed that with small resonator sizes $l_r = w_r < 1.5 \text{ mm}$, the radiation patterns are deformed and the maximum gain is low. The gain is also decreased when $l_r = w_r > 2.5 \text{ mm}$. The patterns remain quite stable when $2 \text{ mm} < l_r = w_r < 2.5 \text{ mm}$. The maximum size is restricted by the chosen array element spacing of 2 mm .

The simulated and measured reflection coefficients of two antenna samples, and the simulated maximum gain of the optimised antenna are presented in Fig. 4 of [III]. The correlation between the simulations and the measurements is very good. The measured center frequency is about 2 GHz (2.2 %) higher than

Figure 5.3. Effect of the resonator size on the antenna element radiation patterns. (© 2017 IEEE [III])

the simulated one probably due to small difference in the realised permittivity of the LTCC, or errors in the realised dimensions. The measured $|S_{11}|$ is below -10 dB between 88 GHz and 97 GHz. The simulated gain is higher than 6 dBi from 85 GHz to 103 GHz with a peak value of 7 dBi at 92 GHz.

The 1×4 -element antenna array has a size of $a \times b \times c = 8.2 \times 3.3 \times 0.388 \text{ mm}^3$. The gain patterns simulated at 90 GHz with equal amplitudes and progressive phase shifts of 0° , $+90^\circ$, and -90° are shown in Fig. 5.4. The maximum antenna gains are 12.5 dBi, 12.1 dBi, and 12.1 dBi, respectively. Based on the array factor, the scan range with an element spacing of $0.6\lambda_0$ is limited to about 40° to avoid grating lobes [11]. For wider scan ranges, the element spacing would have to be decreased.

Figure 5.4. Simulation model of the four-element antenna array. Dimensions (in mm): $a = 8.2$, $b = 3.3$, $c = 0.388$, and $d = 2$. (b)–(d) Simulated realised gain of the four-element array at 90 GHz with a progressive phase shift of (b) 0° , (c) $+90^\circ$, and (d) -90° . The directions of the maximums of the beams are: (b) $\theta = 0^\circ$, $\phi = 0^\circ$, (c) $\theta = 25^\circ$, $\phi = 180^\circ$, and (d) $\theta = 25^\circ$, $\phi = 0^\circ$. The element spacing is $0.6\lambda_0$. (© 2017 IEEE [III])

Figure 5.5. Simulated (dashed lines) and measured (solid lines) S-parameters of a back-to-back power distribution network. Markers "○," "□," and "△" denote $|S_{11}|$, $|S_{21}|$, and $|S_{22}|$, respectively. The black dots in the photograph are screen-printed resistors. (© 2017 IEEE [III])

A one-to-four power division network is designed to distribute RF signal from the mixer to different antenna branches. The power division is based on two cascaded Wilkinson power dividers that have been successfully implemented on LTCC in earlier works at 60 GHz in [I] and at W-band in [VII]. The required 100-Ω resistors are screen-printed in the LTCC process. Since it was not possible to measure the power division network with multiple outputs on an on-wafer probe station, a back-to-back test structure was manufactured and tested (see Fig. 5.5). The measured $|S_{11}|$ and $|S_{22}|$ for the back-to-back test structure are below -10 dB between 88 GHz and 96 GHz, whereas the measured $|S_{21}|$ is about -4.1 dB around 90 GHz. Thus, the insertion loss of the single one-to-four power division network is about 2.1 dB. Due to symmetry, the four branches in the antenna array are equal in amplitudes and phases.

The measured LTCC microstrip line attenuation at 75–110 GHz is shown in Fig. 17 of [III]. The attenuation is about 1.2 dB/cm at 75 GHz and 2.0 dB/cm at 95 GHz. Strong ripple can be observed at higher frequencies which is probably due to errors in calibration. More *lines* of different lengths could be designed for the *thru-reflect-line* (TRL) calibration kit to improve accuracy.

For the LO signal, a transition from a WR-10 waveguide to a microstrip line on LTCC is needed. Such transition has been developed earlier and the design is presented in [VI]. The transition is a dual-resonant structure providing an operational bandwidth from about 77 GHz up to 110 GHz. The integration topology shown in Fig. 1.1b is used. The LTCC is mounted directly on top of a PCB and the DC connections are done using bondwires. A cut-out is processed on the PCB around RF lines and the MMIC components on LTCC. Photographs of the realised phased array Tx LTCC module intergated on PCB are shown in Fig. 5.6.

Beamsteering with the phased-array Tx is demonstrated at 90 GHz in Fig. 5.7. Beamsteering to scan angles of -25° , 0° , $+25^\circ$ is achieved. The measured half-power beamwidth (HPBW) of the radiated pattern is $\sim 20^\circ$ at 90 GHz.

(a)

(b)

Figure 5.6. 90 GHz phased array transmitter on LTCC mounted on PCB. (a) front side showing the antenna array and the waveguide transition. (b) back side showing the flip-chipped mixer, phase shifters and amplifiers, and the power division network on LTCC. (© 2017 IEEE [III])

(a)

(b)

(c)

Figure 5.7. Simulated and measured radiation patterns at 90 GHz with progressive phase shift of (a) $+90^\circ$, (b) 0° , and (c) -90° . (© 2017 IEEE [III])

Moderate agreement is seen in the main beams and the first sidelobes between the simulated and the measured radiation patterns. Higher sidelobes in the measured patterns are probably due to reflections in the lab environment.

In the test setup, the highest measured power at 92 GHz is -37.3 dBm, while the predicted power is ~ 10 dB higher. A possible reason could be a misalignment between the WR-10 and the LTCC substrate. Thin LTCC is fragile and does not handle too much force when connecting a waveguide with screws. The WR-10 is connected using two nylon screws which could result in as power leakage and lower LO power than assumed for the mixer. It is noteworthy that the WR-10 connection is needed only for the testing purposes and can be excluded in a final application. The measured cross-polarised power is -54.2 dBm which results in a polarisation discrimination of 17 dB.

A 90 GHz phased-antenna-array transmitter using CMOS MMICs integrated on LTCC is demonstrated. Good agreement between the simulated and measured antenna patterns is achieved for the single antenna element as well as for the phased-array. A $\pm 25^\circ$ beam steering range with a 20° HPBW is measured. The design is scalable for 2D beam steering and for the higher number of array elements. The developed antenna array could be a possible candidate for the 5G high data rate millimetre-wave connections in mobile devices.

The novel contribution of this Section [III] is the demonstration of a 90 GHz CMOS phased-array transmitter integrated on LTCC having a 1×4 patch array with via fences surrounding the array elements. The simulated single-element antenna gain above 6 dBi is achieved from 85 GHz up to 103 GHz. Beamsteering to $-25^\circ, 0^\circ, +25^\circ$ is measured at 90 GHz.

5.3 71–76 GHz beam-switching dual-spherical lens antenna

Usually, the scanning range of an extended hemispherical lens antenna is limited to about $\pm 20^\circ$ [17]. By placing feed antennas on a spherical lens surface, the scanning range can be significantly increased [45], [46]. In [45], Schottky diodes were used as detectors for millimetre-wave signal. In [46], the measurements were done using an open-ended WR-10 waveguide as a feed antenna.

In this work, an electronically controllable beam-switching dual-spherical lens antenna for E-band frequencies (71–76 GHz) is developed. The antenna is fed from a single RF port and can be used in both ends of an RF link, i.e., as a transmitting or a receiving antenna. The antenna can be easily integrated with the transceiver MMIC on the same PCB, or can be connected to another PCB board with a 1.0 mm RF coaxial cable. The antenna design is presented in this section. The detailed description can be found in [IV].

The antenna system consists of a dual-spherical lens antenna, a 16-element feeding antenna array, and a beam-switching network. The hemispherical lens made of Teflon ($\epsilon_r = 2.1, \tan \delta = 0.001$) has a radiation aperture with 26 mm radius. The extension length of 37.5 mm is based on lens optimisation for the

Figure 5.8. Simulation model of (a) the dual-spherical lens antenna and (b) the Vivaldi feed antenna for E-band (71–76 GHz). (© 2018 IEEE [IV])

maximum directivity of 30.3 dB by using ray-tracing simulations [74].

For beam scanning in 1D, an end-fire type Vivaldi antenna is selected as a feed for the lens. The lens and the feed are designed so that a scanning range between $\pm 40^\circ$ in 1D with approximately -3 dB crossover level between beams is achieved. The Vivaldi antenna is printed on a multilayer PCB which consists of Astra MT77 and FR-4 laminates by Isola Group. The microstrip feed line is on top surface and the ground plane including the Vivaldi antenna is about $127\ \mu\text{m}$ distance below the feed line. The total thickness of the PCB is about 0.5 mm. To improve the input matching and the antenna gain, and to reduce the cross-polarization level, $\lambda/4$ slots are patterned on the ground plane to reduce ground currents as in [75] (see Fig. 5.8b). The Vivaldi antenna has the simulated maximum gain of 10.5 dBi and the half-power beamwidths of 48° (E-plane) and 61° (H-plane) when radiating into the Teflon half-space.

An essential part of the feeding antenna array is the beam-switching network which consists of grounded coplanar waveguide (GCPW) transmission lines integrated with five TGS4306-FC SP4T switches by Qorvo [69]. The switch network provides 1 input and 16 outputs for the 16 feeding antennas. The switches are mounted on the PCB by using flip-chip techniques [43]. The Fig. 5.9 shows a photograph of the manufactured PCB including the switching network.

It has been observed that the switches are not well matched into $50\ \Omega$ which results in strong standing waves and high losses in the beam-switching network in [43]. Open-shunt-stub matching networks are designed for the assembled switches. As seen in Fig. 4 of [IV], the input and output matching of the beam-switching network are below -10 dB between 69 GHz and 76 GHz for all outputs. The insertion loss is between 7 dB and 10.5 dB at 71–76 GHz. The simulated and measured reflection coefficients for the 16 feeding Vivaldi antennas are below -10 dB from 68 GHz at least up to 100 GHz.

The electromagnetic (EM) simulations of the lens with a single feeding antenna are done using CST Microwave Studio [76]. A full 16-element array is not

Figure 5.9. Photograph of the beam-switching network (1 input and 16 outputs) and the 16 Vivaldi feeding antennas. The size of the PCB is 77 mm $\times$ 63 mm. (© 2018 IEEE [IV])

Figure 5.10. Simulated directivity (dashed lines) and realised gain (solid lines) of the dual-spherical lens with the feed network at 71 GHz. For the realised gain, the measured S-parameter of the test board are included in the EM simulator to take the beam-switching network losses into account. (© 2018 IEEE [IV])

included due to limited computing resources. Beam-switching is simulated by rotating the feed antenna on the lens bottom surface to 16 different feed positions. The Fig. 5.10 shows the simulated directivity and realised gain patterns for the lens antenna system. For the realised gain, the measured S-parameter of the test board, the simulated losses in the Vivaldi antenna, and the lens losses are taken into account. The simulated directivity is about 30 dB for all the beams whereas the simulated gain is between 18 dBi and 21 dBi. The results show that the realised gain difference between the beams is due to variation in feed branch losses rather than the scan loss of the dual-spherical lens.

The radiation patterns measured using a near-field scanner at 71 GHz are compared with simulations in Fig. 7 of [IV]. Beam-switching between $\pm 40^\circ$ is measured. The measured (simulated) side-lobe level is below -12 dB (-14 dB). The scan loss of the lens antenna system excluding the switching network losses is 1.2 dB (beam 1) and 1.3 dB (beam 16) for the outermost beams. The designed lens has a minimal scan loss and the directivity in Fig. 5.10 is almost the same for all beams. The higher measured scan loss is probably due to the radiation blockage by the metallic support used in the measurements (see Fig. 5 of [IV]). The simulated and measured maximum realised gain as a function of frequency for the beams 1–8 are shown in Fig. 8 of [IV]. The measured realised gain is higher than 13.1 dBi at 71–76 GHz with the maximum of 19.6 dBi for the beam 7 at 71 GHz. This difference in the realised gain between simulations and measurements is 0.8–3.4 dB. The difference is most likely caused by the radiation leakage from the end-launch connector [77] used in the measurements.

An electronically beam-switchable dual-spherical Teflon lens antenna system at 71–76 GHz is designed. Beam steering between $\pm 40^\circ$ is demonstrated in 1D with 16 Vivaldi feeding antennas on PCB. The losses of the switching network are minimised with carefully designed matching networks for the RF switches. By excluding the switching networks losses, the maximum measured scan loss for the lens is 1.3 dB. The developed antenna has application, for example, in millimetre-wave access points in future 5G wireless networks.

The novel contribution of this Section [IV] is the demonstration of a 71–76 GHz electronically beam-switchable lens antenna with a small scan loss. Impedance matching networks are designed for the SP4T switches and the insertion losses of the beam-switching network are minimised. The measured maximum antenna gain of 19.6 dBi at 71 GHz and the gain variation smaller than 6.5 dB at 71–76 GHz are achieved.

5.4 Comparison of the switchable beam antenna systems

The gain improvement method for the end-fire antenna described in Section 4.2.1 [V] is experimentally demonstrated in Section 5.1 [VI]. Beam switching to three directions is demonstrated by using a single SP4T switch. The number of different beams could be increased for an optimal beam cross-over level by

adding more antennas and switches.

In principle, the phased-array demonstrator presented at 90 GHz in Section 5.2 [III] could provide more versatile beam steering than a beam-switching antenna. However, the used phase shifter has a 2-bit resolution and only a few different beams can be constructed. More advanced beamforming is possible with a SiGe vector modulator presented in [78]. The designed patch antenna surrounded with via fences provides a stable antenna gain above 6 dBi over a 19% bandwidth. The bandwidth is comparable to the one obtained for the stacked patch design presented in Section 4.1.3 [VII] but the antenna gain is about 3 dB higher. Although manufacturing is more complex due to the via fences, the antenna design of [III] can be fabricated using the standard LTCC process.

The beam-switching lens antenna shown in Section 5.3 [IV] is the most advanced antenna system presented in this thesis. The main beam having a 30 dB directivity can be switched to 16 directions between $\pm 40^\circ$ with a low scan loss. The beam-switching feed network and the Vivaldi-type feeding antennas are manufactured on a multilayer PCB. A whole transceiver could be also integrated on the same PCB. The designed Vivaldi antenna has a large bandwidth having the measured reflection coefficient < -10 dB from 68 GHz at least up to 100 GHz. In combination with a wideband dielectric lens, the antenna system is usable for a broad frequency range. The main frequency restriction is the beam-switching network which is optimised for 71–76 GHz.

6. Summary of publications

Publication I: “60-GHz patch antennas and arrays on LTCC with embedded-cavity substrates”

This paper presents the design, manufacturing and measurements of 60 GHz patch antennas and arrays on low temperature co-fired ceramic (LTCC) substrates. A method based on processing air cavities inside substrate to increase the antenna gain and the operational bandwidth is utilised. In addition, co-fired LTCC resistors are processed for a Wilkinson power divider to be used in array feed networks instead of a reactive T-junction. The results verify the feasibility of the LTCC process for the fabrication of 60 GHz antennas and arrays. The measured S-parameters indicate impedance bandwidths of 9.5% and 5.8% for the array elements with and without an embedded cavity. The measured maximum gains for the 16-element patch arrays (with and without cavity) are 18.2 dBi and 15.7 dBi, respectively.

Publication II: “UC-EBG on LTCC for 60-GHz frequency band antenna applications”

In this publication, a uniplanar-compact electromagnetic band-gap (UC-EBG) structure is designed on LTCC for the 60 GHz frequency band. The UC-EBG design is used with a patch antenna and with a 16-element array to increase the antenna gain. The UC-EBG is also used to reduce the mutual coupling between antennas in the E- and H-planes. The performance of the antennas with and without UC-EBG are evaluated with the probe-station and radiation-pattern measurements. In addition, the reflection from the UC-EBG surface is measured using a WR-15 waveguide excitation. An increase of up to 4.5 dBi and 2.3 dBi is achieved in the gain for a single element and for a 16-element array, respectively. A reduction of up to 11.8 dB is observed in the E-plane coupling between two patches.

Publication III: “90 GHz CMOS phased-array transmitter integrated on LTCC”

The paper presents a 90 GHz phased array transmitter integrated on LTCC. The monolithic microwave integrated circuits (MMICs) are manufactured using complementary metal oxide semiconductor (CMOS) technologies and flip-chipped on LTCC. The LTCC board is mounted on a printed circuit board (PCB) for RF testing. A four-element antenna array is designed for the transmitter. The antenna is formed by a patch surrounded by a rectangular cavity resonator having via walls. For the antenna element, the simulated antenna gain is higher than 6 dBi from 85 to 103 GHz with a peak value of 7 dBi at 92 GHz. For the array, the simulated maximum gain is from 12.1 dBi to 12.5 dBi when scanned between $\pm 25^\circ$. A $\pm 25^\circ$ beam steering range with a 20° HPBW is measured for the phased array transmitter at 90 GHz.

Publication IV: “Beam-switching dual-spherical lens antenna with low scan loss at 71–76 GHz”

This paper presents a beam-switching lens antenna system for the E-band (71–76 GHz) frequencies. A 16-element beam-switching feed antenna array is designed for the hemispherical Teflon lens having a collimating surface diameter of 52 mm. The beam-switching feed array is based on single-pole four-throw (SP4T) RF switches and tapered slot antennas, so called Vivaldi antennas. The feed array is manufactured on a multilayered PCB. Beam switching between $\pm 40^\circ$ is demonstrated in one dimension with the measured scan loss below 1.3 dB. The maximum simulated and measured realised gain including the switch network losses is 21.8 dBi and 19.6 dBi, respectively.

Publication V: “Wideband millimetre wave end-fire antenna and array for wireless short-range applications”

Designs of a 60 GHz end-fire dipole antenna and a four-element array on LTCC is presented in this paper. The measured maximum antenna gain for the single element and for the array are 7.1 dBi and 9.5 dBi, respectively. It is shown with simulations that a maximum gain of 10.7 dBi is achievable for a single element by increasing the substrate length up to 15 mm.

Publication VI: “77 GHz beam-switching high-gain end-fire antenna on LTCC”

A gain-maximised end-fire antenna on LTCC is designed for 77 GHz. A max-

imum gain of 9.2 dBi and a -3-dB beamwidth of about 40° are measured. In addition, beam-switching with three steps in the E-plane is demonstrated by using an SP4T RF switch.

Publication VII: “Wideband stacked patch antenna array on LTCC for W-band”

In this paper, a wideband LTCC patch antenna and a 16-element array are designed for the W-band (79–99 GHz) frequencies. Wideband performance is achieved with stacked patches designed by using an equivalent circuit model together with electromagnetic simulators. The manufactured antenna array is integrated with a WR-10-to-microstrip-line transition to facilitate RF testing. The measured maximum gain is higher than 11.2 dBi between 78.5 GHz and 98.5 GHz with a peak value of 14.2 dBi at 84 GHz.

Publication VIII: “High gain 60 GHz LTCC chain antenna array with substrate integrated waveguide feed network”

This paper presents a design of a 60 GHz traveling wave chain antenna array on LTCC. The antenna consists of microstrip chains fed by a substrate integrated waveguide (SIW) feed network to minimise the transmission line losses. A WR-15 to SIW transition is also designed for the RF testing. The maximum gain of 22 dBi at 62 GHz is measured for a prototype antenna of size $27\text{ mm} \times 22\text{ mm} \times 1.1\text{ mm}$.

7. Conclusions

In this work, practical realisation techniques of millimetre-wave antennas for 60–110 GHz frequency bands are investigated. The developed antennas are targeted for the fifth generation (5G) wireless communications applications. Common requirements for such systems are: moderate or high antenna gain, beam steering, low manufacturing cost, small form factor, and integrability with radio frequency front ends, which are often called as antenna-in-package systems.

The work starts with designs of antennas and antenna arrays on low temperature co-fired ceramic (LTCC) substrate radiating broadside or endfire radiation beams. Methods for improving antenna performance are implemented. First method is based on utilisation of an air cavity inside LTCC substrate to reduce effective dielectric constant of patch antenna substrate and thereby increase antenna gain and operational bandwidth. Second method is to implement a uniplanar compact electromagnetic bandgap (UC-EBG) structure on LTCC around a patch antenna and an array to suppress surface waves, to increase the antenna gain, and to reduce mutual coupling between the antennas. Third method is based on a patch having surrounding metal planes and grounding vias to form a radiating resonator to increase the antenna gain. This antenna design is used in the 90-GHz phased antenna array demonstrator. To increase bandwidth, stacked patches providing a dual-resonant behaviour are designed on LTCC for the W-band (75–110 GHz).

For the end-fire radiation, a planar surface-wave assisted dipole and array on LTCC and a Vivaldi-type tapered slot antenna on printed circuit board (PCB) are designed. The antenna gain increase method by modifying the dipole antenna substrate is utilised. Also the Vivaldi antenna performance is improved by patterning quarter-wavelength slots in the antenna ground plane. The design is implemented in the E-band (71–76 GHz) beam-switching lens feeding antenna array.

Three beam-steering antenna demonstrators are developed: a 77 GHz beam-switching end-fire antenna, a 90 GHz phased antenna array transmitter and a 71–76 GHz beam-switching dual-spherical lens antenna system. The first one has three end-fire dipoles on LTCC integrated with an RF switch. The

phased antenna array has a 1×4 patch array with surrounding metal planes and vias. Beam-steering angles of -25° , 0° , $+25^\circ$ are demonstrated at 90 GHz. The E-band lens antenna includes a 1×16 electrically switchable Vivaldi feeding antenna array. The antenna system provides beam steering between $\pm 40^\circ$ with low scan loss in one dimension.

The low temperature co-fired ceramic (LTCC) is a feasible manufacturing technology for millimetre-wave applications due to its multilayer characteristics, narrow conductor patterning down to $50 \mu\text{m}$, and capability for flip-chip processing of monolithic microwave integrated circuits (MMICs). However, LTCC is not perhaps the most cost effective solution in large scales. In recent years, standard PCB processing has developed and low-loss materials are available also for the millimetre-wave frequencies. The PCB technology enables the smallest line and gap widths of about $100 \mu\text{m}$ and also multilayer build ups can be manufactured. The PCB is cost effective since it is a mature technology. In addition, a standard PCB panel size of $297 \text{ mm} \times 420 \text{ mm}$ (A3) is much larger than that of LTCC ($100 \text{ mm} \times 100 \text{ mm}$), which enables manufacturing of multiple millimetre-wave antennas and arrays on a single panel which reduces the manufacturing cost in mass production.

For future development, beam steering in 2D is targeted. For 2D beam switching with the spherical lens, a stack of multiple PCBs could be used as a feeding matrix. This leads to a mechanically complex system. A planar phased array antenna with a high number of antenna elements is a more favorable solution. For an adequate link range of up to hundreds of meters at millimetre-wave frequencies, the number of phased-array elements should be 16, 64, 128, 256, or even higher. Since each element should be equipped with a phase shifter, large phased arrays are complex systems providing many challenges also for the future work.

References

- [1] H. H. Meinel, "Commercial applications of millimeterwaves: history, present status, and future trends," *IEEE Trans. Microw. Theory Techn.*, vol. 43, no. 7, pp. 1639–1653, July 1995.
- [2] L. Yujiri, M. Shoucri, and P. Moffa, "Passive millimeter wave imaging," *IEEE Microw. Mag.*, vol. 4, no. 3, pp. 39–50, Sep. 2003.
- [3] A. Luukanen, T. Kiuru, M. M. Leivo, A. Rautiainen, and J. Varis, "Passive three-colour submillimetre-wave video camera," in *SPIE Defense, Security, and Sensing*, vol. 8715, May 2013, pp. 1–6.
- [4] Z. Pi and F. Khan, "An introduction to millimeter-wave mobile broadband systems," *IEEE Commun. Mag.*, vol. 49, no. 6, pp. 101–107, June 2011.
- [5] T. S. Rappaport, S. Sun, R. Mayzus, H. Zhao, Y. Azar, K. Wang, G. N. Wong, J. K. Schulz, M. Samimi, and F. Gutierrez, "Millimeter wave mobile communications for 5G cellular: It will work!" *IEEE Access*, vol. 1, pp. 335–349, 2013.
- [6] A. Ghosh, T. A. Thomas, M. C. Cudak, R. Ratasuk, P. Moorut, F. W. Vook, T. S. Rappaport, G. R. MacCartney, S. Sun, and S. Nie, "Millimeter-wave enhanced local area systems: a high-data-rate approach for future wireless networks," *IEEE J. Sel. Areas Commun.*, vol. 32, no. 6, pp. 1152–1163, June 2014.
- [7] "GSMA Public Policy Position," <https://www.gsma.com/spectrum/wp-content/uploads/2019/07/5G-Spectrum-Positions.pdf>, GSMA Association, London, UK, accessed: 2019-09-03.
- [8] T. S. Rappaport, Y. Xing, O. Kanhere, S. Ju, A. Madanayake, S. Mandal, A. Alkhatieb, and G. C. Trichopoulos, "Wireless communications and applications above 100 GHz: Opportunities and challenges for 6G and beyond," *IEEE Access*, vol. 7, pp. 78 729–78 757, June 2019.
- [9] Y. Zhang and J. Mao, "An overview of the development of antenna-in-package technology for highly integrated wireless devices," *Proc. IEEE*, pp. 1–16, Aug. 2019.
- [10] C. A. Balanis, *Antenna Theory*, 2nd ed. New York: Wiley, 1997.
- [11] R. J. Mailloux, *Phased Array Antenna Handbook*. Artech House, 1994.
- [12] M. Fakharzadeh, M. Nezhad-Ahmadi, B. Biglarbegian, J. Ahmadi-Shokouh, and S. Safavi-Naeini, "CMOS phased array transceiver technology for 60 GHz wireless applications," *IEEE Trans. Antennas Propag.*, vol. 58, no. 4, pp. 1093–1104, Apr. 2010.
- [13] W. Hong, "Solving the 5G mobile antenna puzzle: assessing future directions for the 5G mobile antenna paradigm shift," *IEEE Microw. Mag.*, vol. 18, no. 7, pp. 86–102, Nov. 2017.

- [14] I. Lindell and K. Nikoskinen, *Antenniteoria*, 4th ed. Oatieto, 1997.
- [15] "IEEE Standard for Definitions of Terms for Antennas," *IEEE Std 145-2013 (Revision of IEEE Std 145-1993)*, pp. 1–50, Mar. 2014.
- [16] D. F. Filipovic, S. S. Gearhart, and G. M. Rebeiz, "Double-slot antennas on extended hemispherical and elliptical silicon dielectric lenses," *IEEE Trans. Microw. Theory Techn.*, vol. 41, no. 10, pp. 1738–1749, Oct. 1993.
- [17] D. F. Filipovic, G. P. Gauthier, S. Raman, and G. M. Rebeiz, "Off-axis properties of silicon and quartz dielectric lens antennas," *IEEE Trans. Antennas Propag.*, vol. 45, no. 5, pp. 760–766, May 1997.
- [18] A. Karttunen, "Millimetre and submillimetre wave antenna design using ray tracing," Ph.D. dissertation, Aalto University, Espoo, Sep. 2013. [Online]. Available: <https://aaltodoc.aalto.fi/handle/123456789/10945>
- [19] T. C. Cheston and E. J. Luoma, "Constant-K lenses," *APL Technical Digest*, pp. 8–11, Mar.–Apr. 1963.
- [20] A. Balankutty, S. Pellerano, T. Kamgaing, K. Tantwai, and Y. Palaskas, "A 12-element 60 GHz CMOS phased array transmitter on LTCC package with integrated antennas," in *IEEE Asian Solid-State Circuits Conference 2011*, Nov. 2011, pp. 273–276.
- [21] D. G. Kam, D. Liu, A. Natarajan, S. Reynolds, H. Chen, and B. A. Floyd, "LTCC packages with embedded phased-array antennas for 60 GHz communications," *IEEE Microw. Wireless Compon. Lett.*, vol. 21, no. 3, pp. 142–144, Mar. 2011.
- [22] D. G. Kam, D. Liu, A. Natarajan, S. K. Reynolds, and B. A. Floyd, "Organic packages with embedded phased-array antennas for 60-GHz wireless chipsets," *IEEE Trans. Compon. Packag. Manuf. Technol.*, vol. 1, no. 11, pp. 1806–1814, Nov. 2011.
- [23] J. Kuo, Y. Lu, T. Huang, Y. Chang, Y. Hsieh, P. Peng, I. Chang, T. Tsai, K. Kao, W. Hsiung, J. Wang, Y. A. Hsu, K. Lin, H. Lu, Y. Lin, L. Lu, T. Huang, R. Wu, and H. Wang, "60-GHz four-element phased-array transmit/receive system-in-package using phase compensation techniques in 65-nm flip-chip CMOS process," *IEEE Trans. Microw. Theory Techn.*, vol. 60, no. 3, pp. 743–756, Mar. 2012.
- [24] E. Cohen, M. Ruberto, M. Cohen, O. Degani, S. Ravid, and D. Ritter, "A CMOS bidirectional 32-element phased-array transceiver at 60 GHz with LTCC antenna," *IEEE Trans. Microw. Theory Techn.*, vol. 61, no. 3, pp. 1359–1375, Mar. 2013.
- [25] S. Emami, R. F. Wiser, E. Ali, M. G. Forbes, M. Q. Gordon, X. Guan, S. Lo, P. T. McElwee, J. Parker, J. R. Tani, J. M. Gilbert, and C. H. Doan, "A 60 GHz CMOS phased-array transceiver pair for multi-Gb/s wireless communications," in *2011 IEEE International Solid-State Circuits Conference*, Feb. 2011, pp. 164–166.
- [26] M. SeyyedEsfahlan, E. Öztürk, M. Kaynak, and I. Tekin, "77-GHz four-element phased-array radar receiver front end," *IEEE Trans. Compon. Packag. Manuf. Technol.*, vol. 6, no. 8, pp. 1162–1173, Aug. 2016.
- [27] A. Valdes-Garcia, A. Natarajan, D. Liu, M. Sanduleanu, X. Gu, M. Ferriss, B. Parker, C. Baks, J. Plouchart, H. Ainspan, B. Sadhu, M. Islam, and S. Reynolds, "A fully-integrated dual-polarization 16-element W-band phased-array transceiver in SiGe BiCMOS," in *2013 IEEE Radio Frequency Integrated Circuits Symposium (RFIC)*, June 2013, pp. 375–378.
- [28] S. Shahramian, M. J. Holyoak, and Y. Baeyens, "A 16-element W-band phased-array transceiver chipset with flip-chip PCB integrated antennas for multi-gigabit wireless data links," *IEEE Trans. Microw. Theory Techn.*, vol. 66, no. 7, pp. 3389–3402, July 2018.

- [29] P. Peng, P. Chen, C. Kao, Y. Chen, and J. Lee, "A 94 GHz 3D image radar engine with 4TX/4RX beamforming scan technique in 65 nm CMOS technology," *IEEE J. Solid-State Circuits*, vol. 50, no. 3, pp. 656–668, Mar. 2015.
- [30] Y. A. Atesal, B. Cetinoneri, M. Chang, R. Alhalabi, and G. M. Rebeiz, "Millimeter-wave wafer-scale silicon BiCMOS power amplifiers using free-space power combining," *IEEE Trans. Microw. Theory Techn.*, vol. 59, no. 4, pp. 954–965, Apr. 2011.
- [31] S. Zahir, O. D. Gurbuz, A. Kar-Roy, S. Raman, and G. M. Rebeiz, "60-GHz 64- and 256-elements wafer-scale phased-array transmitters using full-reticle and subreticle stitching techniques," *IEEE Trans. Microw. Theory Techn.*, vol. 64, no. 12, pp. 4701–4719, Dec. 2016.
- [32] S. Shahramian, M. J. Holyoak, A. Singh, and Y. Baeyens, "A fully integrated 384-element, 16-tile, W-band phased array with self-alignment and self-test," *IEEE J. Solid-State Circuits*, vol. 54, no. 9, pp. 2419–2434, Sep. 2019.
- [33] T. Sowlati, S. Sarkar, B. G. Perumana, W. L. Chan, A. Papio Toda, B. Afshar, M. Boers, D. Shin, T. R. Mercer, W. Chen, A. Grau Besoli, S. Yoon, S. Kyriazidou, P. Yang, V. Aggarwal, N. Vakilian, D. Rozenblit, M. Kahrizi, J. Zhang, A. Wang, P. Sen, D. Murphy, A. Sajjadi, A. Mehrabani, E. Kornaros, K. Low, K. Kimura, V. Roussel, H. Xie, and V. Kodavati, "A 60-GHz 144-element phased-array transceiver for backhaul application," *IEEE J. Solid-State Circuits*, vol. 53, no. 12, pp. 3640–3659, Dec. 2018.
- [34] A. Townley, P. Swirhun, D. Titz, A. Bisognin, F. Giancesello, R. Pilard, C. Luxey, and A. M. Niknejad, "A 94-GHz 4TX–4RX phased-array FMCW radar transceiver with antenna-in-package," *IEEE J. Solid-State Circuits*, vol. 52, no. 5, pp. 1245–1259, May 2017.
- [35] I. Aziz, R. Dahlbäck, E. Öjefors, K. Sjögren, A. Rydberg, and D. Dancila, "60 GHz compact broadband antenna arrays with wide-angle beam steering," *J. Eng.*, vol. 2019, no. 8, pp. 5407–5414, Aug. 2019.
- [36] J. G. Lee, T. H. Jang, G. H. Park, H. S. Lee, C. W. Byeon, and C. S. Park, "A 60-GHz four-element beam-tapering phased-array transmitter with a phase-compensated VGA in 65-nm CMOS," *IEEE Trans. Microw. Theory Techn.*, vol. 67, no. 7, pp. 2998–3009, July 2019.
- [37] A. Rashidian, S. Jafarlou, A. Tomkins, K. Law, M. Tazlauanu, and K. Hayashi, "Compact 60 GHz phased-array antennas with enhanced radiation properties in flip-chip BGA packages," *IEEE Trans. Antennas Propag.*, vol. 67, no. 3, pp. 1605–1619, Mar. 2019.
- [38] B. Rupakula, A. Nafe, S. Zahir, Y. Wang, T. Lin, and G. Rebeiz, "63.5–65.5-GHz transmit/receive phased-array communication link with 0.5–2 Gb/s at 100–800 m and $\pm 50^\circ$ scan angles," *IEEE Trans. Microw. Theory Techn.*, vol. 66, no. 9, pp. 4108–4120, Sep. 2018.
- [39] E. Topak, J. Hasch, C. Wagner, and T. Zwick, "A novel millimeter-wave dual-fed phased array for beam steering," *IEEE Trans. Microw. Theory Techn.*, vol. 61, no. 8, pp. 3140–3147, Aug. 2013.
- [40] G. V. Eleftheriades, Y. Brand, J. F. Zurcher, and J. R. Mosig, "ALPSS: A millimetre-wave aperture-coupled patch antenna on a substrate lens," *Electronics Letters*, vol. 33, no. 3, pp. 169–170, Jan. 1997.
- [41] N. T. Nguyen, R. Sauleau, M. Ettorre, and L. L. Coq, "Focal array fed dielectric lenses: an attractive solution for beam reconfiguration at millimeter waves," *IEEE Trans. Antennas Propag.*, vol. 59, no. 6, pp. 2152–2159, June 2011.

- [42] J. R. Costa, E. B. Lima, and C. A. Fernandes, "Compact beam-steerable lens antenna for 60-GHz wireless communications," *IEEE Trans. Antennas Propag.*, vol. 57, no. 10, pp. 2926–2933, Oct. 2009.
- [43] J. Ala-Laurinaho, J. Aurinsalo, A. Karttunen, M. Kaunisto, A. Lamminen, J. Nurmiharju, A. V. Räisänen, J. Säily, and P. Wainio, "2-D beam-steerable integrated lens antenna system for 5G E-band access and backhaul," *IEEE Trans. Microw. Theory Techn.*, vol. 64, no. 7, pp. 2244–2255, July 2016.
- [44] A. Artemenko, A. Mozharovskiy, A. Maltsev, R. Maslennikov, A. Sevastyanov, and V. Ssorin, "Experimental characterization of E-band two-dimensional electronically beam-steerable integrated lens antennas," *IEEE Antennas Wireless Propag. Lett.*, vol. 12, pp. 1188–1191, Sep. 2013.
- [45] B. Schoenlinner, X. Wu, J. P. Ebling, G. V. Eleftheriades, and G. M. Rebeiz, "Wide-scan spherical-lens antennas for automotive radars," *IEEE Trans. Microw. Theory Techn.*, vol. 50, no. 9, pp. 2166–2175, Sep. 2002.
- [46] A. Karttunen, J. Ala-Laurinaho, R. Sauleau, and A. V. Räisänen, "Extended hemispherical integrated lens antenna with feeds on a spherical surface," in *2013 7th European Conference on Antennas and Propagation (EuCAP)*, Apr. 2013, pp. 2539–2543.
- [47] N. G. Alexopoulos, P. B. Katehi, and D. B. Rutledge, "Substrate optimization for integrated circuit antennas," *IEEE Trans. Microw. Theory Techn.*, vol. 31, no. 7, pp. 550–557, July 1983.
- [48] "Design guidelines for low temperature co-fired ceramic modules," https://www.vtt.fi/files/research/mel/ltcc_design_rules.pdf, VTT Technical Research Centre of Finland Ltd, Oulu, Finland, accessed: 2019-02-20.
- [49] "A6M/A6M-E high frequency LTCC tape system," <https://www.ferro.com/-/media/files/resources/electronic-materials/ferro-electronic-materials-a6m-e-ltcc-tape-system.pdf>, Ferro Corporation, Mayfield Heights, OH, USA, accessed: 2019-02-20.
- [50] A. Lamminen, "Design of millimetre-wave antennas on low temperature co-fired ceramic substrates," M. Sc. thesis, Helsinki University of Technology, Espoo, Finland, Jan. 2006. [Online]. Available: <http://lib.tkk.fi/Dipl/2006/urn006166.pdf>
- [51] "Ultralam 3850 datasheet," <http://www.rogerscorp.com/documents/730/index.aspx>, Rogers Corporation, Chandler, AZ, USA, accessed: 2019-02-20.
- [52] D. C. Thompson, O. Tantot, H. Jallageas, G. E. Ponchak, M. M. Tentzeris, and J. Papapolymerou, "Characterization of liquid crystal polymer (LCP) material and transmission lines on LCP substrates from 30 to 110 GHz," *IEEE Trans. Microw. Theory Techn.*, vol. 52, no. 4, pp. 1343–1352, Apr. 2004.
- [53] "RO3003 datasheet," <https://www.rogerscorp.com/documents/722/acs/RO3000-Laminate-Data-Sheet-RO3003-RO3006-RO3010-RO3035.pdf>, Rogers Corporation, Chandler, AZ, USA, accessed: 2019-02-20.
- [54] Rogers Corporation, "New laminates enable 79 GHz technology advancements," *Microwave Journal*, vol. 58, no. 12, pp. 1–3, Dec. 2015.
- [55] "TLY datasheet," <http://www.taconic.co.kr/download/TLY.pdf>, Taconic, Petersburg, NY, USA, accessed: 2019-04-18.
- [56] "Astra MT77 datasheet," <https://www.isola-group.com/wp-content/uploads/data-sheets/astra-mt77.pdf>, Isola Group, Chandler, AZ, USA, accessed: 2019-04-20.

- [57] "PCB Material Selection for RF, Microwave and Millimeter-wave Design," <https://www.isola-group.com/wp-content/uploads/PCB-Material-Selection-for-RF-Microwave-and-Millimeter-wave-Designs-1.pdf>, Isola Group, Chandler, AZ, USA, accessed: 2019-04-20.
- [58] "Optiprint technical information," <http://optiprint.ch/default-wAssets/docs/zertifikate/technische-information-english.pdf>, Optiprint, Berneck, Switzerland, accessed: 2019-02-20.
- [59] F. Huang, C. Lee, C. Kuo, and C. Luo, "MMW antenna in IPD process for 60-GHz WPAN applications," *IEEE Antennas Wireless Propag. Lett.*, vol. 10, pp. 565–568, June 2011.
- [60] A. Bisognin, D. Titz, F. Ferrero, G. Jacquemod, R. Pilard, F. Ganesello, D. Gloria, P. Brachet, C. Laporte, H. Ezzeddine, and C. Luxey, "PCB integration of a Vivaldi antenna on IPD technology for 60-GHz communications," *IEEE Antennas Wireless Propag. Lett.*, vol. 13, pp. 678–681, Mar. 2014.
- [61] S. Hage-Ali, N. Tiercelin, P. Coquet, R. Sauleau, H. Fujita, V. Preobrazhensky, and P. Pernod, "A millimeter-wave microstrip antenna array on ultra-flexible micromachined polydimethylsiloxane (PDMS) polymer," *IEEE Antennas Wireless Propag. Lett.*, vol. 8, pp. 1306–1309, Dec. 2009.
- [62] M. Kyrö, V. Kolmonen, P. Vainikainen, D. Titz, and C. Villeneuve, "60 GHz membrane antenna array for beam steering applications," in *2012 6th European Conference on Antennas and Propagation (EUCAP)*, Mar. 2012, pp. 2770–2774.
- [63] S. Hsu, K. Wei, C. Hsu, and H. Ru-Chuang, "A 60-GHz millimeter-wave CPW-fed Yagi antenna fabricated by using 0.18- μm CMOS technology," *IEEE Electron Device Lett.*, vol. 29, no. 6, pp. 625–627, June 2008.
- [64] C. Liu and R. G. Rojas, "V-band integrated on-chip antenna implemented with a partially reflective surface in standard 0.13- μm BiCMOS technology," *IEEE Trans. Antennas Propag.*, vol. 64, no. 12, pp. 5102–5109, Dec. 2016.
- [65] D. M. Pozar, "Microstrip antennas," *Proc. IEEE*, vol. 80, no. 1, pp. 79–91, Jan. 1992.
- [66] R. Coccioli, F.-R. Yang, K.-P. Ma, and T. Itoh, "Aperture-coupled patch antenna on UC-PBG substrate," *IEEE Trans. Microw. Theory Techn.*, vol. 47, no. 11, pp. 2123–2130, Nov. 1999.
- [67] J. Ollikainen and P. Vainikainen, "Design and bandwidth optimization of dual-resonant patch antennas," Helsinki University of Technology, Radio Laboratory publications, Espoo, Tech. Rep. S 252, Mar. 2002. [Online]. Available: <http://lib.tkk.fi/Diss/2004/isbn9512273810/article1.pdf>
- [68] M. Tiuri, S. Tallqvist, and S. Urpo, "Chain antenna," in *1974 Antennas and Propagation Society International Symposium*, vol. 12, June 1974, pp. 274–277.
- [69] "TGS4306-FC datasheet," <http://www.mouser.com/ds/2/412/TGS4306-FC-198621.pdf>, TriQuint/Qorvo, Hillsboro, Oregon, United States, accessed: 2019-01-02.
- [70] A. Vahdati, "Design and characterisation of monolithic millimetre-wave integrated circuits for phased-array transmitter front-end," Ph.D. dissertation, Aalto University, Espoo, Nov. 2017. [Online]. Available: <http://urn.fi/URN:ISBN:978-952-60-7699-7>
- [71] J.-H. Lee, N. Kidera, S. Pinel, J. Laskar, and M. M. Tentzeris, "60 GHz high-gain aperture-coupled microstrip antennas using soft-surface and stacked cavity on LTCC multilayer technology," in *2006 IEEE Antennas and Propagation Society International Symposium*, July 2006, pp. 1621–1624.

- [72] S. Beer, L. Pires, C. Rusch, J. Paaso, and T. Zwick, "A 122 GHz microstrip slot antenna with via-fence resonator in LTCC technology," in *2012 6th European Conference on Antennas and Propagation (EUCAP)*, Mar. 2012, pp. 1329–1332.
- [73] C. Heine, S. Beer, C. Rusch, and T. Zwick, "Via-fence antennas on LTCC for radar applications at 122 GHz," in *2013 European Microwave Conference*, Oct. 2013, pp. 40–43.
- [74] A. Karttunen, J. Ala-Laurinaho, R. Sauleau, and A. V. Räsänen, "Reduction of internal reflections in integrated lens antennas for beam-steering," *Progress in Electromagnetics Research*, vol. 134, pp. 63–78, 2013.
- [75] J. Ala-Laurinaho, A. Lamminen, J. Säily, R. Luomaniemi, M. Kaunisto, T. Kovarik, P. Wainio, and A. V. Räsänen, "Dual-polarised lens feed arrays and end-fire antennas in E-band," in *2016 10th European Conference on Antennas and Propagation (EuCAP)*, Apr. 2016, pp. 1–5.
- [76] "CST MICROWAVE STUDIO," <https://www.cst.com/products/cstmws>, CST - Computer Simulation Technology, Darmstadt, Germany, accessed: 2019-01-02.
- [77] "1.0mm end launch connector: 2492-04A-6," <http://mpd.southwestmicrowave.com/products/endLaunch.php>, Southwest Microwave, Tempe, Arizona, United States, accessed: 2019-01-02.
- [78] M. Kantanen, J. Holmberg, M. Varonen, and A. Rantala, "Digitally controlled vector modulator SiGe MMIC for millimeter-wave phased array applications," in *2018 11th German Microwave Conference (GeMiC)*, Mar. 2018, pp. 51–54.

ISBN 978-952-60-8778-8 (printed)

ISBN 978-952-60-8779-5 (pdf)

ISSN 1799-4934 (printed)

ISSN 1799-4942 (pdf)

Aalto University
School of Electrical Engineering
Department of Electronics and Nanoengineering
www.aalto.fi

**BUSINESS +
ECONOMY**

**ART +
DESIGN +
ARCHITECTURE**

**SCIENCE +
TECHNOLOGY**

CROSSOVER

**DOCTORAL
DISSERTATIONS**