Computational Problems in Simulation of Electrical Machines

Lauri Perkkiö

Computational Problems in Simulation of Electrical Machines

Lauri Perkkiö

A doctoral dissertation completed for the degree of Doctor of Science (Technology) to be defended, with the permission of the Aalto University School of Science, at a public examination held at the lecture hall M1, and also via remote technology, on 22nd January 2021 at 12.

Aalto University
School of Science
Department of Mathematics and Systems Analysis
Applied mathematics

Supervising professor

Assistant Professor Antti Hannukainen, Aalto University, Finland

Preliminary examiners

Professor Stefan Kurz, Technische Universität Darmstadt, Germany

Associate Professor Noemi Petra, University of California, USA

Opponent

Professor Herbert de Gersem, Technische Universität Darmstadt, Germany

Aalto University publication series

DOCTORAL DISSERTATIONS 200/2020

© 2020 Lauri Perkkio

ISBN 978-952-64-0164-5 (printed)

ISBN 978-952-64-0165-2 (pdf)

ISSN 1799-4934 (printed)

ISSN 1799-4942 (pdf)

<http://urn.fi/URN:ISBN:978-952-64-0165-2>

Unigrafia Oy

Helsinki 2020

Finland

Printed matter
4041-0619

Author

Lauri Perkkiö

Name of the doctoral dissertation

Computational Problems in Simulation of Electrical Machines

Publisher School of Science**Unit** Department of Mathematics and Systems Analysis**Series** Aalto University publication series DOCTORAL DISSERTATIONS 200/2020**Field of research** Mathematics**Manuscript submitted** 20 August 2020**Date of the defence** 22 January 2021**Permission for public defence granted (date)** 21 September 2020**Language** English☐ **Monograph**☒ **Article dissertation**☐ **Essay dissertation****Abstract**

This thesis deals with computational challenges related to simulation of electrical machines. Electromagnetic fields and heat conduction in the machines are modeled by partial differential equations (PDEs), which are treated numerically by using the finite element (FE) method combined with appropriate time integration schemes. The uniting theme of this work is the prediction of iron losses in electrical machines.

Simulating energy losses and mechanical torque in an electrical machine involves computation of the energy in the system, and a time integration method may introduce numerical errors in such computations. Additional complications are caused by a moving subdomain in a machine, and the fact that the resulting discretized problem does not lead into a system of ordinary differential equations (ODEs), but to a differential-algebraic equation (DAE). All this has to be taken into account to construct proper time integration schemes, which is the first topic of thesis.

A core of an electrical machine often consists of a hysteretic ferromagnetic material. Conventionally, hysteresis is neglected in electromagnetic simulations, as its inclusion is complicated and computationally expensive. In this thesis, we propose and test numerically a method to incorporate the Jiles-Atherton magnetic hysteresis model into a FE simulation.

The last article approaches the iron loss prediction from an inverse problem perspective. The iron loss acts as an unknown heat source term in the heat equation, and the source is reconstructed from a limited number of temperature measurements conducted on and inside the machine. A computational framework and temperature sensor placement optimization is proposed and numerically tested in the thesis.

Keywords electric machines, FEM, inverse problem, numerical methods**ISBN (printed)** 978-952-64-0164-5**ISBN (pdf)** 978-952-64-0165-2**ISSN (printed)** 1799-4934**ISSN (pdf)** 1799-4942**Location of publisher** Helsinki**Location of printing** Helsinki **Year** 2020**Pages** 102**urn** <http://urn.fi/URN:ISBN:978-952-64-0165-2>

Tekijä

Lauri Perkkiö

Väitöskirjan nimi

Laskennallisia ongelmia sähkökoneiden numeerisessa mallintamisessa

Julkaisija Perustieteiden korkeakoulu**Yksikkö** Matematiikan ja systeemianalyysin laitos**Sarja** Aalto University publication series DOCTORAL DISSERTATIONS 200/2020**Tutkimusala** Matematiikka**Käsikirjoituksen pvm** 20.08.2020**Väitöspäivä** 22.01.2021**Väittelyluvan myöntämispäivä** 21.09.2020**Kieli** Englanti☐ **Monografia**☒ **Artikkeliväitöskirja**☐ **Esseeväitöskirja****Tiivistelmä**

Tässä väitöskirjassa käsitellään sähkökoneiden mallintamiseen liittyviä laskennallisia haasteita. Koneissa esiintyviä sähkömagneettisia kenttiä ja lämmönjohtumista kuvataan osittaisdifferentiaaliyhtälöillä (ODY), joita ratkaistaan numeerisesti elementtimenetelmän ja sopivan aikaintegrointimenetelmän avulla. Tätä kirjaa yhdistävä teema on sähkökoneissa esiintyvien rautahäviöiden mallinnus.

Sähkökoneen energiahäviöiden ja vääntömomentin laskeminen edellyttää systeemin energian laskentaa numeerisesti. Tämä liittyy käytettyihin aikaintegroimismenetelmiin, jotka voivat aiheuttaa numeerista virhettä energian laskennassa. Ongelman monimutkaisuutta lisää muuttuva laskenta-alue pyörivässä sähkökoneessa, ja se, että diskretisaatiosta seuraava ongelma ei ole tavallinen differentiaaliyhtälö, vaan differentiaaliyhtälö. Näiden asioiden huomioonottaminen on yksi tämän kirjan aiheista.

Sähkökoneen ydin koostuu usein hystereettisestä ferromagneettisesta materiaalista. Tavallisesti, tätä ei oteta simulaatioissa suoraan huomioon, koska se vaatii huomattavaa laskennallista lisätyötä. Tässä työssä ehdotamme ja testaamme numeerisesti uutta laskennallista menetelmää, jonka avulla Jiles-Atherton hystereesimallia voidaan käyttää elementtimenetelmään perustuvassa simulaatiossa.

Kirjan viimeisessä artikkelissa rautahäviön määrittäminen muotoillaan inversio-ongelmana. Rautahäviötä käsitellään lämpöyhtälön tuntemattomana lähdeterminä, ja tämä lähde pyritään rekonstruoidaan rajallisesta määrästä lämpötilamittauksia koneen pinnalla ja sen sisällä. Inversio-ongelman ratkaisun ja lämpötilamittausten sijainnin optimointiin annetaan laskennalliset puitteet, ja menetelmiä testataan numeerisesti.

Avainsanat FEM, inversio-ongelma, numeeriset menetelmät, sähkökoneet**ISBN (painettu)** 978-952-64-0164-5**ISBN (pdf)** 978-952-64-0165-2**ISSN (painettu)** 1799-4934**ISSN (pdf)** 1799-4942**Julkaisupaikka** Helsinki**Painopaikka** Helsinki**Vuosi** 2020**Sivumäärä** 102**urn** <http://urn.fi/URN:ISBN:978-952-64-0165-2>

Preface

This thesis collects the work done in Aalto University, the Department of Mathematics and Systems Analysis, and the Department of Electrical Engineering and Automation. The thesis concludes several years of studies in Otaniemi, where I started as an Engineering Physics student in TKK.

The supervisor of my Master's Thesis, late Prof. Timo Eirola, asked me in 2013 if I was interested in pursuing a doctoral degree, and if I preferred a practical or a theoretical topic. I had no idea, so my answer was a confident “a practical one”. This led to a collaboration with the group of Electromechanics in the School of Electrical Engineering and Automation.

Prof. Eirola passed away in 2016. Prof. Antti Hannukainen became my supervisor in mathematics and positive Aalto spirit. In the inverse problem project, Prof. Nuutti Hyvönen gave a significant support. I thank Profs. Eirola, Hannukainen, and Hyvönen for their guidance.

Thanks to all Maths people. I thank Prof. Antero Arkkio, Prof. Paavo Rasilo, Dr. Bishal Silwal, Brijesh, and several other people in Electromechanics for both technical and non-technical discussions, and cakes. I thank Prof. Herbert de Gerssem, who acted as the opponent. I thank pre-examiners Prof. Stefan Kurz and Prof. Noemi Petra for their feedback.

Kiitos perheelle, ystäville, ja monille avulaille ihmisille. Kesäkuussa 2015 äkillisesti kuolleen isäni muistolle.

Helsinki, December 14, 2020,

Lauri Perkkiö

Contents

Preface	1
Contents	3
List of Publications	5
Author's Contribution	7
1. Introduction	9
1.1 Induction Machines	9
1.2 Quasistatic Electromagnetic Problem	11
1.2.1 Maxwell's Equations and Constitutive laws	11
1.2.2 Low-frequency Regime in 2D	12
1.2.3 Potential Formulation	13
1.3 Heat Conduction Problem	14
1.3.1 Heat Equation	14
1.4 Contributions and Novelty	14
2. Parabolic PDEs and Their Discretization	17
2.1 Elliptic Boundary Value Problem	17
2.1.1 Linear Problem	18
2.1.2 Quasilinear Problem	18
2.2 Finite Element Discretization	19
2.2.1 Finite Element Solution of Linear Problem	20
2.2.2 Finite Element Solution of Quasilinear Problem	21
2.3 Parabolic Initial/Boundary Value Problem	21
2.3.1 Linear Parabolic Problem	22
2.4 Time Discretization	22
3. Research Problems and Findings	25

3.1	Mechanical Rotation, Time Integration, Energy Balance, and Torque Computation	25
3.1.1	Rotating Subdomain	25
3.1.2	Differential-Algebraic Equation	26
3.1.3	Magnetic Field Energy and Torque Computation	27
3.1.4	Energy Balance	28
3.2	Jiles-Atherton Model in Finite Element Simulation	28
3.3	Iron Loss Determination as Inverse Heat Source Problem . . .	29
	References	31
	Errata	35
	Publications	37

List of Publications

This thesis consists of an overview and of the following publications which are referred to in the text by their Roman numerals.

I Paavo Rasilo, Lauri Perkkiö, Antti Hannukainen, Bishal Silwal, Timo Eirola, Antero Arkkio. Instantaneous Power Balance in Finite-Element Simulation of Electrical Machines. *IEEE Transactions on Magnetics*, Vol. 50, May 2014.

II Lauri Perkkiö, Paavo Rasilo, Bishal Silwal, Antti Hannukainen, Antero Arkkio, Timo Eirola. Energy-Preserving Methods and Torque Computation From Energy Balance in Electrical Machine Simulations. *IEEE Transactions on Magnetics*, Vol. 52, August 2016.

III Lauri Perkkiö, Brijesh Upadhaya, Antti Hannukainen, Paavo Rasilo. Stable Adaptive Method to Solve FEM Coupled With Jiles–Atherton Hysteresis Model. *IEEE Transactions on Magnetics*, Vol. 54, February 2018.

IV Antti Hannukainen, Nuutti Hyvönen, Lauri Perkkiö. Inverse Heat Source Problem and Experimental Design for Determining Iron Loss Distribution. Submitted to *SIAM Journal on Scientific Computing*, April 6th 2020.

Author's Contribution

Publication I: “Instantaneous Power Balance in Finite-Element Simulation of Electrical Machines”

The author proposed some of the methods, and participated in their implementation with Hannukainen and Rasilo.

Publication II: “Energy-Preserving Methods and Torque Computation From Energy Balance in Electrical Machine Simulations”

The author proposed the methods, provided the analysis, wrote the text, and implemented the methods on the base provided by Hannukainen and Rasilo.

Publication III: “Stable Adaptive Method to Solve FEM Coupled With Jiles–Atherton Hysteresis Model”

The author proposed the methods, provided the analysis, wrote the text, and implemented the methods using Publication I as the basis.

Publication IV: “Inverse Heat Source Problem and Experimental Design for Determining Iron Loss Distribution”

The author developed and implemented the computational methods and participated in writing the article.

1. Introduction

This thesis studies computational problems related to simulating electromagnetic fields and heat conduction in electric machines, such as electric motors, generators, or transformers. One goal of such simulations is to model energy losses, i.e., the amount of energy that is wasted mostly as heat. As electric motors consume approximately 45% of the electricity worldwide [28], the topic has not only practical, but also environmental and economic importance.

When analyzing electrical machines, modeling a quasistatic electromagnetic field or dynamic heat conduction results in a so-called parabolic initial/boundary value problem, a specific type of a partial differential equation (PDE). A standard method to numerically solve these PDEs is the finite element (FE) method, combined with a suitable time integration scheme. The resulting discretized problems involve large systems of nonlinear equations, which need to be solved for several time steps. Thus, special care has to be given for the computational cost of the methods. The aim of this thesis is to develop numerical methods for time integration, torque computation, incorporation of the Jiles-Atherton magnetic hysteresis model into a FE simulation, and an inverse heat source problem.

This summary is organized as follows. Chapter 1 introduces the relevant physical models. Chapter 2 provides a mathematical framework for parabolic initial/boundary value problems and their discretization. Chapter 3 discusses the problems studied in Publications and outlines the results.

1.1 Induction Machines

Induction machines are a specific type of electric machines whose operation is based on the principle of electromagnetic induction. In this Section, we consider the induction motor shown in Figure 1.1a. The major components of the motor are the stator and the rotor. The stator is the outer cylindrical part,

Figure 1.1. a) Induction motor, with detached rotor. The cylindrical object attached to the shaft is called the rotor. The stator core and windings are contained inside the case on the right. b) Geometry of cross section, with coarse FE mesh. The subdomains are shaft (Sh), rotor core (RC), rotor cage bars (RB), air gap (AG), stator core (SC), and the stator windings (SW)

and it contains conducting copper coils connected to a voltage supply. The rotor is the inner, rotating part, and it exerts mechanical force into the application. The rotor includes a conducting cage, which “captures” the magnetic field energy supplied from the input. The core of the stator and the rotor is filled with ferromagnetic material, whose purpose is to amplify the magnetic field. The thin empty space between the stator and the rotor is called the air gap. Figure 1.1b depicts a cross section of the machine.

The conversion of electrical energy into mechanical energy in the machine shown in Figure 1.1 is based on the following physical principles; the same fundamentals hold for other induction machines. Time-varying electric currents in the stator windings (“primary coil”) create a time-varying magnetic field (by *Ampère’s law*) in the rotor bars (“secondary coil”), which in turn induces an electric field therein (*Faraday’s law*). The induced electric field generates a current in the bars (*Ohm’s law*). The current in a magnetic field experiences a so-called *Lorentz force*, which causes torque in the rotor. The mathematical model describing the electromagnetic phenomenon is called Maxwell’s equations, which are a set of PDEs. Complemented with constitutive relations that account for the material behaviour, Maxwell’s equations describe how the electric field, magnetic field, electric charges, and electric currents interact.

Electromagnetic simulations are used in applications such as electrical machine design and real-time control systems [26]. The quantities of interest are, e.g., induced currents and voltages, generated forces and torques, and power losses. One specific quantity of interest is the iron loss, i.e., the energy loss

occurring in the laminated steel sheets in the rotor and stator cores [18]. Using existing iron loss models, the discrepancy between predicted and measured iron losses are of order 10-45% [18, p.130]. In a sense, all Publications included in this thesis are related to improving the energy and loss computations in electrical machines.

1.2 Quasistatic Electromagnetic Problem

In this Section, we derive a PDE describing electromagnetic fields inside an electric machine. We start from Maxwell's equations and introduce simplifications used in modeling electrical machines operating at low frequencies. A more mathematically rigorous treatment is given in Chapter 2.

1.2.1 Maxwell's Equations and Constitutive laws

In the macroscopic formulation of Maxwell's equations [15], the electromagnetic field in matter consists of the electric field $\vec{E}$ and magnetic flux density $\vec{B}$, with electric flux density $\vec{D}$ and magnetic field strength $\vec{H}$ as “auxiliary fields”. The fields are connected with the charge density ρ and the current density $\vec{J}$. All quantities are position $\vec{x} = (x, y, z)$ - and time t -dependent vector fields $\mathbb{R}^3 \times \mathbb{R} \rightarrow \mathbb{R}^3$, except ρ , which is $\mathbb{R}^3 \times \mathbb{R} \rightarrow \mathbb{R}$ (neglecting distributions such as point charges and surface currents for brevity). The four Maxwell's equations relating these six quantities are

$$\nabla \cdot \vec{D} = \rho \quad (\text{Gauss' law}), \quad (1.1a)$$

$$\nabla \cdot \vec{B} = 0 \quad (\text{Gauss' law for magnetism}), \quad (1.1b)$$

$$\nabla \times \vec{E} = -\partial_t \vec{B} \quad (\text{Faraday's law}), \quad (1.1c)$$

$$\nabla \times \vec{H} = \vec{J} + \partial_t \vec{D} \quad (\text{Amperè's law}). \quad (1.1d)$$

In the scope of Publications I and II, the constitutive equations are of the form

$$\vec{D} = \epsilon_0 \vec{E} \quad (1.2)$$

$$\vec{H} = \nu(\vec{x}, |\vec{B}|) \vec{B}, \quad (1.3)$$

where ϵ_0 is the vacuum permittivity, ν is a material- and field magnitude-dependent magnetic reluctivity, and $|\cdot|$ is the Euclidean norm. The current density $\vec{J}$ is considered to consist of “imposed” and “induced” components, $\vec{J} = \vec{J}_{\text{imp}} + \vec{J}_{\text{ind}}$. The third constitutive relation is the Ohm's law,

$$\vec{J}_{\text{ind}} = \sigma(\vec{x}) \vec{E}, \quad (1.4)$$

Figure 1.2. a) Measured hysteretic H - B characteristics of a ferromagnetic steel sheet.
 b) A single-valued H - B curve used in FE simulations. Iron reluctivity is obtained by $\nu_{\text{Fe}}(B) = H/B$.

where the (zero or positive) material-dependent constant σ is called the electric conductivity. With the problem at hand, ν and σ are determined experimentally for different materials. An example of a measured H - B characteristic in ferromagnetic iron is shown in Figure 1.2a. In conventional FE electromagnetic simulations, the curve connecting the tips of the minor loops is used to obtain a single-valued H - B relation, as shown in Figure 1.2b.

1.2.2 Low-frequency Regime in 2D

The following approximations provide an adequate model to analyze the electromagnetic properties of an electric machine [3]. The machine is assumed to be uniform and “infinitely long” along the rotation axis, which is labeled the z -axis. The following are assumed:

$$\vec{J}(x, y, z, t) = J(x, y, t)\vec{e}_z, \quad (1.5a)$$

$$\vec{B}(x, y, z, t) = B_x(x, y, t)\vec{e}_x + B_y(x, y, t)\vec{e}_y, \quad (1.5b)$$

$$\vec{E}(x, y, z, t) = E(x, y, t)\vec{e}_z, \quad (1.5c)$$

with $\vec{H} \uparrow\uparrow \vec{B}$ and $\vec{D} \uparrow\uparrow \vec{E}$ resulting from (1.2) and (1.3). In most practical electrical machine designs, it is realistic to assume an absence of free charges, $\rho = 0$, and thus

$$\nabla \cdot \vec{D} = 0. \quad (1.6)$$

In this work, we consider electrical machines that operate at a low frequency, such as 50 Hz, so we assume the displacement current is small, $|\partial_t \vec{D}| \ll |\vec{J}|$. Under this assumption, $\partial_t \vec{D}$ is omitted from Ampère’s law (1.1d), leading to

the so-called quasistatic approximation

$$\nabla \times \vec{H} = \vec{J}. \quad (1.7)$$

Combining (1.1-1.7), Maxwell's equations (1.1) reduce into

$$\nabla \cdot (E(x, y, t)\vec{e}_z) = 0, \quad (1.8a)$$

$$\nabla \cdot \vec{B}(x, y, t) = 0, \quad (1.8b)$$

$$\nabla \times (E(x, y, t)\vec{e}_z) = -\partial_t \vec{B}(x, y, t), \quad (1.8c)$$

$$\nabla \times [\nu(\vec{x}, |\vec{B}|) \vec{B}(x, y, t)] - \sigma(\vec{x})E(x, y, t)\vec{e}_z = J_{\text{imp}}(x, y, t)\vec{e}_z, \quad (1.8d)$$

where the first equation holds trivially.

1.2.3 Potential Formulation

We use the following potential formulation for (1.8) to further simplify the problem [3, 29]. Let the bounded, simply connected domain $\Omega \subset \mathbb{R}^2$ represent a cross-section of the machine. There exists a “vector” potential $\vec{A}(x, y, t) = A(x, y, t)\vec{e}_z$ such that

$$\vec{B}(x, y, t) = \nabla \times [A(x, y, t)\vec{e}_z], \quad (1.9)$$

$$\vec{E}(x, y, t) = -[\partial_t A(x, y, t)]\vec{e}_z, \quad (1.10)$$

see [3, 29]. Substituting (1.9-1.10) into (1.8d), and choosing relevant initial and boundary conditions, results in the following equation for A :

$$-\nabla \cdot [\nu(\vec{x}, |\nabla A|) \nabla A] + \sigma(\vec{x})\partial_t A = J_{\text{imp}} \quad \text{in } \Omega \times (0, T), \quad (1.11a)$$

$$A = 0 \quad \text{on } \partial\Omega \times (0, T), \quad (1.11b)$$

$$A = A_0 \quad \text{in } \Omega \times \{t = 0\}. \quad (1.11c)$$

When simulating electric machines, one is often interested in the steady state given by a T_p -periodic input $J_{\text{imp}}(x, y, t + T_p) = J_{\text{imp}}(x, y, t)$ for all t . The time interval $(0, T)$ is large enough so that “an almost T_p -periodic” field $A(x, y, t + T_p) \approx A(x, y, t)$, where t is sufficiently large, is reached. The initial state A_0 is either zero, or obtained from a harmonic approximation of the steady state. The boundary condition states that $\vec{B}$ has no normal component on $\partial\Omega$, which is a realistic assumption when ν changes from small (e.g., magnetic iron) to large (e.g., air surrounding Ω).

As real-world machines are usually voltage fed, J and $\partial_t A$ are coupled via additional circuit equations with a source term depending on the input voltage. In addition, the machine may have a moving subdomain. Practical schemes for including such effects in FE simulations are covered, e.g., in [3, 4, 21].

1.3 Heat Conduction Problem

Power losses in electrical machines appear mostly as waste heat. The main heating mechanisms are resistive losses in windings, losses in the core materials, and mechanical losses on the moving parts [18]. Publication IV considers an *inverse problem*, where the aim is to determine the iron loss distribution (i.e., a heat source) by measuring the temperature on certain easily reachable parts of a machine. To this end, one must first construct a *forward model* answering the question “Given heat sources inside a machine, how does the temperature evolve?”.

1.3.1 Heat Equation

The so-called heat equation, a PDE describing heat conduction in medium, is derived from the principle of energy conservation. The physical domain is $\Omega \subset \mathbb{R}^d$, $d = 2$ or 3 . The time-dependent temperature is denoted by $u : \Omega \times [0, T) \rightarrow \mathbb{R}$. The heat (energy) density is assumed to be given by a linear relation $c(\vec{x})u$, where c is a material-dependent heat capacity. The heat flux $\vec{q}$ is assumed to satisfy $\vec{q} = -\underline{k}(\vec{x})\nabla u$, where the heat conduction coefficient $\underline{k}$ is material dependent and can be anisotropic. The requirement that the conducted, the stored, and the externally generated heat f in an infinitesimal volume add up to zero leads to the following PDE (provided with initial and commonly used boundary conditions):

$$-\nabla \cdot (\underline{k}(\vec{x})\nabla u) + c(\vec{x})\partial_t u = f(\vec{x}) \quad \text{in } \Omega \times (0, T), \quad (1.12a)$$

$$u = u_0 \quad \text{in } \Omega \times \{t = 0\}, \quad (1.12b)$$

$$u = 0 \quad \text{on } \Gamma_D, \quad (1.12c)$$

$$\partial_n u = 0 \quad \text{on } \Gamma_N, \quad (1.12d)$$

$$k(\vec{x})\partial_n u = h(\vec{x})(u - u_{\text{out}}(\vec{x})) \quad \text{on } \Gamma_R, \quad (1.12e)$$

where f is the source term, ∂_n is the outward normal derivative, u_{out} is a given ambient temperature, and $\partial\Omega = \bar{\Gamma}_D \cup \bar{\Gamma}_N \cup \bar{\Gamma}_R$ denote (disjoint) parts of the boundary with the so-called Dirichlet, Neumann, and Robin boundary conditions, respectively.

1.4 Contributions and Novelty

Publications I-II consider the time integration of differential algebraic equations (DAEs), along with energy loss and torque computation, in finite element

magnetic field simulations of rotating electrical machines. It is found that considering the commonly used Implicit Euler and Crank-Nicolson schemes as polynomial collocation methods provide a convenient approach to numerically solve the DAE and to compute the energies in a consistent manner. The connection between the “work done by the torque” and (numerical) energy balance is analyzed, and found to be related via the subdomain rotation method.

Publication III proposes a method to include the Jiles-Atherton magnetic hysteresis model in the finite element simulations considered in Publications I-II. We found the methods introduced in earlier works [12, 23] to be unstable if applied directly to the electrical machine simulations. Our proposed method solves the Jiles-Atherton material equation adaptively both in time and space, and numerical results illustrate stability and computational feasibility of the method.

Publication IV provides a computational framework for determining an unknown heat source field inside an electrical machine and finding optimal experimental design (OED) for the problem. We consider the main novelties of this work to be (i) the field of application, and (ii) an alternative sensor location optimization method, which is compared with the reference method described in [2, 13].

2. Parabolic PDEs and Their Discretization

The magneto-quasistatic potential equation (1.11) and the heat equation (1.12) belong to the class of parabolic initial/boundary value problems. Parabolic PDEs are generalizations of the prototype diffusion equation in one spatial dimension,

$$\partial_t u(x, t) = \partial_{xx} u(x, t) + f(x, t),$$

where u is the field under study, f is a given source term, and ∂_t and ∂_{xx} denote the first and second partial derivatives. Due to a complicated geometry and non-constant material parameters, the FE method is chosen for the spatial discretization, whereas implicit Runge-Kutta methods are used for time integration to ensure stability.

2.1 Elliptic Boundary Value Problem

Next, we consider the so-called elliptic component of (1.11a) and (1.12a), so we omit the time-derivative term from the equation. With physically reasonable assumptions, we see that the resulting boundary value problem is well posed.

Let a domain $\Omega \subset \mathbb{R}^d$, $d = 2$ or 3 , have a Lipschitz boundary. For brevity, we assume the zero Dirichlet boundary condition on the whole $\partial\Omega$. The field $u : \Omega \rightarrow \mathbb{R}$ is the weak solution of the boundary value problem (BVP)

$$-\nabla \cdot [\nu(\vec{x}, |\nabla u|) \nabla u] = f \quad \text{in } \Omega, \quad (2.1a)$$

$$u = 0 \quad \text{on } \partial\Omega, \quad (2.1b)$$

where $f \in L^2(\Omega)$. For ν , we have two cases: 1) $\nu = \nu(\vec{x})$, so the PDE is linear. 2) $\nu = \nu(\vec{x}, |\nabla u|)$, and the PDE is *quasilinear*. These cases are discussed in Sections 2.1.1-2.1.2.

Due to spatial jumps in ν and/or f , the derivative $\nabla \cdot [\nu(\vec{x}, |\nabla u|) \nabla u]$ does not exist in the classical sense. Instead, we consider the weak (or variational) formulation of (2.1), which is also the foundation for the FE discretization

later on. In general, the appropriate function space for the weak problem depends on the function ν . In the problems considered in this thesis, the appropriate space is the Sobolev space $H_0^1(\Omega)$. By multiplying (2.1a) with a test function $v \in H_0^1(\Omega)$, integrating over Ω , and applying (2.1b), we obtain the problem: Find $u \in H_0^1(\Omega)$ such that

$$(\nu(\vec{x}, |\nabla u|) \nabla u, \nabla v)_\Omega = (f, v)_\Omega \quad \text{for all } v \in H_0^1(\Omega), \quad (2.2)$$

where $(u, v)_\Omega := \int_\Omega uv$.

We define a “semilinear” form $a(\cdot, \cdot) : H_0^1(\Omega) \times H_0^1(\Omega) \rightarrow \mathbb{R}$,

$$a(u, v) := (\nu(\vec{x}, |\nabla u|) \nabla u, \nabla v)_\Omega. \quad (2.3)$$

With this notation, (2.2) reads as: Find $u \in H_0^1(\Omega)$ such that

$$a(u, v) = (f, v)_\Omega \quad \text{for all } v \in H_0^1(\Omega). \quad (2.4)$$

2.1.1 Linear Problem

In the following, we consider (2.1) with the assumptions

$$\nu(\vec{x}, |\nabla u|) = \nu(\vec{x}), \quad (2.5a)$$

$$\nu \in L_+^\infty(\Omega) := \{v \in L^\infty(\Omega) \mid \text{ess inf } v > 0\}. \quad (2.5b)$$

This linear(ized) model is adequate, when the variation in the temperature or the magnetic field is not too large. Generally, when modeling ferromagnetic core material in electric machines, linearizing ν (see Figure 1.2b) is not a valid approximation.

With the assumptions (2.5), (2.3) reduces into a bilinear form $a_{\text{lin}}(\cdot, \cdot) : H_0^1(\Omega) \times H_0^1(\Omega) \rightarrow \mathbb{R}$,

$$a_{\text{lin}}(u, v) := (\nu(\vec{x}) \nabla u, \nabla v)_\Omega, \quad (2.6)$$

which is symmetric, bounded, and coercive. With these properties, the Lax-Milgram lemma [11] states that the problem: Find $u \in H_0^1(\Omega)$ such that

$$a_{\text{lin}}(u, v) = (f, v)_\Omega \quad \text{for all } v \in H_0^1(\Omega) \quad (2.7)$$

has a unique solution satisfying $\|u\|_{H^1(\Omega)} \leq C \|f\|_{L^2(\Omega)}$.

2.1.2 Quasilinear Problem

A PDE of the form (2.1a) is a *quasilinear* second order elliptic PDE in a *divergence form* [24, Chapter 10]. With certain physical assumptions for the

material function ν , the problem (2.4) has a solution $u \in H_0^1(\Omega)$. Note that the linear material relation (2.5) corresponds to a special case of this quasilinear problem.

In the electromagnetic problem, the domain Ω is split into nonmagnetic and ferromagnetic regions Ω_0 and Ω_{Fe} , respectively. The constitutive relation (1.3) determines the material parameter

$$\nu(\vec{x}, |\vec{B}|) = \begin{cases} \nu_0, & \vec{x} \in \Omega_0, \\ \nu_{\text{Fe}}(|\vec{B}|), & \vec{x} \in \Omega_{\text{Fe}}, \end{cases} \quad (2.8)$$

where ν_0 is the vacuum reluctivity, and ν_{Fe} is the reluctivity function of iron (cf. Figure 1.2b). Let $H(B) := \nu_{\text{Fe}}(B)B$, where $H := |\vec{H}|$, $B := |\vec{B}|$.

We assume (physically reasonably):

- (i) There exists $\nu_{\min}, \nu_{\max} \in \mathbb{R}$ such that

$$0 < \nu_{\min} \leq \nu_{\text{Fe}}(B) \leq \nu_{\max} < \infty \quad \text{for all } B \geq 0.$$

- (ii) $H(B)$ is a strictly increasing function of B .

- (iii) $H(B)$ is continuous w.r.t. B .

We follow the theory in [24, Chapter 10]. For a fixed $u \in H_0^1(\Omega)$, the mapping $H_0^1(\Omega) \rightarrow \mathbb{R}$, $v \mapsto a(u, v)$, is a bounded linear functional. Then, there exists a (nonlinear) mapping $T : H_0^1(\Omega) \rightarrow H^{-1}(\Omega)$ defined by

$$a(u, v) = (T(u), v) \quad (2.9)$$

for all $u, v \in H_0^1(\Omega)$.

Let X be a real, reflexive, Banach space, and X^* be its dual space. The Browder-Minty theorem states if $T : X \rightarrow X^*$ is bounded, continuous, coercive, and monotone, then the equation $T(u) = g$ has a solution $u \in X$ for any $g \in X^*$.

In the problem under study, $X = H_0^1(\Omega)$, $X^* = H^{-1}(\Omega)$. Under the assumptions (i-iii) above, T fulfills the criteria in Browder-Minty theorem, and the problem

$$-\nabla \cdot (\nu(\vec{x}, |\nabla u|) \nabla u) = g$$

has a weak solution $u \in H_0^1(\Omega)$ for every $g \in H^{-1}(\Omega)$.

2.2 Finite Element Discretization

Next, we outline how the finite element method is used to discretize the boundary value problem (2.1). For the linear case (2.5), a mathematical treatment of

FEs is given in, e.g., [7]. For FE analysis designated specifically for electrical machines, see, e.g., [21, 4].

The FE method is a so-called Galerkin method, meaning that in (2.4) we replace the “variation space” $V = H_0^1(\Omega)$ with a finite-dimensional subspace $V_h \subset V$. This results in the problem: Find $u_h \in V_h$ such that

$$a(u_h, v_h) = (f, v_h)_\Omega \quad \text{for every } v_h \in V_h. \quad (2.10)$$

In the FE method, the space V_h is defined in the following manner. The computational domain $\bar{\Omega} \subset \mathbb{R}^d$ is partitioned into elements, such that the element boundaries match with the material parameter boundaries. Electrical machines have complicated geometries, so triangles ($d = 2$) or tetrahedrons ($d = 3$) are most commonly used. Typically, the space $V_h \subset H_0^1(\Omega)$ consists of continuous piecewise polynomial functions of degree p over the partition.

2.2.1 Finite Element Solution of Linear Problem

Assuming the linear material model (2.5), we outline how (2.10) is solved numerically. The chosen finite element basis functions for V_h are denoted by $\{\phi_i\}_{i=1}^n$. Then, (2.10) is equivalent to

$$\mathbf{K}\mathbf{x} = \mathbf{f}, \quad (2.11)$$

where $\mathbf{K} \in \mathbb{R}^{n \times n}$, $\mathbf{f} \in \mathbb{R}^n$, $[\mathbf{x}]_i \in \mathbb{R}^n$ are the coefficients of $u_h = \sum_{i=1}^n x_i \phi_i$, and

$$[\mathbf{K}]_{i,j} := (\nu \nabla \phi_i, \nabla \phi_j)_\Omega, \quad (2.12)$$

$$[\mathbf{f}]_i := (f, \phi_i)_\Omega, \quad (2.13)$$

for $i, j = 1, 2, \dots, n$. The “stiffness” matrix $\mathbf{K}$ is sparse, symmetric, and positive definite. The problems considered in this work are “small”, in the sense that $\mathbf{K}$ can be explicitly assembled. In that case, (2.11) can be solved by, e.g., a (fill-in reducing) Cholesky decomposition.

The FE solution error has the following standard a priori estimate. Let h denote the maximum element diameter. Consider a sequence of FE solutions computed by a family of shape regular (“no thin elements”) partitions. As $h \rightarrow 0$, the FE solution u_h converges to the true solution u under regularity assumptions on u . The well-known result is [7]

$$\|u_h - u\|_{L^2(\Omega)} \leq Ch^{p+1}, \quad (2.14)$$

$$\|\nabla u_h - \nabla u\|_{L^2(\Omega)} \leq Ch^p, \quad (2.15)$$

where p is the polynomial degree of the element space, and $u \in H_0^{p+1}(\Omega)$ is assumed.

2.2.2 Finite Element Solution of Quasilinear Problem

The quasilinear case (2.10) leads to the nonlinear equation

$$\mathbf{k}(\mathbf{x}) = \mathbf{f}, \quad (2.16)$$

where $\mathbf{k} : \mathbb{R}^n \rightarrow \mathbb{R}^n$,

$$[\mathbf{k}(\mathbf{x})]_i := (\nu(\nabla w(\mathbf{x})) \nabla w(\mathbf{x}), \nabla \phi_i)_\Omega, \quad (2.17)$$

$$w(\mathbf{x}) := \sum_{k=1}^n x_k \phi_k, \quad (2.18)$$

$$[\mathbf{f}]_i := (f, \phi_i)_\Omega, \quad (2.19)$$

for $i = 1, 2, \dots, n$. In practice, the system (2.16) is often solved approximately by the Newton-Raphson (NR) iteration,

$$\mathbf{x}_{i+1} = \mathbf{x}_i - [\mathbf{D}_k(\mathbf{x}_i)]^{-1}(\mathbf{k}(\mathbf{x}_i) - \mathbf{f}), \quad (2.20)$$

where $\mathbf{D}_k : \mathbb{R}^n \rightarrow \mathbb{R}^{n \times n}$ is the Jacobian of (2.17). Implementationwise, assembling the matrix $\mathbf{D}_k(\mathbf{x}_i)$ and solving the linear system (2.20) are often the most time-consuming parts of the simulation (as they have to be repeated several times per time step with the time-dependent problem in Section 2.4).

The convergence rate of the FE approximations of the quasilinear problem is similar to the linear problem, see [1] and the references therein.

2.3 Parabolic Initial/Boundary Value Problem

In this Section, we include the time evolution into (2.1). With reasonable assumptions on the source term and the initial state, the solution is (at least) continuously differentiable w.r.t. time.

The domain Ω , boundary conditions, and the material function ν are as in (2.1). The time is denoted by $t \in [0, T]$. The time-dependent field $u : \Omega \times [0, T] \rightarrow \mathbb{R}$ is the weak solution to the parabolic initial/boundary value problem

$$\sigma(\vec{x}) \partial_t u - \nabla \cdot [\nu(\vec{x}, |\nabla u|) \nabla u] = f(t) \quad \text{in } \Omega \times (0, T), \quad (2.21a)$$

$$u = u_0 \quad \text{in } \Omega \times \{t = 0\}, \quad (2.21b)$$

$$u = 0 \quad \text{on } \partial\Omega \times (0, T), \quad (2.21c)$$

assuming

$$\sigma \in L_+^\infty(\Omega), \quad f \in L^2(0, T; L^2(\Omega)), \quad u_0 \in H_0^1(\Omega). \quad (2.22)$$

The requirement of strictly positive σ is lifted in Section 3.1.2.

2.3.1 Linear Parabolic Problem

With the linearity (2.5) and assumptions (2.22), the weak form of (2.21) can be expressed as [11, Chapter 7]: Find $u \in L^2(0, T; H_0^1(\Omega))$, with $\partial_t u \in L^2(0, T; H^{-1}(\Omega))$, satisfying

$$(\sigma \partial_t u, v)_\Omega + a(u, v) = (f, v)_\Omega \quad (2.23)$$

for each $v \in H_0^1(\Omega)$ and a.e. $t \in [0, T]$, and $u(0) = u_0$. The solution u exists and is unique, and $\partial_t u \in L^2(0, T; L^2(\Omega))$. Assuming more spatial regularity on u_0 and more temporal regularity on f , along with certain compatibility conditions, yields more smoothness on u , $\partial_t u$, and existence and smoothness on higher order derivatives $\partial_{tt}^2 u$, etc.

2.4 Time Discretization

We discuss the numerical solution of the parabolic problem (2.21). We use FEs for the spatial discretization and implicit Runge-Kutta (IRK) schemes for time integration.

The spatially FE-discretized solution $u_h \in C^m(0, T; V_h)$, $m \geq 1$, has the expansion

$$u_h(t) = \sum_{i=1}^n x_i(t) \phi_i, \quad (2.24)$$

where $\{\phi_i\}_{i=1}^n$ are the FE basis functions (see Section 2.2) and $\{x_i\}_{i=1}^n$ their time-dependent coefficients. Applied to (2.23), the resulting semidiscretized equation is

$$\mathbf{M} \dot{\mathbf{x}}(t) + \mathbf{k}(\mathbf{x}(t)) = \mathbf{f}(t), \quad (2.25)$$

$$\mathbf{x}(0) = \mathbf{x}_0, \quad (2.26)$$

where $\mathbf{k}, \mathbf{f}$ are defined in (2.17-2.19), and

$$[\mathbf{M}]_{i,j} := (\sigma \phi_i, \phi_j)_\Omega, \quad i, j = 1, \dots, n. \quad (2.27)$$

For convenience, let us write (2.25) in the form

$$\dot{\mathbf{x}}(t) = \mathbf{M}^{-1}[\mathbf{f}(t) - \mathbf{k}(\mathbf{x}(t))] =: \mathbf{F}(\mathbf{x}, t). \quad (2.28)$$

The system is dissipative, meaning that $\|\mathbf{x}(t)\| \rightarrow 0$ as $t \rightarrow \infty$ in the absence of a source $\mathbf{f}$.

When choosing a numerical time integration method for (2.28), one has to consider stability, accuracy, and computational cost of the method. A

typical simulation involves nonlinear equation solutions on a large number of time steps, so the computational cost is an important factor. As other error sources are expected to dominate the time integration error, a sufficient accuracy is reached with a relatively large step size, which in turn leads to the question of the stability of the method.

Certain implicit Runge-Kutta (IRK) methods are A-stable [14], rendering them good options for integrating (2.28). Two commonly used such methods are the implicit Euler (also known as the backward Euler method) and the implicit trapezoidal method (also known as the Crank-Nicolson method when combined with finite differences or finite elements). It is known that an explicit Runge-Kutta method can never be A-stable.

As an example, we employ the Crank-Nicolson (CN) method to numerically solve the ODE (2.28). The unknown $\mathbf{x}(t)$ is approximated at the “time instants” $t_j = j\Delta t$, where Δt is the time step size, and we denote $\mathbf{x}^j := \mathbf{x}(t_j)$. Applied to (2.28), the CN method is

$$\mathbf{x}^{j+1} = \mathbf{x}^j + \frac{\Delta t}{2}(\mathbf{F}(\mathbf{x}^j, t_j) + \mathbf{F}(\mathbf{x}^{j+1}, t_{j+1})),$$

which in this case leads to

$$\mathbf{M}\mathbf{x}^{j+1} + \frac{\Delta t}{2}\mathbf{k}(\mathbf{x}^{j+1}) = \mathbf{M}\mathbf{x}^j + \frac{\Delta t}{2}(\mathbf{k}(\mathbf{x}^j) + \mathbf{f}^j + \mathbf{f}^{j+1}). \quad (2.29)$$

The unknown $\mathbf{x}^{j+1}$ is solved from this nonlinear equation iteratively by the Newton-Raphson method as in (2.20).

3. Research Problems and Findings

This Chapter outlines the problems studied in Publications, and the results are briefly discussed.

3.1 Mechanical Rotation, Time Integration, Energy Balance, and Torque Computation

Publications I-III consider the implementation of the rotor motion, time integration, energy loss and torque computations, and the Jiles-Atherton hysteresis model combined with the FE-discretized magneto-quasistatic problem (1.11).

3.1.1 Rotating Subdomain

We outline how the rotor motion can be included in the simulation of a rotating machine, as the one described in Section 1.1. As long as the rotation speed is well below the speed of light, the following consideration is valid [3]. The coordinate frame in the rotor is fixed with the rotating material (so-called Lagrangian frame), and the rotor FE mesh remains unchanged.

Let $u_R \in H^1(\Omega_R)$ be the field in the rotor Ω_R and $u_S \in H^1(\Omega_S)$ the field in the stator Ω_S . The fields are governed by (2.21). The coupling between u_R and u_S is provided by the following. The field $u_A \in H^1(\Omega_A)$ in the air gap $\Omega_A \subset \Omega$ is determined by

$$-\nabla \cdot (\nu_0 \nabla u_A) = 0 \quad \text{in } \Omega_A, \quad (3.1a)$$

$$u_A = u_R \quad \text{on } \Gamma_{AR,\theta}, \quad (3.1b)$$

$$u_A = u_S \quad \text{on } \Gamma_{AS}, \quad (3.1c)$$

where $\Gamma_{AR,\theta}$ and Γ_{AS} are the air gap-rotor and air gap-stator interfaces, respectively. The well-posedness of (2.21) combined with (3.1) is shown in [8].

Implementationwise, one can think that there are separate systems of the

form (2.25) for FE-discretized u_R and u_S . The coupling is provided by a discretization of (3.1),

$$\mathbf{K}_\theta \begin{bmatrix} \mathbf{x}_{AR} \\ \mathbf{x}_{AS} \end{bmatrix} = \begin{bmatrix} 0 \\ 0 \end{bmatrix}, \quad (3.2)$$

where $\mathbf{x}_{AR}$ (or $\mathbf{x}_{AS}$) are the FE degrees of freedom shared by the rotor (or stator) and the air gap, and the subscript θ denotes the rotor angle-dependency of the matrix $\mathbf{K}_\theta$. Different strategies for constructing $\mathbf{K}_\theta$ are listed below.

In Publications I-III, the rotation is implemented in a FE simulation either by remeshing (or a moving band) [4], or by Nitsche's method [5]. In remeshing, the air gap FE mesh is deformed and retriangulated in a controlled manner. In Nitsche's method, the air gap mesh is allowed to be nonmatching on the rotation interface, and the discontinuity of u on the interface is handled by modifying the weak problem appropriately. It can be argued that Nitsche's method provides a smoother rotation method, as there is no need for retriangularization.

There exists several other strategies, such as computing an exact solution for u in the air gap (i.e., the exact solution to Laplace's equation in an annulus), handling (3.1) by the boundary element method (BEM), and others. The negative side of these methods is that all the FE degrees of freedom active on the rotor-stator interface are coupled, leading to a dense $\mathbf{K}_\theta$.

3.1.2 Differential-Algebraic Equation

Consider the quasistatic problem (2.21) modeling the magnetic field in an electrical machine. The conductivity σ is zero in the air gap and the iron core, and the source term f is supported in the conducting region. Let $\Omega_C := \{\vec{x} \in \Omega \mid \sigma(\vec{x}) > 0\}$ and $\Omega_I := \{\vec{x} \in \Omega \mid \sigma(\vec{x}) = 0\} = \Omega \setminus \Omega_C$. Then, (2.21) reads as

$$\sigma(\vec{x})\partial_t u - \nabla \cdot [\nu(\vec{x}, |\nabla u|) \nabla u] = f(t) \quad \text{in } \Omega_C \times (0, T), \quad (3.3a)$$

$$-\nabla \cdot [\nu(\vec{x}, |\nabla u|) \nabla u] = 0 \quad \text{in } \Omega_I \times (0, T), \quad (3.3b)$$

$$u = u_0 \quad \text{in } \Omega_C \times \{t = 0\}, \quad (3.3c)$$

$$u = 0 \quad \text{on } \partial\Omega \times (0, T), \quad (3.3d)$$

which is a degenerate parabolic problem; see [19] for existence, uniqueness, and regularity results.

A spatial FE-discretization of (3.3), combined with coupled field and circuit equations, leads to a (rank-1) differential-algebraic equation (DAE)

$$\mathbf{M}\dot{\mathbf{y}}(t) + \mathbf{k}_1(\mathbf{y}(t), \mathbf{z}(t)) = \mathbf{f}(t), \quad (3.4a)$$

$$\mathbf{k}_2(\mathbf{y}(t), \mathbf{z}(t)) = 0, \quad (3.4b)$$

where the matrix $\mathbf{M}$ can be rank-deficient, $\mathbf{y}$ denotes the variables whose time derivative appears in the equations, and conversely, $\mathbf{z}$ the variables whose time derivative does not appear.

Publications I-II study time integration schemes for (3.4). It is noted that applying, e.g., the CN scheme (2.29) “blindly” to numerically solve (3.4) accumulates error in the solution. In such case, one essentially ends up integrating an algebraic equation. In addition, if the initial state $(\mathbf{y}_0, \mathbf{z}_0)$ is inconsistent, meaning that $\mathbf{k}_2(\mathbf{y}_0, \mathbf{z}_0) \neq 0$, the numerical integration may lead to artefacts such as oscillation. In practice, this inconsistency may occur if the initial state is obtained from a harmonic approximation, or if the “previous” time step ends in an inconsistent state.

3.1.3 Magnetic Field Energy and Torque Computation

One quantity of interest in an electrical machine simulation is the mechanical torque. There exists different methods to compute the torque from a FE solution, which are outlined below.

An object carrying the current density $\vec{J}$ in a magnetic field $\vec{B}$ experiences the Lorentz force (density) $\vec{f} = \vec{J} \times \vec{B}$. Assuming smooth enough fields, it can be shown that the total torque $\vec{T} = \int_{\Omega} \vec{r} \times \vec{f} d\vec{r}$, where $\vec{r}$ is the position vector, due to the Lorentz force can be computed by integrating the so-called Maxwell stress tensor, and there exists several methods for this (e.g., [3, 16]). Another possibility is to compute the torque by the virtual power principle, $T = \partial_{\theta} W_{\text{mag}}$, i.e., as the change of the configuration’s magnetic energy W_{mag} as the rotor rotates by a small angle θ . In the FE setting, this quantity can be computed exactly, and this is known as the Coulomb’s method [10].

With smooth enough fields, the previous methods yield the same torque. However, with the field represented by linear or quadratic H^1 -FEs, the aforementioned quantities are equivalent only when the integration path is chosen in a specific manner. A natural question is, what is the “correct” way to compute the torque? First, it can be argued that the virtual power principle is more general than the Maxwell stress tensor approach [6]. Second, from a practical standpoint, the hypothesis is that if the torque given by, say, two different integration paths shows large discrepancy, then the FE solution is not “accurate enough”. This is confirmed in numerical tests; higher order elements and/or finer mesh reduce the afore-mentioned discrepancy in torque.

3.1.4 Energy Balance

In addition to afore-mentioned torque, other quantities of interest in electrical machines simulations are input energy, stored energy, energy losses, and the mechanical energy output. With an exact solution, the energy quantities sum up to zero, whereas a numerical time integration scheme may induce error in the computation leading to energy imbalance.

The numerical energy balance is discussed in Publications I-II. The chosen approach is to consider an IRK time integration method as a *collocation method*. For each time step, $t \in [t_j, t_j + \Delta t]$, the variables $x_i(t)$ in (2.25) are considered to be a polynomials (over t) of degree n satisfying the DAE exactly at certain points in the time interval $[t_j, t_j + \Delta t]$. The conventional implicit Euler and Crank-Nicolson methods fall into this category. Choosing an energy-conserving (symplectic) method, such as the implicit midpoint rule, and using the polynomial representation to compute the loss terms, yields a scheme that conserves the conserving part and integrates consistently the loss terms. More generally, the connection between collocation methods, energy conserving systems, and IRK methods is studied in [25].

In Publication II, the relation between the numerical energy balance, torque, and the rotation strategies (cf. Section 3.1.1) is discussed and tested numerically.

3.2 Jiles-Atherton Model in Finite Element Simulation

In Publication III, the aim is to incorporate a variant of the Jiles-Atherton (JA) magnetic hysteresis model [20] into a FE simulation. In general, modeling magnetic hysteresis is nontrivial, and there exists several different hysteresis models [27]. Amongst the models, the JA model is attractive due to its relative simplicity and low computational cost compared to, e.g., Preisach-type models. In the work, we focus on providing a computational scheme that fixes stability issues encountered with previous attempts to combine JA model with FEs.

The following constitutive relation aims at modeling the hysteretic behaviour illustrated in Figure 1.2a, and thus replaces (1.3) as the iron H - B relation. Consider a single spatial point in a ferromagnetic material. In the vectorized inverse JA model [20], the relation between $\vec{H}$ and $\vec{B}$ is given as a differential equation

$$\frac{\partial \vec{H}}{\partial \vec{B}} = \underline{\nu}_D(\vec{H}, \vec{B}, \Delta \vec{H}) \quad (3.5)$$

where the matrix $\underline{\nu}_D$ is called the differential reluctivity, and $\Delta \vec{H}$ denotes

the “instantaneous change of direction” of $\vec{H}$. Computationally, combining a FE solution of a field equation with a constitutive relation of the form (3.5) requires numerical integration of (3.5) at each (numerical quadrature) point in the hysteretic material.

In an electrical machine simulation, a conventional time step size Δt is considerably larger than the step size that is required to integrate (3.5) with a sufficient accuracy and stability. In the method proposed in Publication III, the step size for integrating (3.5) is adaptive both spatially and temporally. The scheme is computationally feasible and stable in the numerical tests that simulate a rotating electrifying machine with coupled circuit and hysteresis models.

3.3 Iron Loss Determination as Inverse Heat Source Problem

Recall that the predictions given by existing iron loss models have error of 10-45% compared to measured losses [18]. Publication IV studies an inverse approach to determine iron losses. Instead of using an existing loss model, the loss acts as an unknown heat source in the heat equation. By measuring the temperature on some easily reachable locations on (and/or inside) the machine, the aim is to reconstruct the heat source.

Given all the parameters (heat conductivity, heat capacity, heat source, etc) and finding the temperature u satisfying (1.12) is called the *forward problem*. As seen in Section 2.3.1, the solution u exists, is unique, and depends continuously on f , so the forward problem is well posed [17]. Conversely, solving for f , given some limited information on u , is an *inverse problem*. It is easy to see that this inverse problem is ill posed.

Publication IV provides a computational framework for solving an ill-posed inverse heat source problem in a *Bayesian* setting. In the Bayesian approach [17], the unknown is treated as a random variable X , which in this consists of the FE representation coefficients of the heat source. The *prior* distribution of X should include as much information as possible on the heat source. In this case, the source is expected to be a spatially smooth function that is concentrated at the windings, and this information is used as a prior. The *posterior* distribution (i.e., “the reconstruction”) is the prior distribution “updated” with the information obtained from measurements, with measurement noise (a random variable) taken into account.

From a practical point of view, the results suggest that a boundary measurement at the steady state temperature gives only little information of the

iron loss. One should include a time transient temperature measurement, and preferably augment the measurement by including temperature sensors inside the object. Such measurements have already been conducted [18, 22], but instead of FE analysis, thermal networks are employed to model the heat conduction.

In addition, the location of the temperature measurements affects the reconstruction quality, so the positioning of the heat sensors is studied numerically in Publication IV. This is accomplished by using (Bayesian) optimal experimental design (OED) theory [9]. The aim is to position the sensors so that the posterior density variance is as small as possible, so the reconstruction uncertainty is minimized. A proposed “sliding sensor method” of finding optimal sensor locations is compared with the so-called l_0 -sparsification method described in, e.g., [2].

The proposed computational setting is viable for treating the inverse problem, and related OED, with a realistic three-dimensional geometry using a single desktop computer.

References

- [1] A. ABDULLE AND M. E. HUBER, *Error estimates for finite element approximations of nonlinear monotone elliptic problems with application to numerical homogenization*, Numerical Methods for Partial Differential Equations, 32 (2016), pp. 15. 955–969, <https://doi.org/10.1002/num.22037>, <http://infoscience.epfl.ch/record/200959>.
- [2] A. ALEXANDERIAN, N. PETRA, G. STADLER, AND O. GHATTAS, *A-optimal design of experiments for infinite-dimensional bayesian linear inverse problems with regularized l_0 -sparsification*, SIAM J. Sci. Comput., 36 (2014), pp. A2122–A2148, <https://doi.org/10.1137/130933381>, <https://doi.org/10.1137/130933381>, <https://arxiv.org/abs/https://doi.org/10.1137/130933381>.
- [3] A. ARKKIO, *Analysis of Induction Motors Based on the Numerical Solution of the Magnetic Field and Circuit Equations*, PhD Thesis, Helsinki University of Technology, 1987, <http://lib.tkk.fi/Diss/198X/isbn951226076X/isbn951226076X.pdf>.
- [4] J. BASTOS AND N. SADOWSKI, *Electromagnetic Modeling by Finite Element Methods*, Electrical and Computer Engineering, CRC Press, 2003, <https://books.google.fi/books?id=7DPK-ZcvWMcC>.
- [5] R. BECKER, P. HANSBO, AND R. STENBERG, *A finite element method for domain decomposition with non-matching grids*, ESAIM: Mathematical Modelling and Numerical Analysis, 37 (2003), p. 209–225, <https://doi.org/10.1051/m2an:2003023>.
- [6] A. BOSSAVIT, *Virtual power principle and Maxwell’s tensor: Which comes first?*, Compel-the International Journal for Computation and Mathematics in Electrical and Electronic Engineering - COMPEL-INT J COMPUT MATH ELEC, 30 (2011), pp. 1804–1814, <https://doi.org/10.1108/03321641111168110>.
- [7] D. BRAESS, *Finite Elements: Theory, Fast Solvers, and Applications in Solid Mechanics*, Cambridge University Press, 3 ed., 2007, <https://doi.org/10.1017/CB09780511618635>.
- [8] A. BUFFA, Y. MADAY, AND F. RAPETTI, *A sliding mesh-mortar method for a two dimensional eddy currents model of electric engines*, ESAIM: Mathematical Modelling and Numerical Analysis - Modélisation Mathématique et Analyse Numérique, 35 (2001), pp. 191–228, <http://eudml.org/doc/194047>.
- [9] K. CHALONER AND I. VERDINELLI, *Bayesian experimental design: A review*, Stat. Sci., 10 (1995), pp. 273–304.

- [10] J. COULOMB, *A methodology for the determination of global electromechanical quantities from a finite element analysis and its application to the evaluation of magnetic forces, torques and stiffness*, IEEE Transactions on Magnetics, 19 (1984), pp. 2514–2519.
- [11] L. EVANS, *Partial Differential Equations*, Graduate studies in mathematics, American Mathematical Society, 2010, <https://books.google.fi/books?id=Xnu0o\EJrCQC>.
- [12] C. GUÉRIN, K. JACQUES, R. V. SABARIEGO, P. DULAR, C. GEUZAIN, AND J. GYSELINCK, *Using a Jiles-Atherton vector hysteresis model for isotropic magnetic materials with the finite element method, Newton-Raphson method, and relaxation procedure*, International Journal of Numerical Modelling: Electronic Networks, Devices and Fields, (2016), pp. n/a–n/a, <https://doi.org/10.1002/jnm.2189>, <http://dx.doi.org/10.1002/jnm.2189>. JNM-15-0192.R1.
- [13] E. HABER, L. HOESH, AND L. TENORIO, *Numerical methods for experimental design of large-scale linear ill-posed inverse problems*, Inverse Problems, 24 (2008), p. 055012, <http://stacks.iop.org/0266-5611/24/i=5/a=055012>.
- [14] E. HAIRER AND G. WANNER, *Solving Ordinary Differential Equations II. Stiff and Differential-Algebraic Problems*, vol. 14, 01 1996, <https://doi.org/10.1007/978-3-662-09947-6>.
- [15] O. HEAVISIDE, *Electrical Papers*, New York and London: Macmillan & Co, 1894, <https://archive.org/details/electricalpapers02heavrich>.
- [16] F. HENROTTE, G. DELIÉGE, AND K. HAMEYER, *The eggshell approach for the computation of electromagnetic forces in 2d and 3d*, COMPEL - The international journal for computation and mathematics in electrical and electronic engineering, 23 (2004), pp. 996–1005, <https://doi.org/10.1108/03321640410553427>.
- [17] J. P. KAIPIO AND E. SOMERSALO, *Statistical and computational inverse problems*, vol. 160 of Applied Mathematical Sciences, Springer-Verlag, New York, 2005.
- [18] A. KRINGS, *Iron Losses in Electrical Machines - Influence of Material Properties, Manufacturing Processes, and Inverter Operation*, PhD Thesis, KTH, School of Electrical Engineering (EES), 2014, <http://urn.kb.se/resolve?urn=urn:nbn:se:kth:diva-145243>.
- [19] K. L. KUTTLER, *The Galerkin method and degenerate evolution equations*, Journal of Mathematical Analysis and Applications, 107 (1985), pp. 396 – 413, [https://doi.org/https://doi.org/10.1016/0022-247X\(85\)90321-X](https://doi.org/https://doi.org/10.1016/0022-247X(85)90321-X), <http://www.sciencedirect.com/science/article/pii/0022247X8590321X>.
- [20] J. V. LEITE, N. SADOWSKI, P. KUO-PENG, N. J. BATISTELA, J. P. A. BAS-TOS, AND A. A. DE ESPINDOLA, *Inverse Jiles-Atherton vector hysteresis model*, IEEE Transactions on Magnetics, 40 (2004), pp. 1769–1775.
- [21] J. LUOMI, *Finite Element Methods for Electrical Machines, Lecture notes for a postgraduate course on electrical machines*, 1993.
- [22] D. G. NAIR AND A. ARKKIO, *Inverse thermal modeling to determine power losses in induction motor*, IEEE Trans. Magn., 53 (2017), pp. 1–4, <https://doi.org/10.1109/TMAG.2017.2661381>.

- [23] J. B. PADILHA, P. KUO-PENG, N. SADOWSKI, AND N. J. BATISTELA, *Vector hysteresis model associated with FEM in a self-excited induction generator modeling*, IEEE Transactions on Magnetics, 52 (2016), pp. 1–4, <https://doi.org/10.1109/TMAG.2015.2483201>.
- [24] M. RENARDY AND R. C. ROGERS, *An Introduction to Partial Differential Equations*, Texts in Applied Mathematics, Springer-Verlag New York, 2004.
- [25] S. J. SMALL, *Runge-Kutta Type Methods for Differential-Algebraic Equations in Mechanics*, PhD Thesis, University of Iowa, 2011, <http://ir.uiowa.edu/etd/1082>.
- [26] H. TOLİYAT AND G. KLIMAN, *Handbook of Electric Motors*, Electrical and computer engineering, CRC Press, 2018, <https://books.google.fi/books?id=4-Kkj53fWTIC>.
- [27] A. VISINTIN, *Differential Models of Hysteresis*, Applied Mathematical Sciences 111, Springer-Verlag Berlin Heidelberg, 1994.
- [28] P. WAIDE AND C. BRUNNER, *Energy-Efficiency Policy Opportunities for Electric Motor-Driven Systems*, tech. report, International Energy Agency, 2011.
- [29] S. ZAGLMAYR, *High Order Finite Element Methods for Electromagnetic Field Computation*, PhD Thesis, Johannes Kepler Universität, 2006, <https://www.numerik.math.tugraz.at/~zaglmayr/pub/szthesis.pdf>.

ISBN 978-952-64-0164-5 (printed)

ISBN 978-952-64-0165-2 (pdf)

ISSN 1799-4934 (printed)

ISSN 1799-4942 (pdf)

Aalto University

School of Science

Department of Mathematics and Systems Analysis

www.aalto.fi

**BUSINESS +
ECONOMY**

**ART +
DESIGN +
ARCHITECTURE**

**SCIENCE +
TECHNOLOGY**

CROSSOVER

**DOCTORAL
DISSERTATIONS**