Robust and Efficient Methods for Distributed Speech Processing

Perspectives on Coding, Enhancement and Privacy

Sneha Das

Robust and Efficient Methods for Distributed Speech Processing

Perspectives on Coding, Enhancement and Privacy

Sneha Das

A doctoral dissertation completed for the degree of Doctor of Science (Technology) to be defended, with the permission of the Aalto University School of Electrical Engineering, at a public examination held at the lecture hall R003/F239a of the school on 26 November 2021 at 12:00.

**Aalto University
School of Electrical Engineering
Signal Processing and Acoustics
Speech Interaction Technology**

Supervising professors

Professor Tom Bäckström,
Aalto University, Finland

Thesis advisors

Professor Tom Bäckström,
Aalto University, Finland

Preliminary examiners

Adjunct Professor, Ing. Ph.D. Philippe Gournay,
Université de Sherbrooke, Canada

Professor Tuomas Virtanen,
Tampere University, Finland

Opponents

Mads Græsbøll Christensen,
Aalborg University, Denmark

Aalto University publication series

DOCTORAL DISSERTATIONS 152/2021

© 2021 Sneha Das

ISBN 978-952-64-0575-9 (printed)

ISBN 978-952-64-0576-6 (pdf)

ISSN 1799-4934 (printed)

ISSN 1799-4942 (pdf)

<http://urn.fi/URN:ISBN:978-952-64-0576-6>

Unigrafia Oy
Helsinki 2021

Finland

Publication orders (printed book):
sneha.das@aalto.fi

Author
Sneha Das

Name of the doctoral dissertation
Robust and Efficient Methods for Distributed Speech Processing

Publisher School of Electrical Engineering

Unit Signal Processing and Acoustics

Series Aalto University publication series DOCTORAL DISSERTATIONS 152/2021

Field of research Speech Technology

Manuscript submitted 6 April 2021

Date of the defence 26 November 2021

Permission for public defence granted (date) 21 September 2021

Language English

☐ **Monograph**

☒ **Article dissertation**

☐ **Essay dissertation**

Abstract

Computers and technology are so deeply embedded in our lives today that people invest a considerable part of their day communicating with technology. Conventional modes of human-technology interaction have predominantly been device-centric, due to which the users are required to be in the vicinity of the device. This can become cumbersome as the number of personal devices owned by an individual increases. A recent positive trend is the evolution towards user-centric modes of communication with technology enabled by the growing use and adoption of speech user interfaces. Furthermore, developments in the field of virtual and ad-hoc microphone networks and sensor technology are supporting this evolution. As a result, speech processing methods are moving towards a more distributed and collaborative approach. However, this has resulted in new challenges and technical problems in managing speech enhancement, coding and user privacy in acoustic sensor networks.

The objectives of this thesis are two-fold: \begin{enumerate*}\item to develop methods to enable the advancement of conventional speech coding for multiple microphones, \item to understand the state of privacy in speech-user interfaces. \end{enumerate*}

In the first part we study and develop postfilters for coding with the final goal of advancing the postfilters to enable conventional speech and audio coding methods in distributed microphone networks. A primary requirement in sensor networks is to have systems and algorithms that are simple and robust. Therefore, we develop methods that do not need the transmission of any side information or inter-microphone communication, and the postfilters are based completely at the decoder. To that end, we develop single microphone postfilters that employ the envelope and harmonic models of speech. Following this, we advance these methods to develop a model based postfilter for multi-microphone speech coding using conventional coding approaches. Our experiments demonstrate that by incorporating speech models in the postfilters as proposed, the output signal quality is improved in comparison to other baseline postfiltering and enhancement approaches.

The lack of user privacy considerations in the design of speech interfaces has had an adverse impact on their widespread adoption. Therefore, methods to enforce the privacy of users within the framework of speech interfaces are necessary and timely. In the second part of the thesis, we address how to instill smart speech interfaces with an intuitive understanding of user privacy preferences. Towards that end, we investigate the perception of privacy for people in noisy acoustic scenarios. The results indicate that individuals have an intuitive understanding of privacy in speech communication that is dependent on the acoustic scenarios among other factors. The insights from these studies can be further exploited by conditioning the privacy preferences on the sensed acoustic environment in a speech interface.

Keywords Speech, Speech-coding, Privacy, Postfiltering, Speech-interfaces

ISBN (printed) 978-952-64-0575-9

ISBN (pdf) 978-952-64-0576-6

ISSN (printed) 1799-4934

ISSN (pdf) 1799-4942

Location of publisher Helsinki

Location of printing Helsinki **Year** 2021

Pages 140

urn <http://urn.fi/URN:ISBN:978-952-64-0576-6>

Preface

My interest in research began as an undergraduate student. Although, I did not have any formal experience in research then, it was something I definitely wanted to try. My first exposure to research, specifically in speech and audio signal processing was during my masters education in Germany, where as part of student jobs at Fraunhofer IIS and International Audio Labs in Erlangen, I was exposed to the exciting aspects of speech and audio technology. It was then and there, that I got introduced to my PhD supervisor and adviser, Tom Bäckström, in his seminar course in 2014 who then offered me a masters thesis. The masters thesis was followed by the opportunity for a PhD in Aalto University, Finland. Looking back at the sequence of events now, I am glad they unfolded the way they did.

First and foremost, I thank Professor Tom Bäckström for his time and patience over all these years, for making this PhD not just a research journey, but a time with significant personal growth and evolution. I thank his commitment to always be there for his students, however busy he may be. I will always find his excitement for discovering beautiful mathematical solutions to problems inspiring and worth emulating.

I would also like to thank Professor Paavo Alku, for supporting me as the official PhD supervisor during the early years of the thesis, that was the official requirement of the program.

This work was carried out in the Department of Signal Processing and Acoustics at Aalto University in Espoo, Finland, and was largely funded by Fraunhofer IIS, Germany. I would like to thank Fraunhofer IIS, Germany for their support through the years. I am deeply grateful to Guillaume Fuchs for his interest and guidance through the work, and his time during my research visit at Fraunhofer IIS that resulted in a publication for this thesis. It is always great discussing research, working and collaborating with him and is inspiring to see his deep expertise on the subject.

I would like to thank my pre-examiners, Professor, Ing. Ph.D. Philippe Gournay and Professor Tuomas Virtanen for their constructive feedback and encouraging comments on the thesis.

My time at Aalto University wouldn't have been the same without the

people around me. Foremost to Pablo, with whom I not only shared the office but a similar mindset on issues. Our discussions and random rants on politics and world affairs over coffee and on an unproductive day was refreshing, and not to forget the bi-weekly sushi custom. Also, Thanks to Emma, Manu, Dhananjaya, Tiina, Lauri, Baji, Shreyas, Narendra, Sudarsana, Anna, Meghna, Abraham and Muhammad for being there.

As mentioned, my journey towards a PhD began long before the actual thesis work. I would like to thank Saneesh Cleatus, for being one of the two teachers during my undergraduate studies, encouraging my questions and interest towards research. To Alexandra, Tobias and Johannes for guiding and supporting me through my time at the International Audio laboratory, Erlangen.

The years and time invested in this work was made possible because of my family. To my parents, Molly and Tarun, for being so understanding and supportive through the years. They gave me the space and time I needed to do my thing, although they still don't entirely understand what I (we) do in academia besides teaching. To my brother Romit, who has always helped me stay grounded and never shirks away from being critical and open about my work and skills.

To my newfound family, my mother-in-law Chitra and sister-in-law Rekha for the consistent encouragement and kind words. To Merete Lundsteen, for actually pushing me to hand-in the thesis since forever, and for making me feel at home always.

Lastly, but most importantly to Raghav, for being such a supportive, understanding and caring partner. I couldn't have asked for more, and the journey so far is so much more satisfying with him beside.

Copenhagen, October 18, 2021,

Sneha Das

Contents

Preface	1
Contents	3
List of Publications	5
Author’s contributions	7
List of Figures	9
Abbreviations	11
Symbols	13
1. Introduction	15
1.1 Objectives	15
1.2 Thesis structure	16
2. Background	19
2.1 Modeling speech and its perception	19
2.2 Speech and audio coding	23
2.2.1 Frequency domain codecs	23
2.2.2 Time domain codecs	24
2.3 Evaluation of speech technology	25
2.3.1 Measures for subjective evaluation	25
2.3.2 Measures for objective evaluation	26
2.3.3 Complexity measures	27
3. Enhancement and postfiltering techniques for speech cod- ing	29
3.1 Approaches to speech enhancement for environmental noise	30
3.1.1 Single-channel enhancement	30
3.1.2 Multi-channel enhancement:	33
3.1.3 Deep learning methods for enhancement	33

3.2	Postfiltering for speech coding	34
3.2.1	Noise filling	35
3.2.2	DNN-based postfilters	35
3.3	Acoustic sensor networks	36
4.	Privacy in speech interfaces	39
4.1	Privacy in speech interfaces	39
4.2	Approaches to privacy preservation	40
4.2.1	Principles for personal data privacy	40
4.2.2	Techniques and tools for privacy preservation . .	41
4.3	Summary	43
5.	Summary of publications	45
5.1	Publication I: “Postfiltering with Complex Spectral Correlations for Speech and Audio Coding”	45
5.2	Publication II: “Postfiltering Using a Log-Magnitude Spectrum for Speech and Audio Coding”	46
5.3	Publication III: “Fundamental Frequency Model for Postfiltering at Low Bit rates in a Transform-Domain Speech and Audio Codec”	47
5.4	Publication IV: “Enhancement by Postfiltering for Speech and Audio Coding in Ad Hoc Sensor Networks”	49
5.5	Publication V: “Postfiltering Using Source Modeling for Speech and Audio Coding in Ad Hoc Sensor Networks” . .	50
5.6	Publication VI: “Sound Privacy: A Conversational Speech Corpus for Quantifying the Experience of Privacy”	51
5.7	Publication VII: “Perception of Privacy Measured in a Crowd–Paired Comparison on the Effect of Background Noise”	53
6.	Conclusions	55
	References	59
	Publications	65

List of Publications

This thesis consists of an overview and of the following publications which are referred to in the text by their Roman numerals.

- I** Sneha Das, Tom Bäckström. Postfiltering with Complex Spectral Correlations for Speech and Audio Coding. In *Proceedings of the Annual Conference of the International Speech Communication Association (INTERSPEECH)*, Hyderabad, pp. 3538-3542, September 2018.
- II** Sneha Das, Tom Bäckström. Postfiltering Using Log-Magnitude Spectrum for Speech and Audio Coding. In *Proceedings of the Annual Conference of the International Speech Communication Association (INTERSPEECH)*, Hyderabad, pp. 3543-3547, September 2018.
- III** Sneha Das, Tom Bäckström, Guillaume Fuchs. Fundamental Frequency Model for Postfiltering at Low Bit Rates in a Transform-Domain Speech and Audio Codec. In *Proceedings of the Annual Conference of the International Speech Communication Association (INTERSPEECH)*, Shanghai, China, pp. 2837-2841, October 2020.
- IV** Sneha Das, Tom Bäckström. Enhancement by postfiltering for speech and audio coding in ad-hoc sensor networks. *The Journal of the Acoustical Society of America Express Letters*, pp. 015206, January 2021.
- V** Sneha Das, Tom Bäckström. Postfiltering Using Source Modeling for Speech and Audio Coding in Ad Hoc Sensor Networks. Submitted to *IEEE Access*, 2021.
- VI** Pablo Perez Zarazaga, Sneha Das, Tom Bäckström, V. V. Vidyadhara Raju, Anil Kumar Vuppala. Sound Privacy: A Conversational Speech Corpus for Quantifying the Experience of Privacy. In *Proceedings of the Annual Conference of the International Speech Communication Association (INTERSPEECH)*, Graz, Austria, pp. 3720-3724, September 2019.

- VII** Anna Leschanowsky, Sneha Das, Tom Bäckström. Perception of Privacy Measured in the Crowd –Paired Comparison on the Effect of Background Noises. In *Proceedings of the Annual Conference of the International Speech Communication Association (INTERSPEECH)*, Shanghai, China, pp. 4651-4654, October 2020.

Author's contributions

Publication I: “Postfiltering with Complex Spectral Correlations for Speech and Audio Coding”

The author had the main responsibility for the development and the evaluation of the algorithm. The author was also the main writer of the article, including writing a first draft and the subsequent revisions.

Publication II: “Postfiltering Using Log-Magnitude Spectrum for Speech and Audio Coding”

The author had the main responsibility for the development and the evaluation of the algorithm. The author was also the main writer of the article, including writing a first draft and the subsequent revisions.

Publication III: “Fundamental Frequency Model for Postfiltering at Low Bit Rates in a Transform-Domain Speech and Audio Codec”

The author had the main responsibility for the development and the evaluation of the algorithm. The author was also the main writer of the article, including writing a first draft and the subsequent revisions.

Publication IV: “Enhancement by postfiltering for speech and audio coding in ad-hoc sensor networks”

The author had the main responsibility for the development and the evaluation of the algorithm. The author was also the main writer of the article, including writing a first draft and the subsequent revisions.

Publication V: “Postfiltering Using Source Modeling for Speech and Audio Coding in Ad Hoc Sensor Networks”

The author had the main responsibility for the development and the evaluation of the algorithm. The author was also the main writer of the article, including writing a first draft and the subsequent revisions.

Publication VI: “Sound Privacy: A Conversational Speech Corpus for Quantifying the Experience of Privacy”

The author shared 50% of the workload on designing and conducting the onsite questionnaire. The author was 100% responsible for transcribing the responses from the onsite responses into digital format. The author was 100% responsible for setting up the online questionnaire, running the survey and pre-processing the responses. The author wrote sections 3 (3.1, 3.2) and 4 of the manuscript and contributed to the revision of the paper. Lastly, the decision that the research team would start working on privacy issues in speech processing began from a proposal by the author.

Publication VII: “Perception of Privacy Measured in the Crowd –Paired Comparison on the Effect of Background Noises”

The author participated in the planning session of the pilot and main experiment and the subsequent design phase (20%). The author contributed to the revision of the article.

List of Figures

2.1	Block diagram illustrating speech production using the source filter model.	19
2.2	Plot illustrating the concept of frequency masking.	21
2.3	Plot illustrating the concept of temporal masking.	21
2.4	Frequency domain plots of the magnitude spectrum, spectral envelope and the perceptual envelope of a typical voiced speech frame.	22
2.5	Block diagram illustrating frequency domain coding. Figure adapted from https://wiki.aalto.fi/display/ITSP/Introduction+to+Speech+Processing	24
2.6	Block diagram presenting the encoder and decoder in CELP codec. Figure adapted from https://wiki.aalto.fi/display/ITSP/Introduction+to+Speech+Processing	25
3.1	Spectrograms of (a) speech degraded by environmental noise with reverberation, and (b) speech degraded by coding noise.	30
3.2	Spectrograms of (a) clean speech, (b) noisy speech degraded by environmental noise (with) reverberation, and (c) enhanced speech using a Wiener filter.	30
3.3	Illustrating the estimation of the clean speech signal, S_{clean} using non-negative matrix factorization (NMF). W_{speech} , S_{clean} correspond to the basis vectors of speech and the speech activation coefficients, respectively. All three matrices generally have non-negative constraints.	32
3.4	Illustration of a delay-and-sum beamformer. Figure adapted with permission [Bäckström, 2020].	32
3.5	Illustration of an acoustic sensor network system using consumer grade devices with a microphone to provide a unified acoustic front-end to the user. Figure adapted with permissions [Bäckström, 2020]	36

4.1	Summary of data sharing principles employed in different approaches for privacy preservation. Figure adapted with permission [Bäckström et al., 2020].	40
4.2	Workflow structure in a federated learning architecture.	42
4.3	Demonstrating privacy preservation between interacting devices using the concept of acoustic fingerprinting. Figure adapted with permission [Bäckström, 2020]	42
5.1	Illustration of the time-frequency context neighborhood used in Paper I. Figure adapted from figure 1 in Paper I. .	45
5.2	(Left) The line-plots present the true, quantized and estimated spectrum and envelope for an arbitrary speech frame. (Right) Scatter-plots show the true, quantized and estimated signal energy in frequency bins quantized to zero for two context sizes. All plots are adapted from figures 7 and 8 in Paper II.	46
5.3	Spectrograms demonstrating the harmonic structure in the enhanced signal, with respect to the noisy (decoded) signal and the clean signal.	48
5.4	Mean and 95% confidence intervals of the differential PSNR and PESQ scores between the proposed multidevice estimate in Paper IV, a single-channel baseline and the multi-channel Wiener filtered signal.	49
5.5	Mean opinion scores and 95% confidence intervals from the P.835 and P.808 ITU-T recommendation for speech quality using crowd-sourcing presented in Paper V.	50
5.6	The newspaper headlines illustrate the articles addressing the concerns of privacy in speech interfaces over week 32 in 2019.	52
5.7	The barplots adapted from Paper VII demonstrate the mean preference scores and the 95% confidence intervals for each scenario pair for the question: <i>Are you more likely to share a secret, in normal voice, in the acoustic environment A or B?</i>	53

Abbreviations

ACR	Absolute Category Rating
ADPCM	Adaptive Differential Pulse Code Modulation
AMR-WB	Adaptive Multi-Rate WideBand
ASN	Acoustic Sensor Network
CELP	Code-Excited Linear Prediction
DNN	Deep Neural Network
EVS	Enhanced Voice Services
IGF	Intelligent Gap Filling
LC3	Low-complexity Communications Codec
LPC	Linear Predictive Coding
LSTM	Long Short-Term Memory
LTP	Long-Term Prediction
MDCT	Modified-Discrete Cosine Transform
MPEG-USAC	MPEG-Unified Speech and Audio Coding
MUSHRA	MUlti Stimulus test with Hidden Reference and Anchor
MVDR	Minimum Variance Distortionless Response
NMF	Non-negative Matrix Factorization
PESQ	Perceptual Evaluation of Speech Quality
PSNR	Perceptual Signal-to-Noise Ratio
PSQM	Perceptual Speech Quality Measure
RNN	Recurrent Neural Network
SEGAN	Speech Enhancement Generative Adversarial Network

Abbreviations

SNR	Signal-to-Noise-Ratio
STFT	Short-Time Fourier Transform
STOI	Short-Time Objective Intelligibility
TCX	Transform Coded EXcitation
WASN	Wireless Acoustic Sensor Network
WMOPS	Weighted Million Operations Per Second

Symbols

List of Latin symbols

$1/A(z)$	Spectral envelope
F_s	Sampling frequency
$F(Z)$	z-transform of the fundamental frequency response
G	Filter gain
H_{speech}	Activation coefficients of the observed speech
$L(Z)$	z-transform of the lip radiation filter
$N(Z)$	z-transform of noise excitation
$P(z)$	Pre-emphasis filter
S	Speech segment
S_v	Voiced speech segment
S_{uv}	Unvoiced speech segment
t	Time
$V(Z)$	z-transform of the time-domain vocal tract filter
W_{speech}	Basis vectors of speech
$\hat{X}$	Estimate of clean speech
x_i	Speech observation at microphone i
Y	Noisy observation

List of Greek symbols

γ_1, γ_2	Weighting constants to compute the perceptual model
ΔT_i	Time delay at microphone i
Λ_N^2	Noise covariance
Λ_Y^2	Covariance of the noisy signal
σ_N^2	Noise variance
σ_Y^2	Variance of the noisy signal

1. Introduction

I know that I know nothing.

Plato's account of Socrates

The popularity of personal assistants comprising of speech interfaces is steadily rising. Furthermore, it is now common for everyday devices such as smart-watches, coffee machines, smart-televisions to have a speech interface, enabled by the presence of embedded microphones. This facilitates the use of voice commands to interact with the devices around us. However, state-of-the-art speech interfaces (e.g. smart-speakers) require the user to be in the vicinity of the device, which can limit the adoption and usage of the technology. To improve usability, we could use all available devices (laptops, tablets, smart phones etc.) to jointly provide a speech interface. The development of distributed and collaborative multi-microphone speech interfaces is thus the next step towards the seamless use of speech and voice to interact with the technology around us. This will take us closer to human-centric models of human-computer interaction, wherein the devices adapt to the needs of the user. The availability of a large number of connected devices and the falling cost of sensors have laid the required infrastructure for ad hoc multi-microphone networks, hence making distributed multi-microphone speech interfaces a possibility.

Current technology for multi-microphone processing and multi-device sensor collaboration requires high-end equipment from a single provider, making the solutions expensive and inflexible. Additionally, a lot of the research till-date on multi-device sensor technology is theoretical, and requires more investigations into its practical implementation and feasibility. Furthermore, the idea of surrounding devices equipped with microphones listening to us all the time gives rise to privacy issues in ad hoc multi-microphone networks. While addressing privacy issues for browser-based and mobile applications has received traction, privacy in speech interfaces is still vastly unexplored.

1.1 Objectives

The aim of this thesis is to identify the challenges of enhancement for speech coding in multi-microphone networks and privacy in speech user

interfaces and to propose feasible improvements and adaptations with practical implementations. To be usable in a sustainable manner, we require that our methods:

1. can be applied on resource-constrained sensor nodes (low-complexity, low bit rates),
2. are robust to background noise and room acoustics, and
3. address the preservation of privacy within their framework.

Furthermore, although the objectives of single-microphone and multi-microphone transmission methods are similar, the two fields have diverged to use different sets of tools. In this work, we also hope to build an interface between the two domains, such that conventional techniques can be adapted and improved to aid multi-microphone methods to obtain practical solutions for speech and audio processing in multi-microphone ad hoc networks.

1.2 Thesis structure

The broad focus of this thesis is three-fold: 1. To develop low-complexity postfiltering methods for speech coding. 2. To advance postfilters for speech and audio coding in ad hoc networks. 3. To quantify the privacy behaviors of people in speech communication.

Low-complexity postfilters for speech coding: We have developed enhancement algorithms which meet low-complexity and low-bit-rate requirements and can be efficiently applied to multi-microphone systems. This is in contrast to many existing conventional postfilters that are based on the transmission of side information to the decoder and require functional blocks both at the encoder and the decoder. Recent developments in machine learning have shown the potential of data-driven algorithms. Due to the correlated structure of speech, enhancement algorithms can benefit from data-driven approaches. However, current state-of-the-art data-driven and end-to-end algorithms are extremely complex and are often sub-optimally designed for speech processing [Engel et al., 2019, Valin and Skoglund, 2019]. Motivated by these constraints in the current state of data-driven approaches for speech and audio, we have proposed low complexity data-driven algorithms that incorporate knowledge about speech signals (domain-knowledge), hence making it optimal for speech processing. Papers I, II and III are based on this approach.

Postfilters for speech and audio coding in ad hoc networks: Past research on multi-device sensor technology and multi-microphone fusion methods has lead to the development of news tools to address the over-coding

problem in multi-microphone systems [Zahedi et al., 2015b, Zahedi et al., 2015a]. While many of these algorithms are theoretically optimal, the practical feasibility of these methods requires further study. Furthermore, few methods address the over-coding problem with respect to perceptual and envelope models used in single-microphone speech and audio coding, despite the fact that source and perceptual models are highly efficient at single-channel coding.

The objective of this part of the study is to investigate the feasibility of extending conventional single-microphone speech and audio coding methods to a multi-microphone setup by using a postfilter at the decoder. We have proposed an alternative enhancement algorithm to fuse signals from multi-microphone speech transmissions, and an evaluation of the method indicates robustness to background noise and reverberation which is shown in paper IV. Furthermore, due to the success of the model based postfilters, we employed the modeling techniques to develop a unified postfiltering framework which is presented in paper V.

Quantifying and modeling privacy preferences in speech communication:

The final objective of our study on privacy is to enable smart speech interfaces to understand user privacy and adapt to the privacy preferences of individuals. To that end, the first step is to quantify and model the perceptions of privacy in human-to-human speech communication. Prior studies in psychology and sociology indicate that people have an intuitive understanding of privacy preferences in speech communication and this preference often depends on the acoustic environment [Petronio, 2002]. The objective here is to investigate how the privacy preferences of people vary with the acoustic-environment. Successfully studying and modeling the privacy preferences can lead us to instill this understanding in speech interfaces so that devices can automatically adapt to the privacy requirements of the user with minimal user-intervention. Papers VI and VII are derived from this work. Methods to address privacy problems and speech interfaces (e.g. smart-speakers, smart-homes) is in its early stages and the work produced here is among the earliest studies on the topic.

2. Background

Nothing in life is to be feared, it is only to be understood. Now is the time to understand more, so that we may fear less.

Marie Curie

To understand the motivation for the methods proposed in the thesis, this chapter presents an overview of certain essential concepts in speech communication technology. The topics discussed below have a vast body of contributions within themselves and the discussions here only provide an outline of those topics.

2.1 Modeling speech and its perception

Speech communication is a culmination of multiple human facilities coordinating with each other to enable speech production and reception by the human auditory system. Beginning from the intent to speak, followed by the formation of the speech content, to the articulation of speech in the form of phonemes and phonation, these facilitate the process of speech production. The physical aspect of speech production constitutes the vocal tract shaping the glottal impulses following which the speech signal is emanated from the lips. Subsequently, it propagates in the form of sound waves and is received and processed by the human auditory system. Therefore, speech production and speech perception are the two critical aspects in speech communication and are collectively considered when designing speech communication technology.

Figure 2.1. Block diagram illustrating speech production using the source filter model.

Models of speech production: Speech is a highly time-varying signal. However, to aid the process of modelling speech, a speech signal is segmented into shorter intervals, in the order of milliseconds, that are then assumed to be stationary. Each stationary segment of speech can be considered to mainly comprise of: 1. the excitation of the vocal folds producing a semi-periodic impulse train or a noise-like excitation produced due to the constriction of the vocal tract, 2. the vocal tract response which shapes the incoming excitation, thereby acting as an acoustic filter. This system of production is often modeled by a linear system composed of a set of linear-filters [Fant, 1981], which is stated as follows: if the vocal tract response, the lip radiation, and the quasi-periodic impulse response corresponding to the fundamental frequency are represented by the z-transforms of the time-domain filters $V(Z)$, $L(Z)$, $F(Z)$ respectively, then the speech signal during a voiced instance can be formulated as:

$$S_v(Z) = F(Z)V(Z)L(Z), \quad (2.1)$$

and the unvoiced speech is modeled as:

$$S_{uv}(Z) = N(Z)V(Z)L(Z), \quad (2.2)$$

where $N(Z)$ accounts for the white-noise like excitation instances from a constricted vocal tract. Since the excitation is composed of both a semi-periodic impulse and a noise element in varying proportions, the overall speech can be represented by summing the two components:

$$S(Z) = [F(Z) + N(Z)]V(Z)L(Z). \quad (2.3)$$

Generally, the vocal tract response and the lip radiation filters are combined and approximated by a single filter, $H(Z)$ leading to the formulation $S(Z) = [F(Z) + N(Z)]H(Z)$. This filter represents the spectral envelope of the speech signal and can be obtained from the Linear Predictive Coding (LPC) coefficients. This theory, which was referred to as the source-filter model and illustrated in Fig. 2.1, was first proposed by Fant [Fant, 1981, Flanagan, 2013] and is widely used in speech processing applications largely due to its relative simplicity.

Models of speech perception: The goal of speech communication technology is to provide a pleasant listening experience, with the human auditory system as the target receiver. Therefore, communication systems have exploited aspects of human hearing which allow reduction in data transmission without infringing on the perceptual quality of the transmitted speech and audio. In this regard, perceptual models are largely used in codecs to optimize the distribution of quantization noise and coding noise, such that the resulting noisiness is imperceptible to the human ear.

The perceptual models employed in codecs are motivated by the effects

Figure 2.2. Plot illustrating the concept of frequency masking.

of masking weak tones in the presence of stronger tones in the frequency and temporal neighborhood. Under no masking conditions, the minimum sound pressure sensed by the human ears is termed as the threshold of hearing in quiet. This threshold is modified to increase at the desired frequency in the presence of a masker, and the amount of increase in the threshold is governed by the frequency of the masker, the maskee and the amplitude of the masker. The modified threshold in the presence of masking is termed the masking threshold. Furthermore, the band-width of the masker also impacts the masking threshold. This technique is referred to as frequency masking and is illustrated in Fig. 2.2.

Figure 2.3. Plot illustrating the concept of temporal masking.

Temporal masking, illustrated in Fig. 2.3, is another phenomenon in

which strong sounds before and after a relatively weaker sound mask the sound. Post-masking is when a sound within 100-200 ms of a loud sound is inaudible, and can be explained by the fact that the ears experience a fall in sensitivity within this time-span. In contrast, pre-masking occurs when a low sound occurs within a window of 20 ms before a loud sound because the ears take longer to process softer sounds than louder sounds [Herre and Dick, 2019, Fastl and Zwicker, 2006].

Figure 2.4. Frequency domain plots of the magnitude spectrum, spectral envelope and the perceptual envelope of a typical voiced speech frame.

The perceptual model is often computed from the spectral envelope of the speech segment. In other words, due to the large similarity between the perceptual model and the spectral envelope in terms of the location of formant peaks and valleys, the perceptual model can be inferred from the linear predictive coefficients that are used to model the spectral envelope. Fig. 2.4 presents an example of the magnitude spectrum and its corresponding spectral and perceptual envelopes. The first step towards computing the perceptual model is to pre-emphasize the signal, in order to reduce the dynamic range and relatively improve the emphasis on high-frequency components. The pre-emphasis filter $P(z)$ is a first-order high pass filter given as:

$$P(z) = 1 - 0.68z^{-1} \quad (2.4)$$

Following this, the 16-order LPC coefficients of the pre-emphasized signal are computed and are then scaled to smoothen them out and create an envelope. These steps yield an envelope:

$$W(z) = \frac{A(\gamma_1 z)}{A(\gamma_2 z)}, \quad (2.5)$$

where $1/A(z)$ is the spectral envelope of the pre-emphasized signal in the frequency domain, $\gamma_1 = 0.92, \gamma_2 = 0$ for the sampling frequency, $F_s = 12.8\text{kHz}$. In contrast, the perceptual model in audio codecs is computed using scale factor bands, wherein the estimate of the perceptual model is obtained by scaling the energy in each critical band by a multiplier.

2.2 Speech and audio coding

Modern codecs adopt an unified approach to address the coding requirements of both speech and audio signals, which inherently have different characteristics that are exploited for efficient coding. For instance, time domain coding employing the analysis-by-synthesis approach is particularly efficient in encoding speech signals and frequency domain coding generally works well on music and other non-speech audio signals. Therefore, unified codecs can be achieved by employing multiple coding systems and switching between them as per the requirements of the underlying signal. The 3GPP Enhanced voice services (EVS) codec, IEFT Opus codec, and the MPEG-unified speech and audio coding (MPEG-USAC) are some of the most commonly used codecs that operate under this principle [Bruhn et al., 2015, Valin et al., 2012, Neuendorf et al., 2012]. Code-excited linear prediction (CELP) is predominantly used to efficiently encode speech signals. It is based on the source-filter model for speech production and works especially well with rapidly changing signals and signals with a distinct fundamental frequency, F_0 . Therefore, it is predominantly used for speech coding. On the other hand, frequency domain codecs work with the time-frequency transformations of signals and hence are more efficient for signals that are more stationary. As a result, frequency-domain codecs are used for audio coding. The ideal target speech region for both, CELP and TCX would be stationary voiced parts. We briefly describe the two coding approaches in the following sections.

2.2.1 Frequency domain codecs

The signals are first transformed to a time-frequency representation; a modified-discrete cosine transform (MDCT) is used to address the over-coding problem that arises in segmenting the signal in overlapping windows using other transforms such as the short-time Fourier transform [Wang and Viterbo, 2003]. MDCT ensures the smooth overlapping windowing of the signals without expending additional bits to encode repeated information. This is achieved by transforming the signal in such a way that the common signal in the overlapping parts are orthogonal to each other. This means that unique information from an arbitrary signal part is distributed equally between two consecutive frames, and a perfect reconstruction can

Figure 2.5. Block diagram illustrating frequency domain coding. Figure adapted from <https://wiki.aalto.fi/display/ITSP/Introduction+to+Speech+Processing>.

be obtained by performing an overlap-add between the consecutive frames. Following the transformation of the signal to the MDCT domain, the perceptual model is computed to determine the quantization noise distribution within a frame. The spectrum is quantized using the perceptual input, following which it is entropy coded to convert it into a bit stream. The reverse steps are followed at the decoder to obtain the sound output. The block diagram in Fig. 2.5 illustrates a frequency domain codec.

2.2.2 Time domain codecs

The time domain codec CELP employs the analysis-by-synthesis approach to obtain the optimum parameters to yield a reconstructed signal that is closest to the original. At the encoder, the first step is to compute the linear prediction coefficients (LPCs) that are used to construct the LPC filter. The output from the filter is then removed from the signal to leave behind the LPC residual. The LPC residual at this stage is comprised of the harmonic component of the signal and the residual noise. The harmonic component is removed using long-term prediction (LTP), whereby the harmonic residual is the only non-modeled component and resembles white noise. The harmonic residual, LTP parameters and the LPC parameters are quantized; the analysis-by-synthesis approach comes into play at this stage, wherein to evaluate the quality of the parameters the encoded parameters are decoded and the signal is reconstructed back from the decoded parameters. The set of parameters which show the lowest loss between the reconstructed and original signal are transmitted to the decoder. An illustration of the CELP codec is provided in Fig. 2.6.

Figure 2.6. Block diagram presenting the encoder and decoder in CELP codec. Figure adapted from <https://wiki.aalto.fi/display/ITSP/Introduction+to+Speech+Processing>.

2.3 Evaluation of speech technology

Methods to evaluate speech technology, specifically within speech coding and enhancement, can be broadly classified into objective and subjective methods. This is to ensure that methods for evaluation are available for both to obtain the theoretical metrics of quality and to study the perceptual gains of a method. Additionally, in speech coding complexity and delay metrics are crucial to evaluate methods. We discuss some of the prominent evaluation metrics below.

2.3.1 Measures for subjective evaluation

Since humans are the target audience of codecs, subjective evaluation is the gold standard to evaluate methods in speech and audio coding and for enhancement applied to codecs. While there are a number of subjective measures, here we discuss a few prominent ones that are utilized in our work.

MUSHRA: This refers to the MUlti Stimulus test with Hidden Reference and Anchor and is designed to directly compare multiple competing audio systems. Listeners rate the provided samples from 1 to 100 [ITU-R-BS1534-3, 2014]. Each trial is comprised of a hidden reference which is used to screen out participants who are unable to accurately rate it. In addition,

every trial has one or two low quality signals which act as lower anchors for the methods being evaluated.

ITU-T Recommendation P.835: This is a standard which provides a method to evaluate speech communication systems comprising of noise suppression algorithms in terms of the subjective quality [ITU-T-P835, 2003]. The method employs an absolute category rating (ACR) to obtain scores from listeners and comprises of questions addressing the speech distortion, background noise and overall quality separately. The signals are rated on a scale of 1 to 5.

Recently, the P.835 evaluation method has been combined with crowd-sourcing resources in order to utilize the availability of abundant listeners from online platforms. This enables the participation of crowd in the test. For this purpose, the ITU-T recommendation P.808, “Subjective evaluation of speech quality with crowd-sourcing approach” was introduced [ITU-T-P808, 2018].

However, despite being the gold-standard for evaluation, subjective tests require considerable resources in terms of test setup, test participants and costs, and the time spent to obtain results is relatively long. Therefore, subjective evaluation is often employed at the last stages of development.

2.3.2 Measures for objective evaluation

One of the main advantages of using objective measures to evaluate a speech technology is the short time and costs associated with obtaining results of the evaluation compared to subjective tests. Some commonly used objective metrics are described below.

Perceptual SNR (PSNR): This is an objective measure which is designed to measure the subjective noisiness in a sound more accurately than the conventional SNR [Atal et al., 1991]. Since perceptual models are commonly employed in speech and audio coding, this is a concept that originated from coding. To obtain the PSNR, we filter the signal in such a way that numerically identical distortions at any two frequencies are perceived similarly. This is sometimes referred to as perceptual whitening. To obtain the PSNR the filter weights, also known as the perceptual envelope, are first computed. In our work we use an LPC-based perceptual model used in the CELP-codec. The signal under evaluation and the reference signal are both weighted by the perceptual model, following which the SNR is computed as the ratio of the signal energy and the noise energy.

PESQ: The Perceptual Evaluation of Speech Quality, commonly known as PESQ, is an objective method designed to evaluate speech in terms of the subjective quality and was standardized as per the ITU-T recommendation P.862 as “An objective method for end-to-end speech quality

assessment of narrow-band telephone networks and speech codecs” [Rix et al., 2001, ITU-T-P862, 2001]. The measure improves upon the perceptual Speech Quality Measure (PSQM) from ITU-T recommendation P.831 for the objective quality measurement of telephone band (300 to 3400 Hz) speech codecs by accounting for the filtering, variable delay, and short localized distortions [ITU-T-P861, 1996].

POLQA: Perceptual Objective Listening Quality prediction has been developed as per the ITU-T recommendation P.863 to subjectively evaluate both narrowband and fullband speech quality [ITU-T-P863, 2018].

STOI: The Short-Time Objective Intelligibility measure provides a quantitative method to measure speech degradation in terms of the intelligibility. With respect to other objective intelligibility measures, the STOI measure is designed to detect degradation with a higher time-frequency granularity. Additionally, it is modeled with fewer parameters in relation to other similar algorithms [Taal et al., 2010].

The quality of the results obtained from objective scores sometimes do not match the perceived quality obtained using subjective tests. Despite this, objective methods for evaluation are suitable for evaluating methods in the initial stages of development and can be paired with a subjective evaluation at the final stage.

2.3.3 Complexity measures

To account for resource constraints at deployment, complexity is an important metric which can be used to evaluate speech technology methods. The computational complexity in coding applications is reflected by the number of instructions executed per signal frame. In order to account for the operations that consume multiple CPU-cycles, a weight can be assigned to the operations. Thus, the framewise complexity is computed by summing the weighted operations and then dividing by the span of the frame in seconds. This number yields the weighted million operations per second (WMOPS) which is employed as a standard metric to evaluate the complexity of codec systems [ITU-T-Software-Tool, 2009].

3. Enhancement and postfiltering techniques for speech coding

In all affairs it's a healthy thing now and then to hang a question mark on the things you have long taken for granted.

Betrand Russell

Speech processing often requires access to speech signals with a high SNR. Consequently, speech signals that are corrupted by noise, e.g. background, channel and transmission noise, need to be enhanced. Speech enhancement refers to the process of improving the quality of speech signals, by reducing noise, distortion or interference. The field of speech enhancement has existed for a long time with the first algorithms proposed in the 1970s [Lim and Oppenheim, 1979]. Classical speech enhancement methods are targeted mostly toward background and environmental noises. Large portions of the speech enhancement literature assume additive and uncorrelated Gaussian noises for the background noises. A parallel set of methods address speech signals corrupted by room impulse responses and subsequently reverberation. Another category of noise is coding and quantization noise, introduced in speech and audio signals via codecs. This type of noise varies in its characteristics from the classical assumption of additive uncorrelated Gaussian noise, as it is often multiplicative in nature, or specifically for frequency domain codecs operating at relatively low bit rates. Hence, the resulting noise and distortions in the speech are correlated to the underlying signal and this is not necessarily Gaussian. Therefore, to cater to the requirements for improving the signal quality at the decoder, various postfiltering methods have been introduced within the codec, such that the postfilters take into consideration the sources of the noise. Spectrograms in Fig. 3.1 demonstrate the differences between signals corrupted by environmental (background and reverberation) noise and coding noise. In the following subsections, we describe some of the main approaches concerning enhancement for environmental noise and postfilters to improve the signal quality at the decoder.

Figure 3.1. Spectrograms of (a) speech degraded by environmental noise with reverberation, and (b) speech degraded by coding noise.

3.1 Approaches to speech enhancement for environmental noise

We organize the methods for enhancement into classical approaches based on filters, for single- and multi- channel enhancement, and relatively new techniques using advanced deep neural networks.

3.1.1 Single-channel enhancement

Figure 3.2. Spectrograms of (a) clean speech, (b) noisy speech degraded by environmental noise (with) reverberation, and (c) enhanced speech using a Wiener filter.

Gain oriented filters: Gain based filters and enhancement algorithms compute the optimal gain or mask for a frequency bin in the time-frequency representation of the speech signal. One possible approach to obtain an optimal filter is based on minimizing the mean square error between the true speech and the estimated speech, which yields the gain:

$$G = \frac{\sigma_Y^2 - \sigma_N^2}{\sigma_Y^2}, \quad (3.1)$$

where σ_Y^2 is the variance of the noisy signal, σ_N^2 is the noise variance. Following this the clean speech estimate $\hat{X}$ is given as:

$$\hat{X} = GY = \frac{\sigma_Y^2 - \sigma_N^2}{\sigma_Y^2} Y. \quad (3.2)$$

This formulation is well-known as the Wiener filter and is a commonly used method for speech enhancement [Loizou, 2013]. Note that in the above formulation the frequency bins are processed separately one at a time and the gain filter is conditioned on a single observation. In the case when the estimation is conditioned on an observation vector, the formulation is:

$$G = \Lambda_Y^{-1}(\Lambda_Y - \Lambda_N), \quad (3.3)$$

where Λ_Y, Λ_N are the covariance matrices of the noisy signal and noise, respectively. An alternate minimization criterion for the Wiener filter with multiple inputs is to use it in tandem with a MVDR filter to obtain the optimal look direction [Benesty and Huang, 2011]. Practical experience has shown that the Wiener filter is an effective method for noise reduction. The functioning of the Wiener filter is heavily dependent on the estimate of the noise. Often, due to an overestimation of the noise energy, the Wiener gain tends to result in negative values or zero. As a result, the estimated signal can have sudden temporal changes in energy which results in musical noise-like artifacts, which is a common problem associated to the use of Wiener filter. The spectrogram of a speech signal enhanced using a Wiener filter is presented in Fig. 3.2 alongside the corresponding clean and noisy signals.

Observe that the Wiener filter in Eq. 3.3 requires access to the noise energy in the observed signal. Often, it is assumed the noise statistics are available using minimum statistics [Martin, 2001, Martin, 1994]. Noise estimation using minimum statistics operates with the insight that the power spectrum of given short time sub-band of noisy speech is comprised of peaks and valleys, wherein the peaks indicate speech presence and the valleys can be assumed to be regions of speech absence. Consequently, the noise power estimate can be obtained from the power spectrum valleys within the sub-band frame. This approach to noise estimation is employed in international coding standards such as the 3GPP EVS [ETSI-TS-126-445, 2015]. However, more accurate methods have been proposed on similar lines which estimate a binary or continuous mask by using a neural network that is trained on speech signals [Narayanan and Wang, 2013], following which the mask is applied to noisy speech to remove noise. However, these methods are computationally more complex.

Non-negative matrix factorization: Also known as NMF, non-negative matrix factorization with statistical priors is a model-based speech enhancement method to learn optimal basis vectors for the speech and noise signals,

Figure 3.3. Illustrating the estimation of the clean speech signal, S_{clean} using non-negative matrix factorization (NMF). W_{speech} , S_{clean} correspond to the basis vectors of speech and the speech activation coefficients, respectively. All three matrices generally have non-negative constraints.

to provide an estimate of the clean speech from a noisy observation [Wilson et al., 2008]. In other words, the speech and the noise models are incorporated and used within the NMF framework in order to learn realistic combinations of the basis functions. A conceptual level illustration of NMF is provided in Fig. 3.3. Multi-channel extensions of the NMF approach have been proposed and show promising improvements on the output signal quality [Sawada et al., 2011, Sawada et al., 2013].

Figure 3.4. Illustration of a delay-and-sum beamformer. Figure adapted with permission [Bäckström, 2020].

3.1.2 Multi-channel enhancement:

Due to the higher sampling of the acoustic space and to the obtention of multiple versions of the same source signal, often with unique representations, it follows that multi-channel speech processing and enhancement is more effective than the single-channel counterparts. Beamforming is a common technique used to address spatial filtering for multi-channel signals. Delay-and-sum beamforming is one of the simplest approaches to spatial filtering. It is based on the projection of sound generated from a far field source as plane waves on a linear microphone array system as shown in Fig. 3.4. As a result, all the received waves can be considered as a delayed version of the reference sound wave plus the interfering noise, such that the clean signal estimate is:

$$\hat{X} = \frac{1}{N} \sum_{n=1}^{n=N} X_n(t - \Delta t_n), \quad (3.4)$$

where Δt_n is the delay between the received sound signals at the reference and microphone n , respectively, N is the total number of microphones, and X_n is the signal received at microphone n . The delay can be estimated by using information on the array configuration and the wavelengths of the underlying signals. While this approach is extremely simple and straightforward, it is mostly unsuccessful in providing any considerable improvement on real world multi-channel signals. Instead, beamformers based on minimum variance distortionless response (MVDR) [Haykin, 2008] are mostly used to process and enhance spatial signals. The underlying principle is that since the noisy signal energy can be represented as a sum of the clean signal and the noise, minimizing the variance of the noisy signal can result in noise removal. However, to ensure that the desired signal regions remain intact the distortionless constraint is employed to maintain the unit response of the filter in the desired signal direction. As mentioned in the earlier sections, a Wiener filter and non-negative matrix factorization have been extended to their multi-channel counterparts for spatial filtering.

3.1.3 Deep learning methods for enhancement

The use of deep learning for speech enhancement and noise suppression is almost a decade old, dating back almost to around the same time as the re-emergence of deep learning itself. In this section we will delve into some of the recent and relevant trends in terms of complexity and real-time processing. Most of the following methods adopt a hybrid approach.

SEGAN: The Speech Enhancement Generative Adversarial Network, commonly known as SEGAN, is an end-to-end approach to speech enhancement

based on generative adversarial networks [Pascual et al., 2017, Goodfellow et al., 2014]. Due to the end-to-end architecture of the system, hand-crafting features are not essential and the network is able to discover insights on speech without human intervention. However, this also means that the large domain knowledge that exists on speech is unused.

RNNoise: A method for real-time application to enhance full-band speech, RNNoise combines signal processing blocks for pitch analysis and pitch filtering and a recurrent neural network (RNN) [Valin, 2018]. The RNN takes the pitch parameters as input to estimate gain that is applied to the noisy signal. This main noise suppression follows the gain- and mask-based approach described above.

PercepNet: An extension of RNNoise, PercepNet exploits the human auditory models of perception for more effective noise suppression [Valin et al., 2020]. In this approach a DNN architecture is trained on features from 34 equivalent rectangular bands derived from the auditory system to yield gain factors. The gain factors are used to compute the amount of filtering from the harmonic filter and the envelope gain. The method seems to outperform the quality obtained using the RNNoise method.

3.2 Postfiltering for speech coding

To aid codecs operating over a vast range of bit rates, post-filters are often employed on the decoded signals to enhance their quality. One of the earliest postfiltering techniques was the adaptive postfiltering technique targeted towards improving the quality of decoded speech encoded using the ADPCM system, specifically at bit rates lower than 32 kbps [Ramamoorthy and Jayant, 1984]. This was subsequently extended to manage the amount of postfiltering by introducing an adaptive coefficient which was a function of the SNR [Jayant and Ramamoorthy, 1986] to address speech distortion introduced as an effect of postfiltering in the preceding method. Both these methods operated by suppressing the energy in non-speech regions while enhancing it in speech regions using a pole-zero filter, wherein the coefficients were adapted based on the local SNR. Subsequently, approaches to postfiltering addressing specific aspects of the codec noise and desired features of speech signals such as the energy in the formant and harmonic peaks and valleys, sharpness of the harmonic peaks, etc. were proposed. We briefly describe a few methods below that are used commonly in codec frameworks in addition to some developmental trends.

Formant enhancement: Decoded speech signals sound noisy sometimes due to the addition of energy at regions of low energy in the original signal. This effect is often observed in CELP codecs when operating at low bit rates. To counter this effect, formant enhancement is used to attenuate the

energy at the formant valleys while retaining or emphasizing the energy at the formant peaks [Chen and Gersho, 1995, Grancharov et al., 2007]. This yields a filter which is inherently biased towards lower energy in the regions of formant valleys. The resulting speech is perceptually better and therefore, the method was subsequently investigated for effectiveness in speech synthesis, and speech enhancement concerning environmental noise [Raitio et al., 2010].

Bass postfilter: Also known as a long-term predictor (LTP) postfilter, a bass postfilter is based on the concept of employing the LTP parameters from the bit stream to enhance the harmonic parts of voiced speech signals [Jelinek et al., 2004, Chiba et al., 2014, ITU-T-G718, 2008, Fuchs et al., 2015]. The pitch lag and quantized LTP gain are used to control the amount of filtering via a comb-filter. For instance, a bass postfilter is applied in the international speech coding standard, 3GPP Enhanced voice services (EVS) in the TCX mode and also in the low-complexity communications codec (LC3) [ETSI-TS-103-634, 2019], and is shown to be effective in reducing distortion in the decoded signal.

3.2.1 Noise filling

Musical noise and birdies are specific to transform-domain codecs operating at low bit rates. Noise filling, that is the process of inserting random noise in quantized frequency bins, is used to address artifacts such as musical noise [Helmrich et al., 2015]. However, due to its simplicity, noise filling cannot preserve the harmonic structure of the signal. Subsequently, intelligent gap filling (IGF) has been proposed to overcome the constraints of noise filling. IGF is a semi-parametric approach to noise filling in high bit rate operation modes and reproducing high frequency components at low bit rates [Disch et al., 2016, Schmidt and Neukam, 2016]. It is often used in tandem with noise filling. IGF has functional blocks both at the encoder and decoder and contributes parameters to the encoder bit stream for transmission. The philosophy behind IGF is that in order to meet the bit rate constraints, it introduces spectral holes in the signal at the encoder. In addition, it also parameterizes the signal, specifically in regions of spectral holes and truncation using temporal and spectral envelopes. At the decoder, the IGF functional blocks use dequantized signal components and transmitted signal parameters to reproduce spectral energy at the spectral holes and for high frequency components.

3.2.2 DNN-based postfilters

A new trend is to explore the application of advanced machine learning and deep learning methods for postfiltering decoded speech. A convolutional neural network-based postfilter has been proposed to improve the quality

of decoded speech in an AMR-WB codec [Zhao et al., 2018, Zhao et al., 2018]. The approaches have been applied in the time domain and the cepstral domain, such that the received decoded signals are first converted to time domain signals and then to relevant domains where the processing is done. On similar postfiltering lines, the use of neural speech synthesis at the decoder for codecs operating at low bit rates has been proposed. While the method has shown improved output speech quality, the delay and complexity of the method is too high for real-time communication. Subsequently, a mask-based DNN postfilter has been presented and quality improvements have been demonstrated for CELP codecs [Korse et al., 2020]. The paper explored three different network architectures using a fully connected neural network, a convolution encoder-decoder network, and an LSTM system that were used to estimate an ideal mask in the STFT domain which was applied to the decoded STFT domain signal. It should be noted that all the above methods were implemented for time-domain codecs and operated in the STFT domain.

3.3 Acoustic sensor networks

Figure 3.5. Illustration of an acoustic sensor network system using consumer grade devices with a microphone to provide a unified acoustic front-end to the user. Figure adapted with permissions [Bäckström, 2020]

In many typical environments today, users own and have access to a multitude of devices with microphones that can be used to provide a unified and collaborative front end to perform a speech processing task (Fig. 3.5). For instance, in a conference room, smartphones of individuals can be re-purposed for the task of speech transcription and understanding [Yoshioka et al., 2019]. The resulting collaborative system of microphones is often referred to as an ASN, and the devices in the network are used in tandem to sample an acoustic environment. Wireless ASN (WASN) is built on ASNs such that the sensors within are battery driven, due to which the devices are resource constrained. A recent variation is a virtual ASN that uses consumer-grade microphones and re-purposes them to conduct a desired task in collaboration. In other words, the primary purpose of the devices is different from the desired task. The abundance of microphones around us

in smartphones, tablets, smart watches, television set, and even regular kitchen equipment such as coffee machines and refrigerators is paving a way towards the application of virtual and ad hoc ASNs. While some of the methods proposed for multi-channel and spatial filtering can be used for speech processing in ASNs, existing and new approaches need to be explored to address challenges in ASNs resulting from resource constrained sensors in terms of power and on-board computation complexity, lack of synchronization between sensors, changing sensor network configuration and unavailability of configuration information.

4. Privacy in speech interfaces

The opposite of a correct statement is a false statement. But the opposite of a profound truth may well be another profound truth.

Niels Bohr

The advancement in speech technologies has led to an accelerated rise in the development and demand for speech user interfaces. Today, not only are most smartphones equipped with a speech-based interface to accept audio commands, speech interfaces are becoming commonplace in everyday household devices such as smart televisions and coffee machines, etc. This is a favorable transition towards transforming human-technology interaction from predominantly device-centric models to user-centric models as technology today is so deeply integrated in our lives. However, the drastic progress and adoption of speech interfaces have triggered a new set of unanswered questions and problems for personal data privacy. In this chapter we discuss the core issues of privacy in the context of speech interfaces and introduce some potential solutions being investigated.

4.1 Privacy in speech interfaces

To provide sufficiently good performance and services, speech interfaces are powered by sophisticated speech processing techniques from the fields of automatic speech recognition, speech enhancement, speech synthesis, and speech coding. Often, these back-end methods require access to high computational resources and storage to execute them successfully. Furthermore, some user services would need collaboration with other service providers over the Internet. To address these requirements, most speech interfaces today are designed to perform a bulk of their run-time operations on a cloud server. Consequently, the data required during the run-time execution of speech commands is transferred to the cloud servers. The implication of this is that by design, personal speech data, which can be considered a biometric marker for an individual is shared with cloud services. In the recent past there have been a multitude revelations of breaches of user privacy wherein sensitive speech segments were trans-

mitted to the cloud, or employees in service provider companies listened to snippets of user speech [Bäckström et al., 2020]. These incidents show that the current model and design of data handling and data processing in speech interfaces do not adhere to the principles of user privacy.

4.2 Approaches to privacy preservation

Personal data privacy is an interdisciplinary problem and requires contributions from fields such as design and engineering as much as it does from policy change and regulation. In this section, we briefly introduce the most common guiding principles towards personal data privacy, and describe the frequently used approaches for privacy preservation.

Figure 4.1. Summary of data sharing principles employed in different approaches for privacy preservation. Figure adapted with permission [Bäckström et al., 2020].

4.2.1 Principles for personal data privacy

Privacy-by-design: It is the concept of *proactively* integrating privacy already at the design and planning phases of a product, rather than a reactive afterthought [Cavoukian, 2009]. At its core is the idea that humanistic and user-centric data handling approaches should be adhered to in spirit. Accordingly, privacy should be the default setting and anything other than that should be explicitly chosen by the user. Transparency of data processing, data handling and data sharing are core to the concept.

MyData: A concept to empower users with their personal data, MyData is founded on the belief that users should have a choice over who stores, sells and uses their data [Kuikkaniemi et al., 2014]. The MyData principle encourages individuals and institutions to extract the benefits of sharing and collaborating with personal data, and emphasizes doing so with consent and utmost transparency.

4.2.2 Techniques and tools for privacy preservation

There are numerous studies on privacy preservation techniques, especially in the domain of computers and browser-based interaction. However, only a few of these techniques are suitable for and can be adapted to speech user interfaces. In the following paragraphs, we describe a few methods that can be employed in our application and a pictorial summary of the different methods is presented in Fig. 4.1.

Edge computing: One of the most straightforward ways to ensure user privacy is to execute all run-time functions on edge devices; this is referred to as edge-computing [Shi et al., 2016]. The approach requires (a) the edge devices have sufficient computation capacity, and/or (b) the algorithms used during run-time have low computational complexity. However, despite fulfilling these two requirements, some data will need to be transmitted to cloud servers to provide relevant services. Furthermore, even if edge devices are equipped with higher computational power, since the speech service is triggered only occasionally by the user they may be redundant for the remaining time. Nevertheless, going forward, edge computing can be employed in tandem with other solutions to provide more holistic privacy preservation.

Anonymization: Anonymization and pseudoanonymization are techniques for cleaning up data to remove traces of personally identifiable information that can be retrieved from a dataset [Bayardo and Agrawal, 2005]. These methods are often used to handle medical records and other highly private data. The idea behind anonymization is to strip the dataset of any irrelevant information that is also private in nature. Pseudoanonymization is slightly different in that the processed data is obfuscated but can be retrieved later using a key or similar additional piece of information. Generalization, perturbation, and permutation are few approaches to anonymization.

Although anonymization and pseudoanonymization can be effective as the first level of privacy preservation, recent studies demonstrate that data can be de-anonymized, even with just a few additional pieces of information [Narayanan and Shmatikov, 2008, Ohm, 2009]. Therefore, when using anonymization as the sole technique to protect personal data, it is imperative to perform a risk assessment of the data de-anonymization.

Federated learning: Federated learning is a technique of learning by collaboration, wherein machine learning models are trained using model updates from edge devices [Mohri et al., 2019]. All the model updates are combined and updated either at a central server or in cooperation between the nodes. Subsequently, the updated final model is sent to the edge devices. The process is depicted in Fig. 4.2. The upside of this method is

Figure 4.2. Workflow structure in a federated learning architecture.

that no raw data leaves the personal devices, thereby it preserves privacy and complies to the principles of privacy-by-design. Therefore, federated learning adapted to speech processing is a potential approach to address privacy issues in speech interfaces [Leroy et al., 2019].

Figure 4.3. Demonstrating privacy preservation between interacting devices using the concept of acoustic fingerprinting. Figure adapted with permission [Bäckström, 2020]

Acoustic fingerprinting: Acoustic fingerprinting provides a method to compare two audio signals without revealing the original audio signals. In other words, acoustic fingerprinting algorithms find representations of audio signals which are as equidistant in the encoding domain as they are in the signal domain [Zarazaga et al., 2020]. Therefore, this technique is useful in pairing devices with access to similar audio inputs, which makes them particularly useful to enable collaboration between acoustic sensors, specifically in ad hoc sensor networks and virtual sensor networks.

Consequently, this approach is being actively investigated as a way to regulate and enable privacy-by-design principles in ad hoc acoustic sensor networks. A conceptual level illustration of acoustic fingerprinting is shown in Fig. 4.3.

4.3 Summary

The approaches to privacy preservation, as discussed above, are predominantly oriented towards enabling data sharing to develop better algorithms in the context of deep learning. In other words, these techniques focus on gaining insights from personal data without access to raw data. However, another important aspect of privacy preservation, specifically in the context of speech communication and interfaces, emerges from our communication with technology. As technology is increasingly acquiring a central role in human lives, we need to gain deeper insights into how individuals perceive privacy within the context of their interaction with technology [Nissenbaum, 2004, Yeasmin et al., 2020]. Furthermore, we need tools to measure and quantify the perception of privacy or the lack of it. Articles VI and VII contribute towards this by investigating how individuals interpret privacy in human-to-human speech communication.

5. Summary of publications

Life can only be understood
backwards; but it must be lived
forwards.

Søren Kierkegaard

Summaries of publications forming the dissertation are presented in this chapter.

5.1 Publication I: “Postfiltering with Complex Spectral Correlations for Speech and Audio Coding”

Figure 5.1. Illustration of the time-frequency context neighborhood used in Paper I. Figure adapted from figure 1 in Paper I.

Pre- and post-filtering methods are employed in codecs to aid their operations beyond the target bit rate range. In this work we propose a postfilter that models complex inter-frame and inter-frequency correlations inherent to speech signals using a context neighborhood. Due to potential transmission losses, the inter-frame correlations cannot be transmitted as parameters. Therefore, we designed the system such that the covariance matrices are composed of two parts: the first part is a normalized covariance matrix trained offline using existing speech datasets for an arbitrary context neighborhood. The second part is an adaptive gain factor estimated

during inference. A fixed context ordering method is used based on the distance of a frequency bin from the frequency bin under consideration as shown in Fig. 5.1.

Our underlying assumption was that the quantization noise is additive and Gaussian, and this can also be achieved at low bit rates with the use of randomization. We performed objective and subjective methods to evaluate the performance of the postfilter. The PSNR scores indicate an improvement between 6 dB and 2 dB compared to the noisy signal, and the MUSHRA scores show an improvement between 10 to 30 MUSHRA points.

This publication was our first improvement to model based postfilters that uses the inherent time and frequency correlations in speech signals, towards the goal of efficient speech communication. The method can be used to improve the overall performance of the codecs. It showed considerable improvement in the output objective scores for simulated coding noise under the above assumptions. However, sometimes the method is more aggressive than desired, leading to additional artifacts in the process of noise removal.

5.2 Publication II: “Postfiltering Using a Log-Magnitude Spectrum for Speech and Audio Coding”

Figure 5.2. (Left) The line-plots present the true, quantized and estimated spectrum and envelope for an arbitrary speech frame. (Right) Scatter-plots show the true, quantized and estimated signal energy in frequency bins quantized to zero for two context sizes. All plots are adapted from figures 7 and 8 in Paper II.

Frequency domain codecs have a tendency to quantize low energy parts of a speech signal to zero at low bit rates. Consequently, the signals quantized at low bit rates can be extremely sparse resulting in muffled artifacts in the signal. In order to address this problem, codecs often use noise filling to fill the regions quantized to zero. To improve the resulting signal quality, parameters guiding the amount of noise filling can be transmitted in the bit stream. In this work, we propose a postfilter to reduce quantization noise that relies on the time-frequency correlations in speech. We carried out the modeling in the log magnitude domain, which models the formant information in speech. We modeled the log-magnitude

context as a multivariate Gaussian distribution. For the inference of the speech energy in quantized bins, we estimate the conditional probability distribution of speech in the considered bin, conditioned by the context neighborhood. The quantization bin limits were then used to compute the truncated Gaussian distribution. The final point estimate was obtained by formulating the loss function as the expected likelihood.

We evaluated the method using the PSNR and the SNR scores. The PSNR improvement was between 1 to 2 dB and the SNR improvement was between 1 to 2 dB for input SNR 4 to 18 dB. As a consequence of modeling in the log-magnitude domain, the proposed method effectively models the spectral envelope of the underlying speech signal. The plots in Fig. 5.2 demonstrate the estimated magnitude spectrum and signal energy with respect to the true and quantized frequency spectrum and energy in an arbitrary frequency bins.

Transform-domain codecs are usually lower in complexity, relative to time-domain codecs like CELP which are based on analysis-by-synthesis. Distributed speech coding involves multiple codecs working in parallel thereby adding complexity, and therefore transform-domain codecs are better suited for coding in distributed speech systems. This article extends the concept of model based postfilter to transform-domain codecs by leveraging the gains from time-frequency spectral correlations. We demonstrate that the log-magnitude postfilter can accurately estimate energies in zero-quantized bins. However, the work has some perceivable limitations that are listed below: 1. The models were trained in the STFT domain, while TCX codecs operate in the MDCT domain. Since MDCT transformation is based on critical sampling, the correlations are smaller in the MDCT domain. Therefore, we anticipate that the models will yield lower improvement when applied on the decoded signals in the MDCT domain. 2. In this work, we estimated the energies of the MDCT coefficients. However, estimating real-valued MDCT coefficient is an important factor towards the usability of the proposed method, and that should be pursued as an extension to this work.

5.3 Publication III: “Fundamental Frequency Model for Postfiltering at Low Bit rates in a Transform-Domain Speech and Audio Codec”

In this paper, we propose a postfilter that incorporates models of the fundamental frequency of speech. Motivated by the speech production model, wherein the vocal tract shapes the glottal excitation, we model clean speech, in the log magnitude domain as the sum of the fundamental frequency model, the spectral envelope model and a residual noise component. While the envelope and the frequency models represent the speech parts of the

Figure 5.3. Spectrograms demonstrating the harmonic structure in the enhanced signal, with respect to the noisy (decoded) signal and the clean signal.

decoded signal, the residual noise component corresponds to not only the noise-like residual in speech but also to the quantization noise, for instance. We obtained the harmonic model from the inverse cepstrum of the speech segment under consideration, which yields a modulated sinusoid. To obtain the optimum filter, the minimum mean square error between the estimated and clean speech signal was used as an optimization criteria.

To gain further insights into the method, we performed the modeling both in the frequency domain and the perceptual domain and observed that modeling the perceptual domain yielded better estimates perceptually. We evaluated the signals objectively using PSNR, PESQ and POLQA scores and show an average improvement of 1 dB, 0.2 MOS and 0.5 MOS, respectively for the female speech samples. For the male samples, while the PSNR improvement was similar, the PESQ scores did not show any improvement and the POLQA improvement was around 0.1 MOS. To evaluate the method subjectively, we conducted an MUSHRA listening test and observed an average improvement of 7 MUSHRA points over the baseline signal using the perceptual domain models. An example of the enhanced signal spectrogram is presented in Fig. 5.3 along with the clean and noisy decoded signal spectrograms.

In this article we work towards improving the model-based postfilter for efficient speech communication by employing a harmonic model that can be used in tandem with envelope based models. Incorporating the harmonic model within the postfilter showed enhanced harmonic structures in the output signal, specifically at lower frequencies, thus aiding against the over-smoothing the output signal as observed in the previous methods. This removes the musical artifacts that are common in TCX codecs. However, one limitation was that the model was unable to completely disentangle the harmonic structure from the envelope and other variations. Consequently, the estimated energy in the spectral valleys was sometimes higher than desired, rendering a hoarse characteristic to the output signal.

5.4 Publication IV: “Enhancement by Postfiltering for Speech and Audio Coding in Ad Hoc Sensor Networks”

Figure 5.4. Mean and 95% confidence intervals of the differential PSNR and PESQ scores between the proposed multidevice estimate in Paper IV, a single-channel baseline and the multi-channel Wiener filtered signal.

Coding and transmission are integral in acoustic sensor networks (ASNs) where the signals received at the nodes are corrupted by environmental noise and coding noise. Some frameworks for spatial filtering in ASN do not address the coding noise while other frameworks assume the coding noise to have an additive Gaussian distribution. While this assumption is valid at moderate to high bit rates, at lower bit rates the coding noise is non-linear. In this work, we present a postfilter that incorporates explicit models of the coding noise along with the environmental noise and is designed to be applied in tandem with conventional frequency domain codecs. To that end, we formulated the system as a Bayesian filter where the distribution inside the quantization bin was modeled with a truncated Gaussian distribution.

For the evaluation, we simulated an ASN comprised of two microphones under the assumption that one microphone would be predominantly corrupted by environmental noise and the other mostly corrupted by coding noise. PSNR and PESQ scores formed the objective part of the evaluation and MUSHRA scores provided subjective evaluation scores. The system was evaluated for multiple bit rates and additive and reverberant degradation. We compared the objective scores with respect to the noisy reference and a multi-channel Wiener filter. In the additive noise scenario the PSNR and PESQ improvement was positive on average with respect to all references and for all bit rates, and the amount of improvement varied with respect to the background noise as shown in Fig. 5.4. However, for the samples degraded by reverberation in addition to background noise,

we found that the absorption coefficient did not have an impact on the performance of the filter. Furthermore, the proposed method improved the MUSHRA score of the male samples, but degraded the female samples.

This paper investigates distributed multi-device postfilters, whereas the previous methods address single-channel codecs. In addition to exploring the advantage of distributing bandwidth over a sensor network with two sensors, in this article we address the fact that often speech signals are corrupted by environmental noise along with coding noise. Under such scenarios, due to the assumptions made on the coding noise model, the postfilters proposed in previous works require additional models to account for the environment noise. Here we take this into consideration by employing separate models for coding noise and environment noise. While coding noise can be inferred from the bitrate, we also assumed that the noise energy from the different channels was known. Furthermore, we do not account for the room impulse response within the problem formulation; we expect that the output gains will be higher if factors of distortion due to reverberation can be incorporated within the formulation. In conclusion, we show that the proposed method improves objective and subjective quality in distributed scenarios, more than single device methods only.

5.5 Publication V: “Postfiltering Using Source Modeling for Speech and Audio Coding in Ad Hoc Sensor Networks”

Figure 5.5. Mean opinion scores and 95% confidence intervals from the P.835 and P.808 ITU-T recommendation for speech quality using crowd-sourcing presented in Paper V.

This paper builds on the work presented in Papers II, III, and IV by implementing the harmonic and envelope models in the postfilter of a real codec and evaluating their joint effect. To that end, the formulation comprises of speech models corresponding to the spectral envelope and harmonic structure, that are trained offline using speech datasets. The

envelope model was obtained from the context neighborhood. We learned the optimal context neighborhood using the Bayesian information criterion, in contrast to Publications I and II where the neighborhood ordering was chosen based on the distance from the frequency bin under consideration. The remaining formulation consists of the posterior distribution that is represented by truncated Gaussian distribution based on the received quantization bin limits from the sensors.

The proposed method was evaluated with additive noise, both without and with reverberation, over a range of bit rates. We used the PSNR, PESQ and STOI as the objective metrics and the ITU-T recommendation P.835 along with P.808 for the subjective evaluation. The barplots in Fig. 5.5 show the mean opinion scores from the P.835 and P.808 subjective evaluation. For reference, we used both signal processing-based filters and deep learning-based methods. We show that while the improvement in the objective quality of the output signal using the proposed method is higher than that of the references for most scenarios and bit rates, the amount of improvement was dependent on the bit rate and relatively higher for the additive noise scenario. In terms of the subjective evaluation, the proposed method improved quality especially in the additive noise scenario.

This paper brings together the models for postfiltering within the framework of speech coding in an ASN, hence bridging all the preceding work towards addressing robust and efficient speech communication for distributed processing. We demonstrate the advantage of distributing bandwidth over two sensors and employing envelope and harmonic models within the framework. However, here we assume that the delay between the microphones is known, whereby the incoming signals are synchronized. We expect that this limitation can be overcome in future works by incorporating delay estimation routines within the postfilter. Furthermore, it is essential to investigate the gains from the postfilter for larger sensor networks and to include factors of room impulse response within the problem formulation to further improve output gains.

5.6 Publication VI: “Sound Privacy: A Conversational Speech Corpus for Quantifying the Experience of Privacy”

Despite the growing popularity and demand for speech interfaces, conversations about privacy concerning speech interfaces has only just started to gain traction (Fig. 5.6). Most approaches addressing this problem propose a generic approach to privacy preservation using methods such as federated learning, edge-computing, etc. The innate understanding of privacy that individuals employ in speech communication, however, can further aid in deploying speech interfaces with user privacy preferences. In this paper we take the first step towards that goal by presenting a corpus that

Figure 5.6. The newspaper headlines illustrate the articles addressing the concerns of privacy in speech interfaces over week 32 in 2019.

quantifies people’s perception of privacy. The process consisted of recording a scripted speech conversation in an acoustic environment immediately followed by a questionnaire that the participants responded to regarding their perception of privacy in that acoustic scenario. The responses and the dataset were validated by an online questionnaire with a different set of participants. The acoustic scenarios were chosen based on our hypothesis that the perception of privacy depends on the amount of stationary and non-stationary background noise and the extent of reverberation in the acoustic environment. The responses from the onsite and online questionnaire correlate, which indicates that auditory stimuli impact the perception of privacy in speech interaction. We also present an evaluation of the responses with respect to the type of acoustic environment.

This work was initiated with the goal to begin a discourse on privacy in speech interfaces with a focus on communication and trust in human-to-human interaction. A dataset comprising of acoustic environments with privacy perception labels was created that can be used to model and quantify the perception of privacy in an acoustic setting; the dataset is publicly available for research purposes. To our knowledge, this is worldwide the first dataset that addresses privacy in human-to-human speech communication. Initial analysis of the data indicates that auditory stimuli from the environment impacts how an individual perceives privacy in that setting. However, exhaustive analysis on this research question is required before drawing further conclusions.

5.7 Publication VII: “Perception of Privacy Measured in a Crowd–Paired Comparison on the Effect of Background Noise”

Figure 5.7. The barplots adapted from Paper VII demonstrate the mean preference scores and the 95% confidence intervals for each scenario pair for the question: *Are you more likely to share a secret, in normal voice, in the acoustic environment A or B?*

The work presented in this paper develops the outcomes and insights from Paper VI by conducting an in-depth analysis of the acoustic features responsible for the quantification of the experience of privacy. We used crowdsourcing to obtain a large sample of responses. We employed two verification questions to screen out unreliable responses, following which we performed consistency checks to ensure that the remaining respondents were consistent. While the responses to certain questions seemed subjective, we demonstrate that scenarios with large differences in the quality of the background noise, such as a coffee shop and home scenario have a significant difference in the ratings. Furthermore, while a pre-tree model illustrates a better fit to the question on the likelihood of sharing a secret, the Bradley-Terry-Luce probabilistic choice model worked better for questions addressing loudness and eavesdropping. Finally, we observe that the presence of speech or babble in background noise is a deciding factor on the grouping of the acoustic scenarios. A snippet of the results from the paper is depicted in Fig. 5.7.

This article demonstrates the role and nature of background noise in influencing an individual’s perception of how private an environment is. By addressing privacy in speech communication, this work helps in designing more robust speech technology. To create a controlled experiment and remove factors of variability within an acoustic scenario, the noisy scenarios were simulated by combining clean speech with additive and reverberant environmental noise. In future studies, it will be worthwhile to explore how the observations in this paper translate to real-world noisy

scenarios.

6. Conclusions

If I have seen further it is by
standing on the shoulders of
giants.

Isaac Newton

Interaction with technology and computers is going through a transition towards more user-centric and natural modes of communication using speech and language, as in speech user interfaces. Everyday devices such as smart-watches and television sets equipped with microphones are deemed common and the demand for and adoption of smart speakers is increasing. This transition is enabled by the recent development and improved scalability of speech processing algorithms, along with the reduced size and cost of sensors. It is further propelled by promising technology such as acoustic sensor networks and virtual microphone arrays. While these developments are positive, new sets of challenges have emerged for the research community. In this thesis, we address problems related to speech and audio coding in multi-microphone networks and privacy in speech interfaces.

To enable speech and audio coding in an acoustic sensor network (ASN) where the sensors transmit coded speech to a fusion center or decoder, we expect that sensors within the network will be constrained in terms of computational resources and power. This means that complex parts of the algorithms will need to reside in a decoder and this includes algorithms that not only decode and combine the signals from multiple microphones, but also postfiltering and enhancement algorithms. Furthermore, reducing the bandwidth by avoiding the transmission of overhead and side information could be another way to meet the resource constraints of such systems.

We approach these conditions by first exploring and developing postfilters for speech coding in single-microphone systems that incorporate speech source models within the framework. The models are trained offline and the adaptive parts of the models are inferred at the decoder from the received signals. This approach saves bandwidth because we do not need to transmit the parameters of the speech model. Additionally, since the postfilter is applied only in the decoder, without any functional blocks necessary at the encoder, this reduces the overall complexity of coding in an ASN. In Articles I and II we modeled speech signals by using the context

neighborhood around the frequency bin of interest. The understanding of that speech signal is comprised of slowly varying parts, i.e. the spectral envelope, and that information can be captured from the surrounding bins in a time-frequency representation. Therefore, modeling the context neighborhood means we are implicitly modeling the spectra of speech, a result which is discussed in Paper II. While the results indicate that postfilters incorporating spectral envelope models improve the output signal quality by an average of 2 dB, the estimated signals were smoother. In other words, the harmonic structure was smoothed out in the postfiltered signal. Hence, in Article III we focused on developing a postfilter that employs harmonic models of speech. The resulting postfiltered signals demonstrate a more pronounced harmonic representation, especially at lower frequencies.

In Paper IV, we employed the method of modeling speech using a truncated distribution that was introduced in Paper II to a multi-mic setup, by distributing the bandwidth across microphones. The combined signal at the decoder was then of better quality relative to a single microphone encoding with full bandwidth. In contrast to related work in the field, the proposed method in this paper allows the exact modeling of the quantization noise, enabled by the truncated Gaussian distribution. Motivated by the results in Papers I, II and III, we advance this work by incorporating speech models, and this is presented in Paper V. The average objective scores indicate a consistent improvement in the model-based postfilter with respect to the corrupted signal and the reference methods. The presented subjective evaluation demonstrates the speech distortion, background noise and the overall quality, and brings forth the classic trade-off between noise reduction versus speech distortion.

There are a few open questions on single- and multi-microphone postfilters that need to be addressed. On the topic of model-based postfilters, we observed that it is particularly difficult to model higher frequencies. One reason could be that at higher frequencies the harmonic components are not only lower in magnitude, but are also relatively out of phase. Using a loss function based on expectation averages out the harmonic structure and yields a smoothed envelope-like estimate at high frequencies. Addressing this would likely improve the perceptual quality of the estimates. Additionally, the harmonic models currently used do not use any inter-frame information on the progression of the harmonic structure. We expect that by employing information on the temporal evolution of the harmonic structure, not only will we have a more accurate speech model, this approach could also improve the harmonic structure at high frequencies. Lastly, despite testing the proposed methods on scenarios with reverberation in Papers IV and V, the signal models assume additive noise only. As a result, while the methods showed some improvement concerning the output quality of the signals with reverberation, the improvement was

much lower relative to the improvement observed in the additive noise scenario. I believe that by modifying the signal model to accommodate reverberation, the performance of the proposed methods can be further improved in scenarios with reverberation.

In the final parts of this thesis, we work on privacy issues in speech user interfaces. We focus on instilling an understanding of privacy in speech interfaces, i.e., based on human-to-human speech communication. From our daily experiences, we know that humans have an intrinsic understanding of privacy, which we use in everyday speech conversation. We begin by investigating if cues on privacy are encoded within an acoustic environment. In Paper VI, we present a corpus which quantifies the level of privacy in audio signals for acoustic scenarios. A preliminary analysis also demonstrate that auditory stimuli have an impact on the perception of privacy of an individual. A deeper analysis of this study with a larger sample size was conducted in the following Paper VII and indicates that the characteristics of the background noise in an acoustic scenario influence the perception of privacy. For instance, there was a significant difference between how people rated the studied coffee shop and home scenarios. The larger goal of investigating and gaining insight into how individuals manage the perception of privacy in speech communication is to use the insights gained to develop models that can be used in speech interfaces. The corpus from Paper VI and the analysis results from Paper VII present the basic tools to develop machine learning algorithms that adapt the privacy setting in speech interfaces based on the acoustic scenario it records.

The publications in this thesis present contributions for robust and efficient distributed speech processing, towards the larger goal of advancing speech communication to more user-centric models of interaction. This thesis specifically focuses on aspects of enhancement in speech coding and privacy in speech interfaces. In general, within the technological landscape the author hopes for a more egalitarian evolution in speech technology, one that is sustainable in terms of resources, empathetic towards the personal preferences of individuals and inclusive over all differences and barriers that exist in the world today.

References

- [Atal et al., 1991] Atal, B. S., Cuperman, V., and Gersho, A. (1991). *Advances in speech coding*, volume 114. Springer Science & Business Media.
- [Bäckström, 2020] Bäckström, T. (2020). Personal communication.
- [Bäckström et al., 2020] Bäckström, T., Brüggemeier, B., and Fischer, J. (2020). Privacy in speech interfaces. *VDE ITG news*, pages 11–14.
- [Bayardo and Agrawal, 2005] Bayardo, R. J. and Agrawal, R. (2005). Data privacy through optimal k-anonymization. In *21st International conference on data engineering (ICDE’05)*, pages 217–228. IEEE.
- [Benesty and Huang, 2011] Benesty, J. and Huang, Y. (2011). A single-channel noise reduction MVDR filter. In *2011 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pages 273–276. IEEE.
- [Bruhn et al., 2015] Bruhn, S., Pobloth, H., Schnell, M., Grill, B., Gibbs, J., Miao, L., Järvinen, K., Laaksonen, L., Harada, N., Naka, N., et al. (2015). Standardization of the new 3gpp evs codec. In *2015 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pages 5703–5707. IEEE.
- [Cavoukian, 2009] Cavoukian, A. (2009). Privacy by design. *Office of the Information and Privacy Commissioner*.
- [Chen and Gersho, 1995] Chen, J.-H. and Gersho, A. (1995). Adaptive postfiltering for quality enhancement of coded speech. *IEEE Transactions on Speech and Audio Processing*, 3(1):59–71.
- [Chiba et al., 2014] Chiba, H., Kamamoto, Y., Moriya, T., Harada, N., Miyabe, S., Yamada, T., and Makino, S. (2014). Adaptive post-filtering controlled by pitch frequency for celp-based speech coder. In *2014 48th Asilomar Conference on Signals, Systems and Computers*, pages 838–842. IEEE.
- [Disch et al., 2016] Disch, S., Niedermeier, A., Helmrich, C. R., Neukam, C., Schmidt, K., Geiger, R., Lecomte, J., Ghido, F., Nagel, F., and Edler, B. (2016). Intelligent gap filling in perceptual transform coding of audio. In *Audio Engineering Society Convention 141*. Audio Engineering Society.
- [Engel et al., 2019] Engel, J., Gu, C., Roberts, A., et al. (2019). DDSF: Differentiable digital signal processing. In *International Conference on Learning Representations*.
- [ETSI-TS-103-634, 2019] ETSI-TS-103-634 (2019). Low complexity communication codec plus. *ETSI*.
- [ETSI-TS-126-445, 2015] ETSI-TS-126-445 (2015). Codec for enhanced voice services (evs): Detailed algorithmic description. *ETSI*.

- [Fant, 1981] Fant, G. (1981). The source filter concept in voice production. *STL-QPSR*, 1(1981):21–37.
- [Fastl and Zwicker, 2006] Fastl, H. and Zwicker, E. (2006). *Psychoacoustics: facts and models*, volume 22. Springer Science & Business Media.
- [Flanagan, 2013] Flanagan, J. L. (2013). *Speech analysis synthesis and perception*, volume 3. Springer Science & Business Media.
- [Fuchs et al., 2015] Fuchs, G., Helmrigh, C. R., Marković, G., Neusinger, M., Ravelli, E., and Moriya, T. (2015). Low delay LPC and MDCT-based audio coding in the evs codec. In *2015 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pages 5723–5727. IEEE.
- [Goodfellow et al., 2014] Goodfellow, I. J., Pouget-Abadie, J., Mirza, M., Xu, B., Warde-Farley, D., Ozair, S., Courville, A., and Bengio, Y. (2014). Generative adversarial nets. In *Proceedings of the 27th International Conference on Neural Information Processing Systems-Volume 2*, pages 2672–2680.
- [Grancharov et al., 2007] Grancharov, V., Plasberg, J. H., Samuelsson, J., and Kleijn, W. B. (2007). Generalized postfilter for speech quality enhancement. *IEEE transactions on audio, speech, and language processing*, 16(1):57–64.
- [Haykin, 2008] Haykin, S. S. (2008). *Adaptive filter theory*. Pearson Education India.
- [Helmrigh et al., 2015] Helmrigh, C. R., Niedermeier, A., Disch, S., and Ghido, F. (2015). Spectral envelope reconstruction via IGF for audio transform coding. In *2015 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pages 389–393. IEEE.
- [Herre and Dick, 2019] Herre, J. and Dick, S. (2019). Psychoacoustic models for perceptual audio coding—a tutorial review. *Applied Sciences*, 9(14):2854.
- [ITU-R-BS1534-3, 2014] ITU-R-BS1534-3 (2014). Method for the subjective assessment of intermediate quality level of audio systems. *International Telecommunication Union Radiocommunication Assembly*.
- [ITU-T-G718, 2008] ITU-T-G718 (2008). G. 718, frame error robust narrow-band and wideband embedded variable bit-rate coding of speech and audio from 8–32 kbit/s. *International Telecommunication Union (ITU)*.
- [ITU-T-P808, 2018] ITU-T-P808 (2018). Subjective evaluation of speech quality with a crowdsourcing approach. *ITU-T recommendation*.
- [ITU-T-P835, 2003] ITU-T-P835 (2003). Subjective test methodology for evaluating speech communication systems that include noise suppression algorithm. *ITU-T recommendation*.
- [ITU-T-P861, 1996] ITU-T-P861 (1996). Objective quality measurement of telephone-band (300 - 3400 hz) speech codecs. *ITU-T recommendation*.
- [ITU-T-P862, 2001] ITU-T-P862 (2001). Perceptual evaluation of speech quality (pesq): An objective method for end-to-end speech quality assessment of narrow-band telephone networks and speech codecs. *ITU-T recommendation*.
- [ITU-T-P863, 2018] ITU-T-P863 (2018). Perceptual objective listening quality prediction. *ITU-T recommendation*.
- [ITU-T-Software-Tool, 2009] ITU-T-Software-Tool (2009). ITU-T software tool library 2009 user’s manual. *ITU-T*.

- [Jayant and Ramamoorthy, 1986] Jayant, N. and Ramamoorthy, V. (1986). Adaptive postfiltering of 16 kb/s-adpcm speech. In *ICASSP'86. IEEE International Conference on Acoustics, Speech, and Signal Processing*, volume 11, pages 829–832. IEEE.
- [Jelinek et al., 2004] Jelinek, M., Salami, R., Ahmadi, S., Bessette, B., Gournay, P., and Laflamme, C. (2004). On the architecture of the cdma2000/spl reg/variable-rate multimode wideband (vmr-wb) speech coding standard. In *2004 IEEE International Conference on Acoustics, Speech, and Signal Processing*, volume 1, pages I–281. IEEE.
- [Korse et al., 2020] Korse, S., Gupta, K., and Fuchs, G. (2020). Enhancement of coded speech using a mask-based post-filter. In *ICASSP 2020 - 2020 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pages 6764–6768.
- [Kuikkaniemi et al., 2014] Kuikkaniemi, K., Poikola, A., and Pitkänen, O. (2014). My data fueling wellbeing applications. In *Proceedings of the 2014 Workshops on Advances in Computer Entertainment Conference*, pages 1–2.
- [Leroy et al., 2019] Leroy, D., Coucke, A., Lavril, T., Gisselbrecht, T., and Dureau, J. (2019). Federated learning for keyword spotting. In *ICASSP 2019-2019 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pages 6341–6345. IEEE.
- [Lim and Oppenheim, 1979] Lim, J. S. and Oppenheim, A. V. (1979). Enhancement and bandwidth compression of noisy speech. *Proceedings of the IEEE*, 67(12):1586–1604.
- [Loizou, 2013] Loizou, P. C. (2013). *Speech enhancement: theory and practice*. CRC press.
- [Martin, 1994] Martin, R. (1994). Spectral subtraction based on minimum statistics. *Proceedings of the European Association for Signal Processing*, 6(8).
- [Martin, 2001] Martin, R. (2001). Noise power spectral density estimation based on optimal smoothing and minimum statistics. *IEEE Transactions on speech and audio processing*, 9(5):504–512.
- [Mohri et al., 2019] Mohri, M., Sivek, G., and Suresh, A. T. (2019). Agnostic federated learning. In *International Conference on Machine Learning*, pages 4615–4625. PMLR.
- [Narayanan and Shmatikov, 2008] Narayanan, A. and Shmatikov, V. (2008). Robust de-anonymization of large sparse datasets. In *2008 IEEE Symposium on Security and Privacy (sp 2008)*, pages 111–125. IEEE.
- [Narayanan and Wang, 2013] Narayanan, A. and Wang, D. (2013). Ideal ratio mask estimation using deep neural networks for robust speech recognition. In *2013 IEEE International Conference on Acoustics, Speech and Signal Processing*, pages 7092–7096. IEEE.
- [Neuendorf et al., 2012] Neuendorf, M., Multrus, M., Rettelbach, N., Fuchs, G., Robilliard, J., Lecomte, J., Wilde, S., Bayer, S., Disch, S., Helmrich, C., et al. (2012). Mpeg unified speech and audio coding-the ISO/MPEG standard for high-efficiency audio coding of all content types. In *Audio Engineering Society Convention 132*. Audio Engineering Society.
- [Nissenbaum, 2004] Nissenbaum, H. (2004). Privacy as contextual integrity. *Wash. L. Rev.*, 79:119.
- [Ohm, 2009] Ohm, P. (2009). Broken promises of privacy: Responding to the surprising failure of anonymization. *UCLA l. Rev.*, 57:1701.

- [Pascual et al., 2017] Pascual, S., Bonafonte, A., and Serrà, J. (2017). Segan: Speech enhancement generative adversarial network. *Proc. Interspeech 2017*, pages 3642–3646.
- [Petronio, 2002] Petronio, S. (2002). *Boundaries of privacy: Dialectics of disclosure*. Suny Press.
- [Raitio et al., 2010] Raitio, T., Suni, A., Pulakka, H., Vainio, M., and Alku, P. (2010). Comparison of formant enhancement methods for hmm-based speech synthesis. In *Seventh ISCA Workshop on Speech Synthesis*.
- [Ramamoorthy and Jayant, 1984] Ramamoorthy, V. and Jayant, N. S. (1984). Enhancement of adpcm speech by adaptive postfiltering. *AT&T Bell Laboratories Technical Journal*, 63(8):1465–1475.
- [Rix et al., 2001] Rix, A. W., Beerends, J. G., Hollier, M. P., and Hekstra, A. P. (2001). Perceptual evaluation of speech quality PESQ-a new method for speech quality assessment of telephone networks and codecs. In *2001 IEEE International Conference on Acoustics, Speech, and Signal Processing. Proceedings (Cat. No. 01CH37221)*, volume 2, pages 749–752. IEEE.
- [Sawada et al., 2011] Sawada, H., Kameoka, H., Araki, S., and Ueda, N. (2011). New formulations and efficient algorithms for multichannel NMF. In *2011 IEEE Workshop on Applications of Signal Processing to Audio and Acoustics (WASPAA)*, pages 153–156. IEEE.
- [Sawada et al., 2013] Sawada, H., Kameoka, H., Araki, S., and Ueda, N. (2013). Multichannel extensions of non-negative matrix factorization with complex-valued data. *IEEE Transactions on Audio, Speech, and Language Processing*, 21(5):971–982.
- [Schmidt and Neukam, 2016] Schmidt, K. and Neukam, C. (2016). Low complexity tonality control in the intelligent gap filling tool. In *2016 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pages 644–648. IEEE.
- [Shi et al., 2016] Shi, W., Cao, J., Zhang, Q., Li, Y., and Xu, L. (2016). Edge computing: Vision and challenges. *IEEE Internet of things journal*, 3(5):637–646.
- [Taal et al., 2010] Taal, C. H., Hendriks, R. C., Heusdens, R., and Jensen, J. (2010). A short-time objective intelligibility measure for time-frequency weighted noisy speech. In *2010 IEEE International Conference on Acoustics, Speech and Signal Processing*, pages 4214–4217.
- [Valin, 2018] Valin, J.-M. (2018). A hybrid DSP/deep learning approach to real-time full-band speech enhancement. In *2018 IEEE 20th international workshop on multimedia signal processing (MMSp)*, pages 1–5. IEEE.
- [Valin et al., 2020] Valin, J.-M., Isik, U., Phansalkar, N., Giri, R., Helwani, K., and Krishnaswamy, A. (2020). A perceptually-motivated approach for low-complexity, real-time enhancement of fullband speech. *arXiv preprint arXiv:2008.04259*.
- [Valin and Skoglund, 2019] Valin, J.-M. and Skoglund, J. (2019). A real-time wideband neural vocoder at 1.6 kb/s using LPCNet. In *Interspeech*. International Speech Communication Association.
- [Valin et al., 2012] Valin, J.-M., Vos, K., and Terriberry, T. (2012). Definition of the opus audio codec. *IETF, September*.

- [Wang and Viterbo, 2003] Wang, Y. and Viterbo, M. (2003). Modified discrete cosine transform: Its implications for audio coding and error concealment. *Journal of the Audio Engineering Society*, 51(1/2):52–61.
- [Wilson et al., 2008] Wilson, K. W., Raj, B., Smaragdis, P., and Divakaran, A. (2008). Speech denoising using nonnegative matrix factorization with priors. In *2008 IEEE International Conference on Acoustics, Speech and Signal Processing*, pages 4029–4032. IEEE.
- [Yeasmin et al., 2020] Yeasmin, F., Das, S., and Bäckström, T. (2020). Privacy analysis of voice user interfaces. *27th IEEE Conference of Open Innovations Association FRUCT*.
- [Yoshioka et al., 2019] Yoshioka, T., Chen, Z., Dimitriadis, D., Hinthorn, W., Huang, X., Stolcke, A., and Zeng, M. (2019). Meeting transcription using virtual microphone arrays. Technical Report MSR-TR-2019-11, Microsoft. Revised version.
- [Zahedi et al., 2015a] Zahedi, A., Østergaard, J., Jensen, S. H., Bech, S., and Naylor, P. (2015a). Audio coding in wireless acoustic sensor networks. *Signal Processing*, 107:141–152.
- [Zahedi et al., 2015b] Zahedi, A., Østergaard, J., Jensen, S. H., Naylor, P., and Bech, S. (2015b). Coding and enhancement in wireless acoustic sensor networks. In *2015 Data Compression Conference*, pages 293–302. IEEE.
- [Zarazaga et al., 2020] Zarazaga, P. P., Bäckström, T., and Sigg, S. (2020). Acoustic fingerprints for access management in ad-hoc sensor networks. *IEEE Access*, 8:166083–166094.
- [Zhao et al., 2018] Zhao, Z., Elshamy, S., Liu, H., and Fingscheidt, T. (2018). A cnn postprocessor to enhance coded speech. In *2018 16th International Workshop on Acoustic Signal Enhancement (IWAENC)*, pages 406–410.
- [Zhao et al., 2018] Zhao, Z., Liu, H., and Fingscheidt, T. (2018). Convolutional neural networks to enhance coded speech. *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, 27(4):663–678.

Computers and technology are so deeply embedded in our lives today that people invest a considerable part of their day communicating with technology. Conventional modes of human-technology interaction have predominantly been device-centric, due to which the users are required to be in the vicinity of the device. This can become cumbersome as the number of personal devices owned by an individual increases. A recent positive trend is the evolution towards user-centric modes of communication with technology enabled by the growing use and adoption of speech user interfaces. Furthermore, developments in the field of virtual and ad-hoc microphone networks and sensor technology are supporting this evolution. As a result, speech processing methods are moving towards a more distributed and collaborative approach. However, this has resulted in new challenges and technical problems in managing speech enhancement, coding and user privacy in acoustic sensor networks. The objectives of this work are two-fold: (1) to develop methods to enable the advancement of conventional speech coding for multiple microphones, (2) to understand the state of privacy in speech-user interfaces. In the first part we study and develop postfilters for coding with the final goal of advancing the postfilters to enable conventional speech and audio coding methods in distributed microphone networks and in the second part, we address how to instill smart speech interfaces with an intuitive understanding of user privacy preferences.

ISBN 978-952-64-0575-9 (printed)
ISBN 978-952-64-0576-6 (pdf)
ISSN 1799-4934 (printed)
ISSN 1799-4942 (pdf)

Aalto University
School of Electrical Engineering
Signal Processing and Acoustics
www.aalto.fi

**BUSINESS +
ECONOMY**

**ART +
DESIGN +
ARCHITECTURE**

**SCIENCE +
TECHNOLOGY**

CROSSOVER

**DOCTORAL
DISSERTATIONS**